

13



Europäisches Patentamt  
European Patent Office  
Office européen des brevets

11

Publication number:

0 317 465  
A2

12

## EUROPEAN PATENT APPLICATION

21 Application number: 88480030.1

61 Int. Cl.<sup>4</sup>: G 06 F 1/00  
G 06 F 3/023

22 Date of filing: 13.09.88

30 Priority: 18.11.87 US 122295

43 Date of publication of application:  
24.05.89 Bulletin 89/21

84 Designated Contracting States: DE FR GB

71 Applicant: International Business Machines  
Corporation  
Old Orchard Road  
Armonk, N.Y. 10504 (US)

72 Inventor: Allen, LindaMay Patterson  
705 14th St. N.E.  
Rochester MN 55904 (US)

Elshaug, Ronald George  
5601 North Highway 63 Lot No.65  
Rochester MN 55904 (US)

Harney, Carrie Lynn  
1856 Terracewood Drive N.W.  
Rochester MN 55901 (US)

Rollings, Glen Everett  
1537 Kings Court, S.E.  
Rochester MN 55904 (US)

Lemmon, Wayne Lawrence  
2227 14th Avenue N.W.  
Rochester MN 55901 (US)

Nordstrom, Michael Lawrence  
715 6th Street S.W.  
Oronoco, MN 55960 (US)

Miller, Irwin  
1440 Willow Lane S.W.  
Rochester MN 55902 (US)

Schablitsky, James Allen  
Rte 1, Box 102  
Kasson MN 55944 (US)

Steinman, Anthony Victor  
1412 Windsor Chase Drive S.W.  
Rochester MN 55902 (US)

Shanklin, Johnnie Dean  
2115 8th Avenue N.E.  
Rochester MN 55904 (US)

Taylor, Deanna Christine  
2630 11th Avenue N.W.  
Rochester MN 55901 (US)

Walberg, Darrel Clifford  
404 24th Street S.W.  
Rochester MN 55902 (US)

Miller, Irwin Jonel  
RR 1, Box 639  
Pine Island MN 55963 (US)

Suther III, Thomas Wilson  
Box 299  
Oronoco Minnesota 55960 (US)

Wojtczak, Eugene Paul  
510 26th Street  
N.W. Rochester Minnesota 55901 (US)

Murray, Gerald David  
1817 16th Street  
N.W. Rochester Minnesota 55901 (US)

Peterson, LaVern Fred  
2108 9th Street  
N.E. Rochester Minnesota 55904 (US)

74 Representative: Vekemans, André  
Compagnie IBM France Département de Propriété  
Intellectuelle  
F-06610 La Gaude (FR)

BEST AVAILABLE COPY

5



## Description

## CUSTOMIZED INSTRUCTION GENERATOR

The invention relates to instructions for installing and changing systems, and in particular to the generation of instructions for installing and changing or upgrading systems.

Computer systems are made up of multiple components which a customer may be required to assemble. Sometimes, a customer may desire to expand a computer system, and may be required to add components. The assembly or addition of components usually requires the placing of components in the correct physical position relative to other components and the cabling of the components together. It can be a complex task depending on the number of components making up the computer system.

Prior computer systems have been shipped to customers with instruction manuals for installation and upgrade. The instruction manuals may provide instructions for most of the components of a basic system, and may make reference to further instruction manuals relating to still more components. An example may be seen by looking at personal computers, where one component is the personal computer box containing a system board and a card for interfacing to a monitor. Another component is the monitor, and the customer is required to connect a cable between the monitor and the computer box. If the customer orders a disk drive device, a separate instruction manual may be needed, or a section in the manual for the computer box must be found in order to determine how to install the disk drive. The disk drive may consist of two components, such as a controller card and the drive itself. There may also be a need to set switches in both the system board and the controller card, with the switch setting being dependent on the rest of the components of the system and size of the drive. This procedure can be quite confusing when multiple options must be installed, or replacement components are required. A customer must search for the appropriate manual to determine how to install the option.

New computer systems in the mid range are much more complex to install than the simple example given above. The system may be made up of one or more racks into which a large variety of cards and devices are installed. The number of options available to customers in ordering such systems is so great that no two systems ordered may look alike, and be installable in the same manner. The use of a generic installation guide is not feasible. If an installation guide set forth instructions in order for one such system, installation of another, different system would cause skipping back and forth between sections of the guide during installation. Further, the guide would be extremely large if it provided sufficient detail for one to successfully install all possible varieties of system.

Customized instructions for a computer system installation or change are generated by an instruction generator program. A system description file describes a desired set of hardware components for

the computer system. Each of the components is broken down by the generator into one or more installation tasks, and the tasks are sequenced in a desired order for installation of the components. The sequence of tasks is then assembled into an installation guide which is customized to each system.

The sequencing of the installation tasks is done by an expert system, which incorporates knowledge of installation experts into a series of rules. The experts have defined a detailed sequence of goals with associated tasks. The expert system sorts on the goals according to the list of desired components. It provides a list of all tasks required, sequenced in proper order.

The installation guide is put together using detailed graphic modules and text modules associated with the tasks, making installation of or change to a system very easy. Line drawings which are modified dependent on the components to be installed are also provided in the installation guide. Since the instructions are specifically tailored to the system which is to be installed or changed, all of the instructions are applicable. The instructions may be followed straight through to completion of the installation or change, thus drastically reducing the time and skill level required to install a system.

Since each task is described using its own graphic and text modules, an engineering change is not nearly as significant an event to the people involved in generating installation instruction manuals. In the past, an engineering change after the manuals were printed would result in either a reprinting of the manuals, or at the least an insert to the manuals. With the present invention, a few modules of text, and or graphics are revised. Since the instructions are generated uniquely for each installation or upgrade, the changes will automatically be incorporated in instructions generated after the changes. Once the system is installed or upgraded, the instructions are thrown away as each further change to the system will be described uniquely in a new set of instructions which is likely much smaller than the original set of instructions. There is no huge stockpile of manuals which need to be changed due to engineering changes.

The detail of instructions is also easily controlled. In one preferred embodiment, a very detailed level of instructions is generated. The graphics modules are very detailed, and are integrated with detailed text modules which refer to the graphics. In testing of instructions generated at this detail, it was found that a person with no prior installation skills could install a system in under an hour, where with prior art instructions some prior skills were usually required to even complete the installation. In further preferred embodiments, the instructions are drastically shortened for those which already have installation skills. One need merely have two sets of text and graphics modules to accomplish a variation in the skill level of the instructions generated.

Fig. 1 is a block flow diagram of the facilities used to generate a detailed installation guide in accordance with the invention.

Fig. 2 is a more detailed block flow diagram of the flow in Fig. 1.

Figs. 3a through 3c are descriptions of topology file records which describe different types of components.

Figs. 4a through 4e are descriptions of element description file records, which provide further information describing components.

Fig. 5 is a description of component task file records which identify tasks associated with a component.

Fig. 6 is a description of intermediate file record which identifies tasks and contains a field for a representation of the sequence in which a task is to be performed.

Figs. 7a through 7j are tabular representations of translate table files which provide detailed positional and instruction presentation information for, and graphic artwork associated with, each task.

Fig. 8 is a description of a hardware handling file, which identifies each sequenced task, and components associated with the tasks.

Figs. 9a-9d when placed end to end are a logic flow diagram of a task identifier routine which identifies tasks associated with a component.

Figs. 10a - 10c when placed end to end are a flow diagram of a sequencer for sequencing the tasks identified in Figs. 9a-9d.

Fig. 11 is a flow diagram of a translator program which associates specific modules of text and graphics with the tasks.

Figs. 12a and 12b when placed end to end are a flow diagram of a task to graphics manager for generating line drawings and a script file for the customized instructions.

#### Appendix List:

Appendix I is a description of records and an alphanumerical listing of names of fields used for these records, including definitions of the fields.

Appendix II is a compilation of English rules used by the sequencer of Figs. 10a - 10c in sequencing the tasks in a correct order for installation.

Appendix III is a list of variables and switches corresponding to selected tasks.

Appendix IV is a task summary table which lists tasks and task variations with corresponding components of the system.

Appendix V is a topology file for an order referred to as "0630100" and includes further files shown in Fig. 2 as well as the resulting installation instructions produced for that order.

In Fig. 1, a flow diagram indicated generally at 10 provides an overview of a system for generating detailed, customized installation instructions for the installation, change, and upgrade of a computer system. A topology file is provided by a topology file

generator block 12. The topology file is a list of hardware components making up a computer system. The components are preferably items such as processor cards, equipment racks, cables, power supplies, disk drives, and I/O controllers etc.. While the invention is applicable to components at a much more detailed level, such as nuts and screws, one of the objects of the invention is to make installation of a computer system easily performable by a customer where a customer is an end user, service engineer or value added retailer. The components were chosen at a level of granularity consistent with what different customers might desire to select.

The topology files contain placement and connection information for each component. In the instance of a component to be installed in an equipment rack, it identifies a slot in the equipment rack, and what the component is connected to. When a customer wishes to change an existing system for varying reasons including replacement of components or addition of components, two topology files are provided by file generator 12. The first file being a current configuration, and the second file being an upgraded configuration.

A receiver/splitter/router 14 receives multiple topology files from the topology file generator 12. Several topology files may be received corresponding to different system installations and upgrades. In the preferred embodiment, several topology files of systems to be built or upgraded are processed in a batch job. The receiver/splitter/router 14 is a conventional program that receives batches of topology files from the topology file generator 12 and splits the batch into individual topology files for initial installations, or into pairs of files for an upgrade of an existing system.

Topology files are sent from the receiver/ splitter/ router 14 to a task generator/sequencer program 16. The sequencing program 16 is a blend of conventional software technology and expert system software technology. In processing a topology file or topology file pair, parentage of components is established and a number of installation tasks are identified, sequenced and formatted into a hardware handling file. Tasks are small units of work required to install or update a system. The expert system software is used to sequence the tasks.

The hardware handling file is passed on to a task to graphics interface manager 18 which creates customized line drawings, and sets up variables and generates a master script imbed file for scripting and printing. Variables are values of items being specified in the text of instructions, such as: "set address to ". Each variable is unique to a task and its associated component.

The line drawings and variables are integrated with selected text module names and graphics modules to create a master script imbed file.

The master script imbed file is passed on to a script manager program 20, which selects the graphics and text modules identified, and generates a formatted print file of complete, system unique, installation instructions. The instructions contain text and graphics in line with each other. A graphics print manager 22 routes the formatted print file to a



graphics printer 24.

In Fig. 2, a more detailed block diagram of the instruction generating system is shown. The elements in the diagram will first be described in terms of the data it receives and the data that it produces. The manner in which the elements perform the data manipulations will be described later.

#### Topology Files

The process of generating installation instructions for a particular system installation or upgrade of a system starts with one or two topology files at 40. As previously defined, the topology files contain lists of components or elements of the system. The lists are preferably generated by an expert system configurator, such as that shown in U.S. Patent No. 4,591,983. The configurator is used during initial order placement for a new system by the manufacturer of the system. A customer will order a particular model number and several options from standard literature about the computer system. The configurator will check the validity of the system and will generate the lists which include information on the physical placement of components and their connection to each other. If a customer has not specified required components, such as the case where a disk drive is specified, but the essential controller for that drive was not specified, the configurator will add it. In other embodiments, a human expert will provide the topology file based on the customer order. The human expert can provide the same topology file, but may not be able to process the volume that the expert system can.

A single topology file is used for defining the elements of a new installation. When an upgrade of an existing system is to be performed, a current topology file is first generated which describes the elements of the system as it presently exists. This information is obtained by manually inspecting the system, or preferably, the original topology file for the system as shipped from the factory is stored on the system in permanent storage. The customer will then specify new elements to add to the system, and a second, upgraded topology file is generated by the configurator, or an expert based on the current file and the additional elements ordered.

Examples of the format of records within topology files, and the information contained therein which is utilized in the present invention is shown in Figs. 3a through 3c. In Fig. 3a, a system topology description header record is shown. The header record is shown as a field name and a field descriptive name, and actually consists of a series of fields containing information which describes a system. There is one header record per system which describes customer information and matches a topology file to the customer order. Appendix I provides a more detailed definition of each field based on the field name.

Fig. 3b shows an element record, which describes characteristics of an element such as racks, cards, devices and other elements except cables. It contains version, parentage information, location information and further information associated with each element. There is one element record per element in the topology file. Parentage information

identifies a hierarchy of components. A card cage is the parent of a card. A rack is the parent of a card cage.

Fig. 3c shows a cable record. The cable record identifies a cable, and also defines where it is connected by the use of From and To fields. There is one cable record for every cable in the system.

A task identifier 42 is preferably a procedural software program "layer 2", which receives the topology files 40, identifies tasks associated with the elements described and establishes parentage for each component. The task identifier 42 uses data from an element description file 44 and a component task file 46 and produces an intermediate file 48, which identifies tasks for installing the system.

The format of, and information contained in the element description file 44 is further detailed in Figs. 4a through 4e. File 44 contains further information on all of the elements available to be ordered for a system. Each record provides detailed information of the element or component which is not practicable to be provided in the topology files because of the large storage requirements. Each of the Figs. in the Fig. 4 series of figures describes a type of record which may be used to describe a particular component. Fig. 4a contains release level control information. Fig. 4b contains information relative to device to bill of materials (B/M), and conversion tables which are used for generating a list of parts for cross-checking by the installer or upgrader.

Fig. 4c is a basic element record which all elements have. It provides more detail about the component itself, including part numbers, internal names and physical characteristics.

Figs. 4d and e are used in combination to generate a chart of communication lines to enable a customer to associate a line resource name with particular line characteristics such as communications protocols.

The format of a component task file record 46 is shown in detail in Fig. 5. It contains descriptions of installation tasks which are cross referenced with the component described in the topology file 40 and the element description file 44. Each task file is stored in accordance with the list in Fig. 5, which includes fields identifying the task type to execute, and a number of task identifiers. It also includes fields for defining the amount of time to complete the task, a field for a sequence number of the task in the installation instructions and several other fields.

A TTYPE field represents the type of task. The types are divided into adding a new rack, upgrading a system, removing a component, installing a component and a universal task, which is a task associated with every upgrade or installation.

The first digit represents the type of task being performed: add, remove, modify, or Universal Tasks.

The second digit represents the class of hardware being addressed: RACK, DEVICE, CARD, etc.

A HANCD field identifies the type of handling a component is to receive, such as adding the component, removing the component or moving the component.

A HPCDN field is the unique name for a hardware element as used in software.

An ELMTP field defines the general physical class of a device, such as a tower, a tower mountable unit, a card or a cable. A tower as used here is a rack within which other elements of the computer system are mounted.

An ELMST field defines the logical class of a device within a physical type. The type of tower unit is described, such as disk drives, power interfaces, OEM reserved space... The types of cards and cables are also defined.

A FILL1 field describes an expansion area which is used for future use.

A GROUP field contains a task group flag. It is used to identify tasks that are similar to other tasks and should be performed as a group to cut down the time required to perform them.

TIXRF is a general task cross reference number, and TIGRP specifies a unique number for each task description for an element.

PERSP defines a perspective to take when selecting a group of components to work on for a given task. Several perspectives are available including system, rack, extra, card cage/tail gate and pseudo tasks, which are tasks which are any actions or preparations other than physical tasks to perform an installation such as checking to determine that all components were shipped.

GLSQN is used to define tasks which belong together within a major goal sequencing group.

UPDSQ is used to identify specific goal sequence points when specific tasks should be selected.

STATE defines the particular state of processing certain tasks. It has possible values of first, last, cabling, etc. Cabling is done only if cabling is required.

A DIRET field defines the direction of progressing through different perspectives of a system, rack, card cage etc. It can specify progressing from the highest location to the lowest location or from the lowest location to the highest location. It is used to sequence tasks so they do not interfere with future tasks.

POWST describes whether a system should be powered up or down when performing the task.

SUBCP identifies a particular sub component activity, such as terminator, address switch or voltage switch which is associated with installation of a component.

TCMTM is a field specifying an estimate of the task completion time. TCMTM is the primary time to complete the task, and TCMTA is an alternate time, if the task is in a group of tasks. TCMTA is usually less than TCMTM because it is assumed that performing similar tasks at the same time will reduce the time required per similar task.

MUPID is a model upgrade indicator. It identifies whether a component is related to a model upgrade.

PHPDN contains a descriptive name of the parent device of the component whose installation task is being described.

CABRL describes a cable end relationship to the location of the components the cable attaches to. The values are intra-rack or inter-rack.

HANLR is handler code which identifies whether the customer service person, etc. is doing the

component handling

CINTK identifies tasks which support the physical installation or removal of a component. The values are install task or disassemble task.

5 CLASS determines the values/variables to be set for a task.

SPCLS identifies a special class of values to be set for a task.

FIL15 is a reserved field.

10 The intermediate file 48 consists of a record as indicated in Fig. 6 for each task identified by the task identifier. The record is very similar to the component task file 46 records. The first few fields are exactly the same. Some fields are added from the topology file 40 and the element description file 44. Those are defined below:

TSEQN is a task sequence number. It specifies the task sequence number in relation to other tasks that must be performed.

20 TSKID is a task identification number which determines the task identification to graphics modules, and is made up of TIGRP and TIXRF from the component task file 46.

25 RPERM indicates whether a component is to be removed permanently, or temporarily if removed at all.

HPAGE identifies a hierarchical parentage of the component being handled. ELJL1-4 and LOCL1-4 are an element identifier and location code for a level 1, 2, 3 or 4 component. CORY 2-4 are vertical offsets of a device within a level. Levels refer to parent information. Level 1 is a rack, level 2 is a device, level 3, a card, and level 4 is a cable.

35 CPFC4 identifies a cable's parent feature code number. The feature code number corresponds to the cable's line speed, protocol, connection, and electrical interface.

The sequencer 50 is an expert system software program. It uses installation rules indicated at 52 which are written in expert system code. The rules are expressed as major task sequencing goals and detailed goal listings in Appendix II, the English sequence rules document 53. The goals embody a set of hierarchical rules. The only detailed rule is that the goals must be satisfied sequentially.

Sequencer 50 provides a sequenced intermediate file 54 consisting of records in Fig. 6 with the task sequence number field, TSEQN, filled in for each task. The file is organized with the lowest task sequence number first. The sequenced file 54 is then used by another conventional software program translator 56 to produce a hardware handling file 58. Translator 56 uses a translate table file 60 shown in Fig. 7 which contains multiple tables for translating the tasks obtained from the sequenced intermediate file 54.

The translate tables are used to enlarge the selection of text and/or graphics variations, based on record fields other than device type.

60 If a task requires a translation, it must have an alphabetic character in the second character position of the TIGRP field of the task ID, TSKID field in the intermediate file shown in Fig. 6. A PNLC task, as identified in a TSKID field, is used as an example. The PNLC task directs the installer to find a specified

P/N cable, get 2 labels, write given information on the labels, put the labels on cable ends, select the proper end of the cable and route it into a rack.

The character in the second character position of the TIGRP field of the task ID selects an associated translate chart in the translate table. The actual task ID in this case is PNLC1K. In this case, it is given that the second character is a "K", so Fig. 7a, row 1 is used. The ELMTP and ELMST fields are then examined to select a column of the chart. If the examination yields a B6, the translated task is PNLC122, where 122 is a version of the task for the inbound end of an external workstation cable. The word external is defined as meaning a cable that has only one end inside a given rack.

If the examination of the ELMTP and ELMST fields yielded a B1, the translated task is PNLC1C, and the new character "C" causes a second translation to occur. This time the DVRPQ field is evaluated to select a column in the "C" chart in Fig. 7b. If the evaluation yields 6018, the translated task is PNLC124, which is for the inbound end of an extended CEC-CEU cable. If the evaluation yields blank, then PNLC1P is the translated task, and the port chart "P" is used. The fields used for each chart are indicated next to the charts in the Figures.

Charts in Figs. 7a through 7e correspond to particular text modules to be used for generation of instructions. Graphic charts are similarly expanded in Figs. 7f through 7j, which include charts identifying graphics which are rotated 90 degrees to provide a better view for installation. Further charts refer to port extensions, and switch setting graphics modules.

In Appendix III, task IDs TIGRP, and an abbreviated title are listed in the left column of a table of variables and switches. The variable and switch names are listed across the top of the tables, and the definitions of the names are given on the last page of Appendix III. Tasks which may have one of the variables, are identified with an "X".

In Appendix IV, tasks (TIGRP) are again listed, and this time the rack, device product numbers, and card numbers are listed across the top of a table. The table is filled in with version numbers (TIXRF) of the different versions of text associated with each task dependent on the device, rack or card. With respect to the PNLC task - Label the Cable -previously discussed, one can see that there are multiple versions of the text. 111 is for the outbound end of an external DFCI cable

114 is for the outbound end of an external CEC-CEU cable

121 is for the inbound end of an external DFCI cable

122 is for the inbound end of an external WS cable

123 is for the inbound end of an external COMM cable

124 is for the inbound end of an external CEC-CEU cable

211 is for the first encounter of the outbound end of an internal DFCI cable

214 is for the first encounter of the outbound end of an internal CEC-CEU cable

221 is for the first encounter of the inbound end of an internal DFCI cable

224 is for the first encounter of the inbound end of an internal CEC-CEU cable

Each version has associated graphics/line drawings/lists. 111 uses RSLD208, 209, and 006

114 uses RSLD208, 210, and 202

121 uses RSLD208, 209, and 006

122 uses RSLD011, 208, 270, and 006

123 uses RSLD208, 209, and 006

124 uses RSLD208, 210, and 202

211, 214, 221, and 224 do not have any graphic.

The variables used with this PNLC task are RACK, CBLPN for cable part number, and CBLAB for cable label. These can be found in Appendix III.

An example of a task which uses switches is the PNLC -setup complete - task. Variables CTIE and MRACK are used to tell the installer when to install cable ties. The PNLA variable tells when to pack a hoist adapter tool used to lift some items into place, and the PLNR variable tells the installer to pack the hoist. All covers are closed, and some general housekeeping is identified. Version 100 is for initial install, 300 for upgrade where no reconfiguration is required, and 400 is for and upgrade where reconfiguration is required. Rack is a variable, and MRACK - multiple racks, CTIE - install cable ties, TCAW - more cables to install, PNLA (300/400) -lifter adapter required, and PNLR (300/400) lifter required are switches. All versions of this task use graphics/line drawings/lists RSLD154 and 184.

The hardware handling file 58 is shown in further detail in Fig. 8. Each task is now identified by a hardware handling record. Each record is comprised of the fields indicated in Fig. 8. Most of the fields have been previously identified in references to the element description file 44, the topology file 40, the component task file 46 and the intermediate file 48, from which the hardware handling file is derived. The hardware handling file 58 now contains a detailed set of fields most of which have been previously discussed. Subfields under the field HPAGE identify parentage of the component. The parentage includes what other components the component is attached to in the form of identifiers, ELIL 1-4, CORY 2-4 and a cables parent feature code number CPFC 4.

Some fields not described before include a NCBL field which defines the number of cable ends to sequence, with up to three specifiable. A GRAPHID field is used to identify a graphics module for the instruction guide, and FIL13 identifies further expansion area. The record also includes the STDELEMT record from the topology file of Fig. 3b.

A task to graphic interface manager 64 then uses the hardware handling file 58, and further information from the element description file 44 and the TGIF data file 68.

The TGIF data file 68 is used to create customized line drawing files 72 and a script file 74 which contains names of customized line drawings of racks, card cages, and cable lists, and a sequential set of script module names and variables respectively to control generation of integrated in-line instructions by a task to graphics interface manger executive 80.

Information from the element description files are

used in defining the line drawings. The line drawings are box-like drawings used to depict what an actual system will look like. One example of a line drawing is of a rack, with the devices drawn in as squares and rectangles. Size information for the devices is used to draw the squares and rectangles to size. Names of the devices are also obtained from the element description files, and are inserted into appropriate squares and rectangles. Similar line drawings are used for such things as a card cage, to show the location of cards, with the name of each card.

Script file 74 is simply a list of names or variables corresponding to text files to be incorporated into the instructions. It is based on the tasks identified, and is ordered in the correct sequence for installation of the system. The drawing files 72 are used to define drawings and graphics. Line drawings are used to illustrate things which are unique to each system and which do not require detailed graphics. Some examples as previously mentioned, include a line drawing of a rack, with names of other components positioned to correspond to the physical location of the actual component in the system. They are useful for showing the system before and after an upgrade. A further use is the identification of cards in a rack. The lines already exist, and the names are filled in by task to graphic interface manager 64 dependent on the configuration of the particular system to be installed. Drawing files 72 also include variables to select graphics files.

Text and Graphics sources are indicated at 82 and 84 respectively. The variables contained in the script file 74 and drawing files 72 are used to access the text for instructions and the graphics for the instructions. A composer 80 retrieves the instructions and graphics based on the variables, and integrates them with the customized line drawings to generate a formatted print file of complete, system unique, in-line sequential installation instructions. These are passed on to an all points addressable printer 94 which provides an instruction guide indicated at 94.

In Appendix V, a sample installation guide generated by the instruction generator is presented. Tasks are numbered in the upper left corner. This particular instruction is for a simple system installation. Most of the devices have already been installed in the rack, as seen in the line drawing used in task 3 to verify the content of the rack from the front. A back view of the rack is presented in task 12.

Also in Appendix V, is an updated copy of the translate table, including information used to perform the pseudo task processing block 242 in Fig. 11.

Appendix V shows a topology file consisting of multiple records having the formats identified in Figs. 3a, 3b, and 3c, and corresponding to components for a system. Each row of characters is a record. The first row, where the fourth and fifth digits are "10", is a header record. "10" is in the RCDTP field, which is the record type field. There is only one header record for the topology file. A number in the first row "0630100" corresponding to the SYNUM field, is the system number of the topology file.

The fourth and fifth characters of each record

identify the record type, "40" being an element record, "44" being a cable record, and "60" being a specify record. The next file is the intermediate file for the same system. Each line of alphanumeric characters corresponds to a task identified by the task identifier 42. The format for each task is indicated in Fig. 6.

The hardware handling file for the system is shown next. Again, each task is represented by one line of characters having the format shown in Fig. 8. The script file is shown next in Appendix 5 having script commands such as .SE for setting variables and .IM for imbedding modules. Finally the instructions resulting are shown for the system identified as "0630100".

One can easily trace from the script commands what text and graphics resulted in the instructions. Commands 15-22 resulted in the System Identification, Processor type-model number, and processor serial number being inserted on page 1 of the instructions. The next two commands indicating that TIME = 1.4 and STIM = 1.4 resulted in estimates on page 1 of 1.5 hours to install, and 1.5 hours that the system will not be available during installation. The second time may be less than the first for upgrades, since some tasks may be performed while the system is still running, such as checking to determine if all the components are correct. .1 hours is added to time in the commands for a fudge factor.

Each text module imbedded further imbeds the associated graphics files and line drawings required by the text module.

## PROGRAM FLOWS

### Task Identifier 42

In Figs. 9a through d, a flow diagram is detailed for task identifier 42. Task identifier 42 identifies tasks associated with elements described in topology files. It does this for both upgrades and initial installations, the difference being that two topology files are associated with an upgrade, and task identifier 42 determines which components are to be moved and which are merely to be added. It also establishes parentage for components. Then, it determines the tasks that need to be performed.

Initialization occurs at block 102 in Fig. 9a, including loading the program and allocating required resources. The element description file 44 is then read into an element description table at 104 from secondary storage. The element description file will be used from the element description table rather than from secondary storage to improve performance of the task identifier 42. There are easy references into a table format rather than from a straight file list and no further I/O activity is required.

The component task file 46 is also read at 106. An IDELTA (intermediate file 48) record is written for each "do always" task. "Do always" tasks are included, based on whether an upgrade, initial install or relocate is to be performed. All other tasks are placed into a component task table. At 108, the target element topology file is read from 40 and placed into a topology table. A list of added or moved elements is then built. The target cable

topology file is read at 110, and a list of added or moved cables is built. If the instructions to be generated relate to an upgrade, as determined at 112, the current element and cable topology files (114-116) are read in and further lists of moved or removed elements and cables are determined.

Flow continues in Fig. 9b with initial installation flow starting at 120, and upgrade flow at 122 in separate paths. Much of the function is similar for both paths. Initial installation will be described first. A series of blocks are performed for each rack as indicated at 124. Blocks 126, 128, 130, 132, 134 and 136 select tasks for adding racks, for factory installed devices in new racks and for factory installed cards in new racks for each card in each card cage. Factory simply refers to those components already installed prior to receipt by a customer. For each task, an IDELTA record with parentage is written out. Tasks are also identified for each inter-rack cable starting at 138, 140, and 142, with IDELTA records for each task with parentage being written.

The flow is more complex for upgrades starting at 122 in Fig. 9b. At 144, the lists created in 114, and 116, referred to as a change table, are used to perform steps 146, 148, 150, 152, 154, and 156 on each rack in the change table. Tasks are selected for adding a rack, for factory installed devices in new racks and for each removed rack. An IDELTA record is built for each task with parentage information included, and is written to the intermediate file 48. Starting at 158, the same is done for each device in the change table. Again, at 160, 162, 164, and at 166, tasks for each new field installed or moved device, each removed or moved device, and at 168 and 170 for model changes are selected, with an IDELTA record built and written.

The steps are repeated starting at 172 for each card in the change table. Task selecting and IDELTA record build and writing occurs at 174, 176, 178, 180, 182, and 184 for new field installed cards or each card moved between card cages, for each removed card or for each card moved between cages, and for each card moved within a card cage.

Starting at 186, the same steps are done for cables identified in the change table. At 188, 190, 192, and 194, the IDELTA files are generated and written for removed or moved cables, and for new field installed or moved cables.

At 196, 198, and 200, the IDELTA files are generated and written for each modified device, and at 202, 204, and 206 for each modified rack. At 208, the task identifier 42 is ended, and the sequencer 50 continues with processing of the intermediate file generated by the task identifier.

#### Sequencer 50

As previously stated, sequencer 50 is an expert system software program which uses installation rules indicated at 52. The English language rules embodied in the rules 52 are expressed as major task sequencing goals and detailed goal listings in Appendix II. A short flow diagram is also presented in Fig. 10, which shows initialization at 210 during which, as for any program, external declares, flags,

arrays, file definitions, selectors, and working memory are set up. At block 212, an ON ENTRY expert system rule is done for initialization for further control rules, such as setting a control working memory element flag to "ON". This initialization includes initialization and allocation of working memory into which files will be written.

A REQUEST rule at 214 is a control rule that is executed based on the control working memory element flag being turned "ON". In block 214, a next intermediate file to sequence is read into an area of working memory, and card addresses are calculated. A subroutine RCVRQST, block 218 in Fig. 10c is used to retrieve the next intermediate file's name. REQUEST block 214 is written to process a batch of intermediate files, and after reading each file, the working memory element flag is set "OFF", and SEQUENCE RULES indicated at 215 are executed. Since the sequencing rules are set forth in detail in Appendix II, the flow is abbreviated in Fig. 10a.

After sequence numbers have been assigned, a CLEANUP block 216 in Fig. 10b searches for the lowest sequence numbered record, and writes it into the sequenced intermediate file. After all the records have been found and written, the intermediate file is closed, and flow is returned to REQUEST block 214 for the next intermediate file. If all are done, an ON IDLE block 217 terminates processing of sequencer 50.

In a further embodiment of the expert system software program the task identifier 42 and the formatter 56 are incorporated into the program to form one common program. This eliminates the intermediate files 48 and 54, the delta hardware handling file 58, the TGIF data file 68 and the translation files 60. The task to graphic interface manager 64 is also broken up into routines and pulled into the common program.

The flow is thus modified so that all flags, arrays, and variables associated with the routines pulled into the common program are initialized. On entry, the reading of the element description and component task files is done. The request reads in the topology files into working memory, and calls a new routine to create working memory element tasks. The sequencing rules then sequence the working memory element tasks as before, and a cleanup routine calls the TGIM routines to build the flat drawings from the topology file/working memory elements. Then the cleanup routine then calls the TGIM routing that builds the script imbed file from the working memory element tasks for scripting and printing of the resulting instructions.

The rules in Appendix II precisely define the operation in terms better than that which applicants can envision by means of more detailed flow charts. A shorter statement of the rules follows:

#### Hierarchical Rules:

1. Tasks which can be performed without powering-off the system will precede the tasks which require system power-off.

- a. Load any new code into the system before powering-down the system.

b. If a direct access storage device (DASD) is being removed from the system, instructions on how to 'back-up' the DASD are to be called out and the customer is to be advised to perform that function BEFORE taking the system down to make any changes.

c. If a change will require a system power-down, remove all AC power and remove the line cord from the outlet.

2. Whenever possible, "Remove" tasks will precede "Add" tasks. This rule will facilitate an "Add" at a location previously occupied. (The "Move" task is accomplished by "a Remove followed by an Add".)

3. The task of "Power-On" and related steps will always be last. The only acceptable exceptions are tasks requiring an operational system.

4. A "Perspective" relationship will be established by Text and Graphics. The "Perspective" ordering is:

- a. System perspective.
- b. Rack perspective.
- c. Device perspective.
- d. Card Cage perspective.
- e. Extra perspective.
- f. Pseudo perspective.

5. Whenever possible, "Perspective" related tasks will be group together. (Do all tasks behind the RACK before moving to the front of the RACK)

a. Tasks from a "System" related perspective will have precedence over tasks from a "RACK" related perspective.

- 1) IPL DASD back-up
- 2) RACK Positioning.

b. For multi-RACK upgrades, RACKS will be sequenced beginning with the RACK farthest away from the RACK containing the CEC.

c. For multi-RACK upgrades, tasks relating to the first RACK will be completed before beginning the next RACK in sequence.

6. Within a "perspective area", "positional" sequencing must avoid scheduling tasks that make subsequent tasks more difficult.

a. When doing device REMOVES, work from the top to the bottom.

b. When doing device ADDs, work from the bottom to the top.

c. When doing card REMOVES, work from the right to the left.

d. When doing card ADDs, work from the left to the right.

7. Within "positional" sequencing, "like" tasks should be grouped. (ie-within RACK E, Unlock all DASD shipping clamps.) This rule, when invoked, will temporarily override the "positional:" rule during the sequencing of one task only.

8. Cabling Rules:

- All cables will be treated as two "connect/disconnect cable end" tasks associated with the

appropriate device(s)/card(s).

- All cable tasks must have the cable identified number (EID) supplied in the task text. (This is the same cable identifier number used in the cable chart)

- Intra-RACK cables will be treated as RACK elements. ie - The two "connect cable end" tasks will be consecutively sequenced, following installation of the associated device(s)/card(s).

- For Inter-RACK cables, the two tasks will of necessity fall into separate "perspective" areas. When the initial cable end is installed, the instructions must state that the other end will be installed at a later step.

- For each "Remove cable end" task, if the cable end will not be re-attached before another cable is encountered, suggest that the cable be labeled.

- For each "Install cable end" task, if it is the first end, and the other end will not be installed before another cable is encountered, suggest that the cable be labeled.

Returning to the structure described in Fig. 2, sequencer 50 provides the sequenced intermediate file 54 to the translator 56.

#### TRANSLATOR PROGRAM 56

The translator program 56 flow is shown in Fig. 11. The translator program 56 is used to vary the text and graphics associated with the task. The text and graphics are varied dependent on the particular view desired, which end of a cable, and the type of cable to be installed. Further variation is dependent on the type of view desired in the graphics. Some views are rotated 90 degrees for better view for the installation of a component.

At 220 in the translator program 56 flow, the translation and pseudo task information from the translate table file 60 is read, and put into table form as seen in Fig. 7 for quicker access by the translator program. The pseudo task information is seen in a listing of the translate table file in Appendix V for a further preferred embodiment. A record corresponding to a task is then read from the intermediate file at 222 and it is determined if the last record has been read at 224. Processing is transferred for each record at 226 to a main loop processing section and then the next record is read at 228 and flow returns to 224 to check for the last record.

The main loop processing section starts at 230. Checks are made at 232 and 236 with the resulting actions indicated at 234 and 238. In both cases, nothing is done by the main processing section 230 with the task. If the task cleared the checks at 232 and 236, then cable labeling and table driven pseudo task processing is performed at 240 and 242. This is done substantially as described earlier, using different fields to cross reference into the tables to determine which variations of text and graphics to use for the task. At 244, the hardware handling record is made, and at 246, further translation tables are used to translate the task group's number and complete the graphic identification number, and output the result to the final hardware handling file.



Processing is then returned to 228 at 248.

#### Task to graphics interface manager TGIM 64

The TGIM 64 uses the hardware handling file 58, and further information from the element description file 44 and the TGIF data file 68 to create customized line drawing files 72 and a script file 74 which contains the names of customized line drawings, and a sequential set of script module names and variables to control generation of integrated in-line instructions by the composer 80. The logical flow of the procedural code used is shown in Fig. 12a and 12b.

Following initialization at 250, the IDELTA file is read through at 252 to perform look ahead functions (such as calculating the total installation time and system time, the number of people required, determine the special tools required, etc.).

At 254, an element description file is read into an element description table. Next, the target topology file is read into a target topology table, 256, a loose part list of field installed parts is built at 258, a flat drawing of the card cages is built at 260, both front and back drawings of each rack are built at 262 and 264, and a list of cards in each cage is built. The line drawings are done by building a script file which defines start and end points for lines to create different size boxes dependent on the size of the component. The boxes are then filled in using script commands with information such as name of the component, its location and logical address.

If the instructions are to be for an upgrade, 268, then the sequence of steps from 270 on is performed before flow is merged back together. There are no corresponding steps under 272 for initial install. At 274, the target topology file is read into the target topology table and a table is built at 276 for each element type such as rack, device card and cable. Flat drawings at 278, 280, and 282 are built for card cages and both the front and rear of each rack.

Both initial install and upgrade steps are the same for building charts for various cables at 284, 286, 288, 290, and 292. Finally the TGIM master file is built from the IDELTA file, setting script variables and flags. Flow is ended at 296, with the result being the list of script commands used to generate the customized instructions.

The customized installation instructions, as can be seen in Appendix V are very detailed, and provide even an installer with little technical experience sufficient guidance to install a system very quickly. By customizing the instructions to the particular system to be installed, an installer need not make any cross references to other manuals, thus reducing the chance for confusion and error. Detailed graphics of the components of the system are provided, clearly illustrating each step of the installation process. The line drawings are effectively utilized to give the installer positional information for installing specific components. In some cases, the graphic views are rotated dependent on which view more clearly illustrates the installation steps. Once the system is installed a rack configuration list, and cable list are provided for future reference, and the

installation instructions are thrown away, as they only relate to the installation of the system they were generated for. Further upgrades, modifications, and even system moves will result in a new customized set of instructions detailing the steps involved in adding and removing components or moving the system.

#### Claims

1. A system for identifying tasks associated with installation of a device made up of a variable number of components, characterized in that it comprises :

at least one topology file for identifying desired components for a device, said at least one topology file defining the placement of each component within the device;

a component task file identifying installation tasks corresponding to the possible components in the device;

a task generator coupled to the at least one topology file and to the component task file for generating a list of tasks corresponding to the components in the topology file; and

a sequencer coupled to the task generator for sequencing the tasks in the order they are to be performed for installation of the device.

2. The system of claim 1 wherein each topology file comprises a set of records, each record corresponding to a component, said records being divided into at least five versions comprising:

a rack version for a rack component; a storage media version for storage media components within a rack; Claim 28 Continue

a card cage version for card cage components within the rack;

a card version for card components within a card cage; and

a cable version for cables connecting the racks, card cages and cards.

3. The system of claim 2 wherein the topology file further comprises a representation of the parentage of the storage media, card cages, cards and cables.

4. The system of claim 1 wherein the task generator is coupled to a first topology file for identifying components of an existing computer system, and to a second topology file for identifying components of the modified existing computer system, wherein the task generator further comprises means for determining which components need to be added to the existing computer system, which components need to be moved, and which components need to be removed from the existing device to create the modified existing computer system.

5. The system of claim 1 wherein the component task file further contains representations of pseudo tasks not associated with any

**particular task.**

6. The system of claim 5 wherein the component task file further comprises an estimate of the time for completion of each task.

7. The system of claim 6 wherein the component task file further comprises an estimate of the time for completion of a task when it is performed in conjunction with other like tasks.

8. The system of claim 1 wherein the component task file further comprises a representation of a perspective for a task.

9. The system of claim 1 wherein the task file

further indicates a subcomponent associated with a task, for which a further task is defined.

10. The system of claim 1 wherein the sequencer comprises an expert system program using a set of rules for sequencing the tasks, said rules comprising:

arranging tasks which can be performed with the device powered on first;

grouping tasks which are physically located together into a group to be performed together; and

avoiding scheduling tasks which would make further tasks more difficult.



DOCKET NO. R0987-022

APPENDIX I

Hardware Installation and Removal Services  
Data Dictionary

11/06/87

APPENDIX I

PAGE 1

## HPCS Record Description.

File Name: STSTOPOL Desc Name:-System Topology Description

Record Name: STDHEADR Desc Name: STD Header Record

CHARACTER	ZONE	PACKED	DECIMAL	LENGTH	POSITIONS	FIELD NAME	FIELD DESCRIPTIVE NAME
FR	TO						
X				3	001-003	ELMID	Element Identifier
X				2	004-005	RCDTP	Record Type
X				4	006-009	IDSYS	System Type
X				7	010-016	SYNUM	System Number
X				8	017-024	DTELU	Date Last Update
X				6	025-030	TMENT	Time Last Update
X				3	031-033	WTCTN	World Trade Country
X				6	034-039	RLVL	Rules Level
X		X		4	040-043	BOXSD	Box Ship Date
X				4	044-047	UPCID	Upgrade Control ID
X				4	048-051	PLUPC	Prev Level UPCID
X				1	052-052	SPTYP	Service Processor Type
X				48	053-100	FIL78	Expansion Area

13 SEP. 1988

38480030-1

## HPCS Record Description.

File Name: SYSTOPOL Desc Name: System Topology Description  
 Record Name: STDELEMT Desc Name: STD Element Record

CHARACTER	ZONE	PACKED	DECIMAL	LENGTH	POSITIONS	FIELD NAME	FIELD DESCRIPTIVE NAME
FR	TO						
X				3	001-003	ELMID	Element Identifier
X				2	004-005	RCDTP	Record Type
X				3	006-008	ELMFR	Parent Element Identifier
X				4	009-012	IDMAC	Machine type
X				3	013-015	IDSMN	Sales Model
X				6	016-021	DVRPQ	Device/RPQ Code
X				10	022-031	BMNUM	Bill of Material Number
X				4	032-035	FIL04	Filler
X				1	036-036	ELMTP	Element Type
X				1	037-037	ELMST	Element Subtype
X				1	038-038	ELSCD	Element Source Code
X				9	039-047	MACSR	Machine Serial#/Order#
X	X			5	048-052	CORDX	X-Coordinate Location
X	X			5	053-057	CORDY	Y-Coordinate Location
X				4	058-061	LOCCD	Location Description
X				1	062-062	MGOFF	Mounting Group Offset
X				1	063-063	DFSWA	DFCI Switch A Setting
X				1	064-064	DFSWB	DFCI Switch B Setting
X				1	065-065	DFTRA	DFCI Terminator A String
X				1	066-066	DFTRB	DFCI Terminator B String
X				1	067-067	DEVST	Device Status
X				3	068-070	DRIVA	Driver-'A' String or only
X				3	071-073	DRIVB	Driver-'B' String
X				10	074-083	SDATA	S/370 Address Data
X				1	084-084	IPLDC	IPL device
X				1	085-085	PSDVC	Primary / Secondary Device Code
X				15	086-100	FIL16	Filler -- Expansion Area

## HPCS Record Description.

File Name: SYSTOPOL

Desc Name: System Topology Description

Record Name: STDCABLE

Desc Name: STD Cable Record

CHARACTER	ZONE	PACKED	DECIMAL	LENGTH	POSITIONS	FIELD NAME	FIELD DESCRIPTIVE NAME
FR	TO						
X				3	001-003	ELMID	Element Identifier
X				2	004-005	RCDTP	Record Type
X				3	006-008	MACID	ID of Machine Order
X				6	009-014	DVRPQ	Device/RPQ Code
X				10	015-024	BMNUM	Bill of Material Number
X				4	025-028	FIL04	Filler
X				1	029-029	ELMTP	Element Type
X				1	030-030	ELMST	Element Subtype
X				1	031-031	ELSCD	Element Source Code
---'From' Loc Data---							
X				3	032-034	ELMFR	'From' Element Identifier
X				4	035-038	LOCCD	Location Description
	X			5	039-043	CORDX	X-Coordinate Location
	X			5	044-048	CORDY	Y-Coordinate Location
---End 'From' Loc Data---							
---'To' Loc Data---							
X				3	049-051	ELMTO	'To' Element Identifier
X				4	052-055	LOCCD	Location Description
	X			5	056-060	CORDX	X-Coordinate Location
	X			5	061-065	CORDY	Y-Coordinate Location
---End 'To' Loc Data---							
---2nd 'To' Loc Data---							
X				3	066-068	ELMTO	'To' Element Identifier
X				4	069-072	LOCCD	Location Description
	X			5	073-077	CORDX	X-Coordinate Location
	X			5	078-082	CORDY	Y-Coordinate Location
---End 2nd 'To' Loc Data---							
X				1	083-083	DEVST	Device Status
X				1	084-084	PSDVC	Primary / Secondary Device Code
X				16	085-100	FIL17	Filler -- Expansion Area

## HPCS Record Description.

File Name: ELEMDESC

Desc Name: Element Description File

Record Name: BASELEMT

Desc Name: Basic Element Record

CHARACTER	ZONE	PACKET	DECODE	LENGTH	POSITIONS	FIELD NAME	FIELD DESCRIPTIVE NAME
FR	TO						
x				1	001-001	RCDTP	Record Type
x				4	002-005	FIL04	Filler - Expansion Area
x				10	006-015	BMNUM	Bill of Material Number
x				8	016-023	FIL10	Expansion Area
x	x			2	024-025	FNLVL	Functional Level
x				1	026-026	ELMTP	Element Type
x				1	027-027	ELMST	Element Subtype
x				10	028-037	ELMNM	Descriptive Name
x				10	038-047	HPCDN	HPCS Device Name
x				10	048-057	ACCES	Accessory Part Number
	x			4	058-061	EXWDT	External Width
	x			4	062-065	INWDT	Internal Width
	x			2	066-067	EHGHT	Height (EIA Units)
	x			5	068-072	MLGHT	Length or Height (MM)
	x			4	073-076	MDPTH	Depth (MM)
	x	1		4	077-080	KWGHT	Weight (Kilograms)
	x			3	081-083	PWRVL	Power Value (KVA)
	x			1	084-084	MGOFF	Mounting Group Offset
	x			4	085-088	MCBIN	Cable Lgth Increm (MM)
	x			2	089-090	PWOCT	Power Outlets Count
	x			2	091-092	ARMCT	DASD Arms Count
	x			2	093-094	CPTCT	Control Port Count
	x			2	095-096	DEVCT	Count of Devices card can drive
	x			1	097-097	BUSCT	Count of Buses
	x			4	098-101	INTWL	Internal Wiring Length
x				3	102-104	FIL03	Filler - Expansion Area
	x			2	105-106	FWCSN	First Wide Card Slot Number
x				1	107-107	SWDEV	Switched DASD Device Flag
x				1	108-108	TRMTP	Terminator Type
x				1	109-109	HPADD	Device Added By HPCS
x				4	110-113	IDMAC	Machine type (HPCS Adds Only)
x				3	114-116	IDSMN	Sales Model (HPCS Adds Only)
x				6	117-122	DVRPQ	Device/RPQ Code (HPCS Adds Only)
x				1	123-123	CBEXL	Cable Exit Location
x				1	124-124	TOWMT	Tower Mounted Device
x				1	125-125	DPOCD	Delayed Power Off Code
	x			3	126-128	LVKVA	110 V Rack KVA Override
	x			3	129-131	COGRX	Center of Gravity X Coordinate
	x			3	132-134	COGRY	Center of Gravity Y Coordinate
	x			3	135-137	COGRZ	Center of Gravity Z Coordinate
x				4	138-141	STCAP	DASD Storage Capacity
x				13	142-154	FIL17	Filler - Expansion Area
96 Bytes--Array of 6 sets of Coordinates							
x				4	155-	LOCCD	Location Description
x				4		JAKNM	Jack Number for Plug
	x			4		CORDX	X-Coordinate Location
	x			4	-250	CORDY	Y-Coordinate Location
End of Array							

## HPCS Record Description.

File Name: ELEMDESC Desc Name: Element Description File

Record Name: COMMSPEC Desc Name: Comm Specify Code Definition.

CHARACTER	ZONE	PACKED	DECIMAL	LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
x				1	001-001	RCDTP	Record Type
x				4	002-005	IDSYS	System Type
x				2	006-007	SEQNM	Sequence Number
x				35	008-042	FIL35	Filler area for key
-----208 Bytes-----Array of 8 sets of Communication Lines-----							
x				3	043-	SPCPF	Specify Code Prefix
x				1		FIL01	Filler - Expansion Area
x				1		ELEIF	Electrical Interface
x				1		PROTO	Communications Protocol
x				1		CNNCT	Connection 'To' Parameter
x				1		LSCAT	Line Speed Catagory
x				1		CSSTP	Communication Subsystem Type
x				1		FIL02	Expansion Area
x				10		BMNUM	Bill of Material Number
x				06	-250	FIL06	Filler - Expansion Area
-----End of Array-----							

## HPCS Record Description.

File Name: ELEMDESC

Desc Name: Element Description File

Record Name: LNSPDCAT

Desc Name: Line Speed Category Record

CHARACTER	ZONE	PACKET	DICTIONARY	LENGTH	POSITIONS	FIELD NAME	FIELD DESCRIPTIVE NAME
				FR-TO			
X				1	001-001	RCDTP	Record Type
X				4	002-005	IDSYS	System Type
X				2	006-007	SEQNM	Sequence Number
X				18	008-025	FILL8	Filler area for key
-----220 Bytes-----Array of 22 Sets of line speed parameters-----							
X				1	026-	SPCSF	Specify Code Suffix
X				1		LSCAT	Line Speed Category
X	X			4		LNSPD	Line Speed
X				4	-245	FILL04	Filler - Expansion Area
-----End of Array-----							
X				05	246-250	FILL05	Filler - Expansion Area

## HIRS Record Description.

File Name: DELTAHHF Desc Name: Delta Hardware Handling File

Record Name: DELTAHHI Desc Name: Delta Hardware Handling

CHARACTER	ZONE	PACKED	DECIMAL	LENGTH	POSITIONS	FIELD NAME	FIELD DESCRIPTIVE NAME
REC	DEC	DEC	DEC	FR	TO		
-	-	-	-	2	001-002	TTYPE	Task Type to Execute
x				1	003-003	HANCD	Handling Code
	x			5	004-008	TSEQN	Task Sequence Number
					009-	TSKID	Task Identification Number
x				4	009-012	TXRF	Task ID - Cross Reference Number
x				3	013-015	TIGRP	Task ID - General Grouping Number
x				1	016-016	POWST	Power Status
x				1	017-017	SUBCP	Sub component indicator
					018-	TCMTM	Task Completion Time
	x			3	018-020	TCMTP	Primary Time to Complete Task
	x			3	021-023	TCMTA	Alternate Time if Task is in a Group
x				1	024-024	RPERM	Remove Permanently Flag
x				1	025-025	HANLR	Handler Code
					026-	HPAGE	Parentage
x				3	026-028	ELIL1	Element Identifier Level 1 (Rack)
x				4	029-032	LOCL1	Location Code Level 1
x				3	033-035	ELIL2	Element Identifier Level 2 (Device)
	x			5	036-040	CORY2	Coordinate Y Level 2
x				4	041-044	LOCL2	Location Code Level 2
x				3	045-047	ELIL3	Element Identifier Level 3 (Card)
x	x			5	048-052	CORY3	Coordinate Y Level 3
x				4	053-056	LOCL3	Location Code Level 3
x				3	057-059	ELIL4	Element Identifier Level 4 (Cable)
	x			5	060-064	CORY4	Coordinate Y Level 4
x				4	065-068	LOCL4	Location Code Level 4
x				6	069-074	CPFC4	Cable's Parent Feature Code Number
x				1	075-075	NCBLE	Number of Cable Ends
x				3	076-078	GRAPHID	Graphics Module ID Number for Pubs
x				1	079-079	GROUP	Task Group Flag (Grouped if "G")
x				1	080-080	CLASS	Class of Values to be Set for Task
x				1	081-081	SPCLS	Special Class of Values to be Set
x				19	082-100	FILLR	RESERVED -- Expansion Area

The remainder of this record format consists of the STDELEMT record from the SYSTOPOL file.



## HIRS Record Description.

File Name: ITDELTA

Desc Name: Intermediate Delta File

Record Name: ITDELTAI

Desc Name: Intermediate Delta

CHARACTER	ZONE	PACKED	DECIMAL	LENGTH	POSITIONS	FIELD NAME	FIELD DESCRIPTIVE NAME
FR	TO						
x	-	-	-	2	001-002	TTYTYPE	Task Type to Execute
x	-	-	-	1	003-003	HANCD	Handling Code
-	x	-	-	5	004-008	TSEQN	Task Sequence Number
-	-	-	-	-	009-	TSKID	Task Identification Number
x	-	-	-	4	009-012	TIXRF	Task ID - Cross Reference Number
x	-	-	-	3	013-015	TIGRP	Task ID - General Grouping Number
x	-	-	-	1	016-016	POWST	Power Status
x	-	-	-	1	017-017	SUBCP	Sub Component Code
-	-	-	-	-	018-	TCMTM	Task Completion Time
-	x	-	-	3	018-020	TCMTP	Primary Time to Complete Task
-	x	-	-	3	021-023	TCMTA	Alternate Time if Task is in a Group
x	-	-	-	1	024-024	RPERM	Remove Permanently Flag
x	-	-	-	1	025-025	HANLR	Handler Code
x	-	-	-	1	026-026	PERSP	Task Perspective
x	-	-	-	3	027-029	GLSQN	Goal Sequence Step Number
x	-	-	-	3	030-032	UPDSQ	Update Sequence Step Number
x	-	-	-	1	033-033	STATE	Task State
x	-	-	-	1	034-034	DIRET	Task Direction
x	-	-	-	1	035-035	MUPID	Model Upgrade Indicator
-	-	-	-	-	036-	HPAGE	Parentage
x	-	-	-	3	036-038	ELIL1	Element Identifier Level 1 (Rack)
x	-	-	-	4	039-042	LOCL1	Location Code Level 1
x	-	-	-	3	043-045	ELIL2	Element Identifier Level 2 (Device)
-	x	-	-	5	046-050	CORY2	Coordinate Y Level 2
x	-	-	-	4	051-054	LOCL2	Location Code Level 2
x	-	-	-	3	055-057	ELIL3	Element Identifier Level 3 (Card)
-	x	-	-	5	058-062	CORY3	Coordinate Y Level 3
x	-	-	-	4	063-066	LOCL3	Location Code Level 3
x	-	-	-	3	067-069	ELIL4	Element Identifier Level 4 (Cable)
-	x	-	-	5	070-074	CORY4	Coordinate Y Level 4
x	-	-	-	4	075-078	LOCL4	Location Code Level 4
x	-	-	-	6	079-084	CPFC4	Cable's Parent Feature Code Number
x	-	-	-	1	085-085	CABRL	Cable Relationship
x	-	-	-	1	086-086	NCBLE	Number of Cable ends
x	-	-	-	1	087-087	GROUP	Task Group Flag (Grouped if "G")
x	-	-	-	1	088-088	CLASS	Class of Values to be Set for Task
x	-	-	-	1	089-089	SPCLS	Special Class of Values to be Set
x	-	-	-	31	090-120	FILLR	RESERVED -- Expansion Area

The remainder of this record format consists of the STDELEMT record from the SYSTOPOL file, please refer to it for rest of the format.

## HIRS Record Description.

File Name: COMPON TASK Desc Name: Component Task File

Record Name: CPTASKII Desc Name: Component Task Include

CHARACTER	ZONE	PACKE	DECE	LEN	POS	FIELD	FIELD
NAME	DE	DE	DE	TH	ITION	NAME	DESCRIPTIVE NAME
---	---	---	---	---	FR-TO	---	---
X				2	001-002	TTYPE	Task Type to Execute
X				1	003-003	HANCD	Handling Code
X				10	004-013	HPCDN	HPCS Device Name
X				1	014-014	ELMTP	Element Type
X				1	015-015	ELMST	Element Subtype
X				1	016-016	FILL1	RESERVED -- Expansion Area
X				1	017-017	GROUP	Task Group Flag (Grouped if "G")
X				4	018-021	TIXRF	Task ID - Cross Reference No.
X				3	022-024	TIGRP	Task ID - General Grouping No.
X				8	025-032	FILL2	RESERVED -- Expansion Area
X				1	033-033	PERSP	Task Perspective
X	X			3	034-036	GLSQN	Goal Sequence Step Number
X	X			3	037-039	UPDSQ	Update Sequence Step Number
X				1	040-040	STATE	Task State
X				1	041-041	DIRET	Task Direction
X				1	042-042	POWST	Power Status
X				1	043-043	SUBCP	Sub Component Identification
X					044-	TCMTM	Task Completion Time
X				3	044-046	TCMTP	Primary Time to Complete Task
X				3	047-049	TCMTA	Alternate Time if Task is in a Group
X				1	050-050	MUPID	Model Upgrade Indicator
X				10	051-060	PHPDN	Parent device name
X				1	061-061	CABRL	Cable Relationship
X				1	062-062	HANLR	Handler Code
X				1	063-063	CINTK	Characterize Independent Task
X				1	064-064	CLASS	Class of Values to be Set for Task
X				1	065-065	SPCLS	Special Class of Values to be Set
X				15	066-080	FILL5	RESERVED -- Expansion Area

## DATA ELEMENT DESCRIPTIONS

E: ACCES D: ACCESSORY CODE

XREF: BASELEMT

DEF: Contains the part number by which a device would be identified when ordered as an accessory.

E: ARMCT D: DASD ARMS COUNT

XREF: BASELEMT

DEF: Count of the number of DASD arms. For a DASD record, this represents the number of arms in the device. For a card record, this represents the number of arms which can be driven.

E: BMNUM D: BILL OF MATERIAL NUMBER

XREF: STDELEMT STDCABLE BASELEMT COMMSPEC

DEF: A top level number MFI number which identifies one piece for a Machine type or feature which is to be located by HPCS.

E: BOXSD D: Box Ship Date

XREF: STDHEADR

DEF: Date a System order is due to ship from manufacturing. Provides identification to plant order processing where they may have multiple system orders with the same System Type / System Number and a different ship date.

E: BUSCT D: BUS COUNT

XREF: BASELEMT

DEF: The Number of busses which a specific CEC or Expansion unit has.

E: CABRL D: CABLE RELATIONSHIP

XREF: ITDELTAI CPTASKII

DEF: Specifies the cable end relationship to the location of the components they attach to.  
Values: 'A' = Intra-rack  
'E' = Inter-rack

E: CBEXL D: Cable Exit Location

XREF: BASELEMT

DEF: Code to indicate the position on a device where the cable will exit when properly installed.

Values: 'L' = Left  
'M' = Middle  
'R' = Right

E: CINTK D: Characterize Independent Task

XREF: CPTASKII

DEF: Identifies tasks which support the physical installation or removal of a component  
Values 'I' = Install Task  
'D' = Disassemble Task

E: CLASS D: CLASS OF VALUES TO BE SET

XREF: DELTAHII ITDELTAI CPTASKII

| DEF: Determines the Values/Variables to be set for the Task.

E: CPFC4 D: CABLE'S PARENT FEATURE CODE NUMBER  
XREF: DELTAHHI ITDELTAI

| DEF: This is the Feature Code number of the Cable's Parent.

E: COGRx D: CENTER OF GRAVITY COORDINATE (X,Y,Z)  
XREF: BASELEMT

| DEF: This is the location of the center of gravity of a device.  
Value is in millimeters from device point of origin.

E: CORDX D: X-COORDINATE LOCATION  
XREF: STDELEMT STDCABLE BASELEMT

| DEF: The horizontal offset of a device or connection within  
another device or the entire system.  
Value is carried in millimeters.

E: CORDY D: Y-COORDINATE LOCATION  
XREF: STDELEMT STDCABLE BASELEMT

| DEF: The vertical offset of a device or connection within  
another device or the entire system.  
Value is carried in EIA units for Units mounted in  
a rack. Carried in millimeters in all other cases.

E: CNNECT D: CONNECT 'TO' PARAMETER  
XREF: COMMSPEC

| DEF: Code to identify the destination of the 'TO' end of  
a communication line.

Values: ' ' = Unknown or does not apply  
'A' = Switched Auto-Call  
'B' = Auto-Call Unit  
'C' = System to Workstation with Clock.  
'D' = System to Workstation without Clock.  
'E' = System to System with Clock.  
'F' = System to System without Clock  
'G' = BIS  
'H' = NonAuto-Call Switch or Non-Switch  
with NonAuto-Call SNBU  
'I' = Nonswitched

E: CSSTP D: COMMUNICATION SUBSYSTEM TYPE  
XREF: COMMSPEC

| DEF: For a communication line, CSSTP identifies the IOP type  
or subsystem type requirements.

Values: ' ' = No specific requirements.  
'1' = Line requires Communications Controller for IOP.

E: CPTCT D: CONTROL PORT COUNT  
XREF: BASELEMT

| DEF: For a device controller this CPTCT contains a count of  
the number of ports to which cables can be attached.

E: DEVCT D: COUNT OF DEVICES  
XREF: BASELEMT

| DEF: Count of the number of devices which have been placed in  
a tower or the number of devices a card can drive.

E: DEVST D: DEVICE STATUS

XREF: STDELEMT STDCABLE

DEF: Code used to identify the status of parts on the Topology file during multiple iterations of an configurator conversation.

Values: 0 = Old (Existed on Topology prior to Conversation)  
 I = Implicitly added to Topology by HPCS.  
 E = Explicitly added to Topology by Layer 1.

E: DFSWA D: DFCI SWITCH A SETTING

XREF: STDELEMT

DEF: This field is used for multiple purposes on the Topology File dependent upon Element Type.

- On DFCI Devices: (DASD and Tape driven by DASD Driver)  
 The value to which a physical switch on a I/O device is set to provide that device a unique address.  
 — String 'A' or only switch.  
 — Values: 0 to 7
- On DASD Device:  
 'A' String Driving Port on the DASD Controller.
- On a Communications IOA Card.  
 Sequence of card within the set of IOA's within the particular communication subsystem.
- On an Channel Adapter Card.  
 Channel Type Attached to Channel Adapter.  
 (2 = Type A, 3 = Type B, 4 = Type C)

E: DFSWB D: DFCI SWITCH B SETTING

XREF: STDELEMT

DEF: This field is used for multiple purposes on the Topology File dependent upon Element Type.

- On string switched DFCI Devices.  
 The value to which a physical switch on a I/O device is set to provide that device a unique address.  
 - String 'B' switch.  
 - Values: 0 to 7
- On DASD Device:  
 'B' String Driving Port on the DASD Controller.
- On a Communications IOP Card.  
 Protocol of one of the Comm Lines attached to one of the IOA cards driven by the IOP.

E: DFTRA D: DFCI TERMINATOR A STRING

XREF: STDELEMT

DEF: Identifies whether or not the DFCI output port on string 'A' for an I/O device has a terminator plugged.

Values: '0' = No terminator '1' = Terminator.

E: DFTRB    D: DFCI TERMINATOR B STRING  
 XREF: STDELEMT  
 DEF: Identifies whether or not the DFCI output port on string.  
       'B' for an I/O device has a terminator plugged.  
       Values: '0' = No terminator        '1' = Terminator.

E: DIRET    D: DIRECTION  
 XREF: ITDELTAI CPTASKII  
 DEF: Defines the direction of progressing thru different  
       perspectives of a system, rack, card cage, etc ...  
       Values: 'H' = Highest location to lowest location  
       ' L' = Lowest location to highest location  
       Proper choices of direction values ensure that tasks,  
       when completed, will not interfere with succeeding tasks.

E: DPOCD    D: DELAYED POWER OFF CODE  
 XREF: BASELEMT  
 DEF: Code to identify a device which needs to have a delayed  
       power off cord.  
       Values: 'T' = True (DPO Cord)        'F' = False (No DPO)

E: DRIVA    D: DRIVER/CONTROL ON A STRING  
 XREF: STDELEMT  
 DEF: Identifies the I/O Adapter Card which is the driver on  
       String 'A' or the only string for an I/O Device.

E: DRIVB    D: DRIVER/CONTROL ON B STRING  
 XREF: STDELEMT  
 DEF: Identifies the I/O Processor Card which is the driver  
       on String 'B' for an I/O Device.

E: DTELU    D: DATE LAST UPDATE  
 XREF: STDHEADR  
 DEF: Last date this file was updated - YYYYMMDD format.

E: DVRPQ    D: DEVICE/RPQ CODE  
 XREF: STDELEMT STDCABLE BASELEMT  
 DEF: Code to identify a device which is feature offered on  
       a machine type. Also can contain an informational  
       specify code which further defines a machine type or  
       a feature.

E: EHGT    D: HEIGHT (EIA UNITS)  
 XREF: BASELEMT  
 DEF: Vertical height of a tower mountable device in EIA units.  
       One EIA unit equals 1 3/4 inches.

E: ELEIF    D: ELECTRICAL INTERFACE  
 XREF: COMMSPEC  
 DEF: Code to identify the electrical interface for a  
       communication line.  
       Values: ' ' = Not a communication line

'A' = RS - 232  
 'B' = RS - 422  
 'C' = X.21-----  
 'D' = V.35  
 'E' = V.25 / RS - 366  
 'F' = V.24  
 'G' = 803.3  
 'H' = 803.5

E: ELMFR D: PARENT ELEMENT IDENTIFIER

XREF: STDELEMT STDCABLE

DEF: Element identifier of the device within which the current device is mounted.  
 For a cable this is the element identifier of the device to which the 'from' end of a cable is attached. (Toward CEC)

E: ELMID D: ELEMENT IDENTIFIER

XREF: STDHEADR STDELEMT STDCABLE

DEF: Code assigned to uniquely identify any device within a common hardware system.

Values: 001 - 999 and AAA - ZZZ.

E: ELMNM D: DESCRIPTIVE NAME

XREF: BASELEMT

DEF: Externally Visible name for a Common Hardware device.  
 - Machine type / Model for a machine.  
 - CCIN number for a Card.

E: ELMST D: ELEMENT SUBTYPE

XREF: STDELEMT STDCABLE BASELEMT CPTASKII

DEF: Code to define the logical class of a device within a physical type.

Values:

(ELMTP) Element Type	(ELMST) Element Subtype	Type of device
T	1	Tower
U	1	Unit - CEC
U	2	Unit - DASD Controller
U	3	Unit - DASD
U	4	Unit - Tape
U	5	Unit - Expansion Unit
U	6	Unit - Rack Mounted Modem
U	7	Unit - Cover
U	8	Unit - System Power Interface
U	9	Unit - Channel Adapter CSU Box
U	A	Unit - Mounting Rail
U	D	Unit - Diskette Unit
U	0	Unit - OEM Reserved Space
U	S	Unit - Sleeve for half wide units (Tape)
U	U	Unit - Device not supported by HPCS
C	1	Card - I/O Processor (Standalone)
C	2	Card - I/O Processor (Requires IOA)
C	3	Card - I/O Adapter.
C	5	Card - Transmitter to another Cage.
C	6	Card - Receiver from another Cage.
C	7	Card - Transmitter or Receiver.
C	8	Card - Memory
C	9	Card - Processor Unit
C	A	Card - Air Flow
B	1	Cable - Data Carriers.
B	2	Cable - Power Carriers.
B	3	Cable - Communications

	B		4		Cable - Power Sequencing
	B		5		Cable - S/370 Channel Adapter Cable
	B		6		Cable - Twinaxial Workstation Cable

E: ELMT0 D: 'TO' ELEMENT IDENTIFIER

XREF: STDCABLE

| DEF: Element identifier of the device to which the 'to' end of a cable is attached (Away from CEC)

E: ELMTF D: ELEMENT TYPE

XREF: STDELEMT STDCABLE BASELEMT CPTASKII

| DEF: Code to define the general physical class of a device.

Values: 'T' = Tower  
'U' = Tower mountable unit  
'C' = Card  
'B' = Cable

E: ELSCD D: ELEMENT SOURCE CODE

XREF: STDELEMT STDCABLE

| DEF: Code to indicate at what point a device will be installed in a system.

Initial Order Values: 'P' = Installed at plant of control  
'F' = Field installed  
'O' = OEM device (installed in field)  
'B' = Part of Base unit before integration

E: EXWDT D: EXTERNAL WIDTH

XREF: BASELEMT

| DEF: Width of a device in millimeters.

E: FNLVL D: FUNCTIONAL LEVEL

XREF: BASELEMT

| DEF: Field is used to show that multiple devices which have the same HPCS device name (HPCDN) are at different functional levels.

Values: 00 = Initial Functional level for a device  
01 - 99 = Subsequent functional levels

E: FWCSN D: FIRST WIDE CARD SLOT#

XREF: BASELEMT

| DEF: Numeric field populated for a processor to identify the first wide card slot number. Used in assignment of Air Flow Cards. Values 01 - nn.

E: GLSQN D: GOAL SEQUENCE STEP NUMBER

XREF: CPTASKII ITDELTAI

| DEF: Defines the Major goal groups which will install major parts of the installation.  
All element tasks necessary to be sequenced in order to accomplish a major subportion of an installation will have a common Goal Sequence Step Number.

E: GRAPHID D: GRAPHICS MODULE ID NUMBER

XREF: DELTAHHI

| DEF: The Graphics Module ID Number of the Information Development Artwork the is associated with the Task.



E: GROUP D: TASK GROUP FLAG

XREF: CPTASKII ITDELTAI DELTAHHI

DEF: Determines if a Task is Groupable with other Tasks with the same Task ID Number (TSKID).  
Values: 'G' = Task is Groupable  
' ' = Task is NOT Groupable

E: HANCD D: HANDLING CODE

XREF: DELTAHHI ITDELTAI CPTASKII

DEF: Identifies the type of handling the component is to receive.  
Values: 'A' = Adding component  
'R' = Removing component  
'M' = Moving component

E: HANLR D: HANDLER

XREF: DELTAHHI ITDELTAI CPTASKII

DEF: Identifies the Person doing component handling  
Values: 'C' = Customer  
'I' = IBM personnel

E: HPADD D: DEVICE ADDED BY HPCS

XREF: BASELEMT

DEF: Code to identify a device on the Element Description file which can potentially be added to an order by HPCS.  
Values: 'T' = Can be added  
'F' = Cannot be added

E: HPAGE D: Hierarchical Parentage  
E: ELILx D: ELEMENT ID LEVEL X (1-4)  
E: CORYx D: COORDINATE Y LEVEL X (1-4)  
E: LOCLx D: LOCATION CODE LEVEL X (1-4)

XREF: DELTAHHI ITDELTAI

DEF: Identifies the Hierarchical Parentage of the Component being Handled.  
Allowing for a maximum of 4 levels in the hierarchy the data for each component per level is defined below:

LEVEL 1 contains Rack Information  
LEVEL 2 contains Device Information  
LEVEL 3 contains Card Information  
LEVEL 4 contains Cable Information

E: HPCDN D: HPCS DEVICE NAME

XREF: BASELEMT CPTASKII

DEF: The unique name by which a Common Hardware device is known within the scope of HPCS layer 3 and HIRS.

E: IDMAC D: MACHINE TYPE

XREF: STDELEMT BASELEMT

DEF: Code by which a machine level device is known in the sales manual.

E: IDSMN D: SALES MODEL

XREF: STDELEMT BASELEMT

DEF: Model within machine type by which a device is known in the sales manual.

E: IDSYS D: SYSTEM TYPE

11/06/87

APPENDIX I

PAGE 17

XREF: STDHEADR COMMSPEC LNSPDCAT

DEF: Code to identify the type of system. Usually the Machine Type of the highest level processor in the system.

937x = 9370 Processors  
9xxx = New X Processor

E: INWDT D: INTERNAL WIDTH

XREF: BASELEMT

DEF: Horizontal open interior space in a tower (millimeters).

E: INTWL D: INTERNAL WIRING LENGTH

XREF: BASELEMT

DEF: The length of the internal wiring within a device.

E: IPLDC D: IPL Device

XREF: STDELEMT

DEF: Identifies the system's IPL devices

Values: 'P' = Primary IPL device  
'S' = Secondary IPL device  
'B' = Both Primary and Secondary IPL device

E: JAKNM D: JACK NUMBER FOR PLUG LOC

XREF: BASELEMT

DEF: The Number which is printed on the surface of a unit to visually name a plug location.

E: KWGHT D: WEIGHT (KILOGRAMS)

XREF: BASELEMT

DEF: Weight of a device in Kilograms (format xxx.x)

E: LNSPD D: LINE SPEED

XREF: LNSPDCAT

DEF: Speed of a communications line in 100's of Bits per second.

E: LOCCD D: LOCATION DESCRIPTION

XREF: STDELEMT STDCABLE BASELEMT

DEF: Name applied to the position of one device within another device.

Values:

Tower Location Scheme

X Y Z Z

----- Number of towers to Left or right of the one containing the CEC.

----- 'C' = Tower which contains the CEC.

----- 'R' = Right of Tower Containing the CEC.

----- 'L' = Left of Tower Containing the CEC.

----- Permanent identifier for a tower (Doesn't Change) (A - Z)

LMnn - Identifies a device mounted flush to the left edge of a tower. Since most devices extend the full width of a tower this will be the most common description for a

tower mounted device. nn varies from 01 - Max.

RMnn - Identifies a device mounted to the right edge of a tower. .  
This description would only be used with devices which extend  
less than full width of a tower. nn varies from 01 - Max.

CSss - Slot number for cards. ss = card slot number (01 - 99)

PWSI - Power Sense In - Attachment loc for  
the intertower power sensor cable.

PWSO - Power Sense Out - Attachment loc  
for intertower power sensor cable.

PInn - Power In - Attachment loc for Power input.

POnn - Power Out - Attachment loc for power outlet.

BMnn - Channel Adapter CSU box mounted at bottom of tower.  
nn = 01 - 08

VM01 - Vertical Mount - Assigned to a SPI box which is  
mounted vertically above the PCC unit in the rack.

PWSI - Power Sense In - Attachment loc for  
the inter-tower power sensor cable.

PWSO - Power Sense Out - Attachment loc  
for intertower power sensor cable.

CCnn - Cable Connection - Coordinates to  
identify the loc of cable connect-  
ions on the back of a card.  
(nn varies from 01 to device Max).

DInn - DFCI Input port - Coordinates to  
identify the loc of DFCI input  
ports on an I/O device.  
(nn = 01 or 02 for current devices)

DOnn - DFCI Output port - Coordinates to  
identify the loc of DFCI output  
ports on an I/O device.  
(nn = 01 or 02 for current devices)

DCnn - DFCI Control port - Coordinates to  
identify the loc of DFCI control  
ports on an DASD Controller or DASD Device.  
(nn = 01 to 04 for DASD Controller)  
(nn = 01 or 02 for DASD Device)

E: LSCAT D: LINE SPEED CATEGORY

XREF: COMMSPEC LNSPDCAT

DEF: Code to identify which category of line speeds applies  
for a Communications specify code.

Values: '0' - '7'.

E: LVKVA D: 110 VOLT RACK KVA OVERRIDE

XREF: BASELEMT

DEF: Alternate KVA value which a device uses when it is  
mounted in a 110 Volt Rack

E: MACID D: ID OF MACHINE ORDER

XREF: STDCABLE

DEF: Element identifier of the machine type on which a feature  
cable is ordered.

E: MACSR D: MACHINE SERIAL#/ORDER#  
 XREF: STDELEMT  
 DEF: Contains the Machine order # assigned by AAS system until a serial number for a machine type is known. After that MACSR contains the serial number.

E: MCBIN D: CABLE LGTH INCREM (MM)  
 XREF: BASELEMT  
 DEF: Contains an additional length parameter which must be added to the calculated length when determining the total required cable length between two ports. This increment is called for by unique characteristics of the device on which it is found. An example is the length cable required by the cable carrier arms on a DASD Device.

E: MDPHTH D: DEPTH (MM)  
 XREF: BASELEMT  
 DEF: Front to back depth of a device in millimeters.

E: MGOFF D: MOUNTING GROUP OFFSET  
 XREF: STDELEMT BASELEMT  
 DEF: Vertical distance from the bottom edge of a tower mounted device to where the mounting group is positioned.  
 Value carried in EIA units.

E: MLGHT D: LENGTH OR HEIGHT (MM)  
 XREF: BASELEMT  
 DEF: Length of a cable or height of a device in millimeters.

E: MUPID D: MODEL UPGRADE INDICATOR  
 XREF: ITDELTAI CPTASKII  
 DEF: Identifies components relating to a Model Upgrade  
 Values: 'M' = Model Upgrade Component  
 ' ' = not related to Model Upgrade

E: NCBLE D: NUMBER OF CABLE ENDS  
 XREF: ITDELTAI DELTAHHI  
 DEF: Defines the number of cable ends to sequence  
 Values: '1' = only 1 end to sequence  
 '2' = 2 ends to sequence  
 '3' = 3 ends to sequence

E: PERSP D: PERSPECTIVE  
 XREF: ITDELTAI CPTASKII  
 DEF: Defines the perspective to take when selecting the group of components to work on for a given task  
 Values: 'S' = System  
 'R' = Rack  
 'X' = Extra  
 'C' = Card Cage / Tail Gate  
 'P' = Pseudo

E: PHPDN D: PARENT HPCS DEVICE NAME  
 XREF: CPTASKII  
 DEF: Contains the component being handled's parent device

descriptive name (see HPCDN for details)

E: PLUPC D: PREV LVL UPCID  
XREF: STDHEADR  
DEF: Upgrade control level code from the input Topology File.

E: POWST D: POWER STATUS  
XREF: DELTAHHI ITDELTAI CPTASKII  
DEF: Status the power to the machine must be in for a task to be performed.  
Values: 'U' = System can be Power Up  
'D' = System is Powered Down

E: PROTO D: PROTOCOL  
XREF: COMMSPEC  
DEF: Code to identify the protocol for a communication line.  
Values: ' ' = Not a Communication line  
'A' = BSC  
'B' = ASC  
'D' = SDLC - NRZI  
'E' = X.25  
'F' = ECL  
'I' = Ethernet  
'J' = SDLC - NON-NRZI  
'K' = HIFAS Character Mode  
'L' = HIFAS Block Mode

E: PSDVC D: PRIMARY/SECONDARY DEVICE CODE  
XREF: STDELEMT STDCABLE  
DEF: Code to indicate whether or not a component is the primary piece for an orderable machine type or feature power sequence jack.  
Values: 'P' = Primary piece for device  
'S' = Secondary piece

E: PWOCT D: POWER OUTLETS COUNT  
XREF: BASELEMT  
DEF: Total number of power outlets on a tower.

E: PWRVL D: POWER VALUE  
XREF: BASELEMT  
DEF: Total amount of power required by a device. For a tower PWRVL represents the total power that can be drawn by the set of devices mounted in the tower.

E: RCDTP D: RECORD TYPE  
XREF: STDHEADR STDELEMT STDCABLE BASELEMT COMMSPEC LNSPDCAT  
DEF: Code to identify the record format which maps the contents of a record. Values vary by file.  
Values: File SYSTOPOL - System Topology  
STDHEADR - System Header = '10'  
STDELEMT - Element = '40'  
STDCABLE - Cable = '44'  
STDSPCFY - Specify Codes = '60'  
STDOEMCH - OEM Character = '70'  
File ELEMDESC - Element Description

```

LEVELCTL - Level Control      = 'A'
COMMSPEC  - Communic Spec Df= 'C'
DEVTABLE  - Dev to B/M Conv = 'D'
LNSPDCAT  - Line Speed Categ= 'L'
SPECDEFN  - Spec Code Def   = 'S'
BASELEMT  - Base Elements   = '1'
EXTCOORD  - Extended Coord's= '3'

```

E: RLLVL D: RULES LEVEL

XREF: STDHEADR

DEF: The maintenance level of the rules file which was used to create the Topology file.

E: RPERM D: REMOVE PERMANENTLY STATUS FLAG

XREF: DELTAHHI ITDELTAI

DEF: Indicated components removal status  
 Values: 'P' = permanent removal  
 ' ' = temporary removal or not removed

E: SDATA D: S/370 ADDRESS DATA

XREF: STDELEMT

DEF: For VM systems, SDATA contains the logical device address.

Card Format (ELMTP = 'C')

```

Byte(1)      = Length
               - 1 for IOP
               - 2 for single Address IOA
               - 3 - 9 for multiple address IOA,s.

```

```

Byte(2)      = Channel
Byte(3-10)   = UU(1).....UU(8)

```

Unit Format (ELMTP = 'U')

```

Byte(1)      = Length
               - 3 for unswitched devices
               - 6 for switched devices.

```

```

Byte(2)      = Channel 1
Byte(3)      = Address 1 on Channel 1
Byte(4)      = Address 2 on Channel 1

```

```

Byte(5)      = Channel 2
Byte(6)      = Address 1 on Channel 2
Byte(7)      = Address 2 on Channel 2

```

E: SPCLS D: SPECIAL CLASS OF VALUES TO BE SET

XREF: DELTAHHI ITDELTAI CPTASKII

DEF: Determines any special Values/Variables to be set for the Task.

E: STATE D: TASK STATE

XREF: ITDELTAI CPTASKII

DEF: Particular state of processing certain tasks  
 Values: 'F' = First, task precedes all others  
 'L' = Last, task follows all others  
 'C' = Cabling, task done only if cabling required  
 'A' = Add, only if NOT added previously  
 'R' = Remove, only if NOT used again  
 0-9 = Perform, only if Digits do NOT match  
 'P' = PSEUDO Task, NOT to be sequenced

E: STCAP D: DASD STORAGE CAPACITY

XREF: BASELEMT

| DEF: Storage Capacity of a DASD device in megabytes

E: SUBCP D: SUB COMPONENT CODE

XREF: ITDELTAI CPTASKII DELTAHHI

| DEF: Identifies a particular sub component activity  
 Values: 'T' = Terminator  
 'S' = DFCI address switch  
 'V' = voltage switch

E: SYNUM D: SYSTEM NUMBER

XREF: STDHEADR

| DEF: Number assigned by AAS to uniquely identify and tie together the components of a system order.

E: TCMTM D: TASK COMPLETION TIME

XREF: DELTAHHI ITDELTAI CPTASKII

| DEF: Amount of time required to accomplish task in minutes. (99.9)  
 TCMTM is the primary time to complete the task.  
 TCMTA is the alternate time, if the task is in a group.  
 (TCMTA is always a fraction of TCMTM. It measures the higher task efficiency within the "Roll n times" grouping.)

E: TIGRP D: TASK GROUP NUMBER

XREF: ITDELTAI CPTASKII DELTAHHI

| DEF: Specifies the unique number for each task description for a Rack, Device, Card, or Cable.

E: TIXRF D: TASK CROSS REFERENCE

XREF: ITDELTAI CPTASKII DELTAHHI

| DEF: Specifies the general task cross reference number

E: TSEQN D: TASK SEQUENCE NUMBER

XREF: ITDELTAI DELTAHHI

| DEF: Specifies the task sequence number in relation to other tasks that must be performed.

E: TSKID D: TASK IDENTIFICATION NUMBER

XREF: DELTAHHI ITDELTAI

| DEF: Determines the unique task identification.  
 Made up of TIGRP & TIXRF.

E: TMENT D: TIME LAST UPDATE

XREF: STDHEADR

| DEF: System time when the previous update was made to a Topology.

E: TRMTP D: TERMINATOR TYPE

XREF: BASELEMT

| DEF: Code to indicate the type of terminator associated with a device.  
 Values: 'D' = DFCI String Terminator.  
 'P' = Power Sequencing Terminator

E: TTYPE D: TASK TYPE TO EXECUTE

XREF: DELTAHII ITDELTAI CPTASKII

DEF: Identifies the Command to be processed.

Values for the First Digit are:

'0' = Add Task

'1' = Remove Task

'4' = Modify Task

Values for the Second Digit are:

'1' = Rack Task

'2' = Device Task

'3' = Card Task

'4' = Model Change Task

'5' = Cable Task

'6' = Terminator Task

Other Values:

'97' = Universal Upgrade Task

'98' = Universal Initial Install Task

'99' = Universal Task

E: UPCID D: UPGRADE CONTROL ID

XREF: STDHEADR

DEF: Code to uniquely identify the Order List and Topology File which are to be used in a upgrade pass through HPCS.

E: UPDSQ D: UPDATE SEQUENCE STEP NUMBER

XREF: CPTASKII ITDELTAI

DEF: Defines the goal point within a major goal group when a, specific task for a set of elements must be sequenced.

E: WTCTN D: WORLD TRADE COUNTRY


XREF: STDHEADR

DEF: The World Trade Country in which a system is to be installed.




# 1.0 Major Task Sequencing Goals

## 1.1 Major Goals for Initial Install



## 1.2 Major Goals for Upgrades



### 1.3 Tasks for Initial Install only

0. Entry Module - Before Beginning	SETM1
1. GOAL: System - RACK Adds	
▪ Position RACK	ASRP1
▪ Set-Up RACK	ASRH1
2. GOAL: System - Prepare for Change	
▪ (Not used for Initial Install)	
3. GOAL: RACK - Device Removes	
▪ (Not used for Initial Install)	
4. GOAL: System - RACK Removal	
▪ (Not used for Initial Install)	
5. GOAL: RACK - Device Adds	
▪ Prepare Device(s) for running:	
▪ Unlock Shipping Wedges	UDSW1
▪ Unlock Shipping Clamps	UDCH1
▪ Open Cable Guide Arm	ODGH_
▪ Verify Cable Terminator	VDCT_
▪ Verify/Set Voltage Switches	SDVS_
▪ Unlock Shock Protection	UDSH_
▪ Set Address Switches	SDAS_
▪ Set Device CB "ON" & chk pwr cbl	SDCB_
▪ Connect Device cables ends:	
▪ Install Device Signal Cable End(s)	ADSC_
▪ Install Device end DFCI Cable End(s)	ADDC_
▪ Install Cables to Guide Arm	ADGH_
▪ Close Cable Guide Arm	CLGH_
6. GOAL: Card Cage - Card Removal	
▪ (Not used for Initial Install)	
7. GOAL: Card Cage - Model Change	
▪ (Not used for Initial Install)	
8. GOAL: Card Cage - Card Adds/Connections	
▪ Install Card end Signal Cable(s)	ACSC_
▪ Install Console Cable to Loon	ASLC1
▪ Install ECS Modem to Line	ASEM1
9. GOAL: RACK - Prepare for Power	
▪ Install Power Sequence Cable	ARSC1
▪ Install Power Cable	ARPC1
▪ Set Circuit breakers "ON"	SRCB1
▪ Set Device(s) to READY/ON	SDSR_
▪ Install SHORE Battery	ADSB1
10. GOAL: System - Prepare for Operation	
▪ Provide AC Power	ASAC1
▪ Power Up System Console	ASCP1
▪ Power Up System	ASYP1
▪ Verify POR sequence	VPOR_
▪ Perform IPL & verify sequence	AIPL_
▪ Verify Tape Drive Operation	VSTD1
▪ Verify ECS Modem Operation	VSEM1
11. GOAL: System - After Operational	
▪ Install remaining W.W. Cables	AWSC1
▪ Install remaining Comm Cables	ACMC1
12. GOAL: System - Dealing with problems	
▪ Power-Up problems	SPUP1
▪ IPL problems	SIPP1
Appended Charts	
▪ RACK Configuration list	RCKCL
▪ Cable Charts	DCABCT

## 1.4 Tasks for Upgrade/Install

0. Entry Module - Before Beginning	SETM2
1. GOAL: System - RACK Adds	
Position RACK	ASRP1
Set-Up RACK	ASRH1
2. GOAL: System - Prepare for Change	
Power Down System	RSYP1
Remove all AC Power	RSAC1
3. GOAL: RACK - Device Removes	
Open Cable Guide Arm	ODGH_
Disconnect Device Cables:	
Remove Device Power Cable(s)	RDPC1
Remove Device Signal Cable End(s)	RDSC_
Remove Device end DFCI Cable End(s)	RDDC_
Remove DFCI Cable Terminator	RDDT_
Prepare Device(s) for remove:	
Lock Shock Protection	LDSH_
Lock Shipping Wedges	LDSW1
Remove cables from Guide Arm	RDGH_
Close Cable Guide Arm	CDGH_
Lock Shipping Clamps	LDCH1
Mechanically remove Device:	
Assemble lifting tool	ALDH1
Assemble adapter tool	ALDH1
Assemble mounting tool	ALDH1
Remove Device from RACK	RLEV_
Remove mounting hardware	RDMH_
Install RACK Filler(s)	ARFH1
4. GOAL: System - RACK Removal	
Disconnect RACK cables:	
Remove Power Cable(s)	RRPC1
Remove Power Sequence Cable end	RRSC1
Remove Pwr Seq Cbl Terminator	RRST1
Remove RACK	RSRH1
5. GOAL: RACK - Device Adds	
Remove RACK Filler(s)	RRFH1
Mechanically Install Device:	
Install mounting hardware	ADMH_
Install Device in RACK	ADEV_
Disassemble mounting tool	RLDH1
Disassemble adapter tool	RLDH1
Disassemble lifting tool	RLDH1
Prepare Device(s) for running:	
Unlock Shipping Wedges	UDSW1
Unlock Shipping Clamps	UDCH1
Open Cable Guide Arm	ODGH_ (dup)
Verify Cable Terminators	VDCT_
Verify/Set Voltage Switches	SDVS_
Unlock Shock Protection	UDSH_
Set Address Switches	SDAS_
Set Device CB "ON" & chk pwr cbl	SDCB_
Connect Device cables ends:	
Install Device Pwr Cbl & set CB "ON"	ADPC1
Install Device Signal Cable End(s)	ADSC_
Remove DFCI Cable Terminator	RDDT_ (dup)
Install Device end DFCI Cable End(s)	ADDC_
Install DFCI Cable Terminator	ADDT_
Install Cables to Guide Arm	ADGH_
Close Cable Guide Arm	CDGH_ (dup)
6. GOAL: Card Cage - Card Removal	

<ul style="list-style-type: none"> <li>Remove Card end Signal Cable(s)</li> <li>Remove Card</li> </ul>	RCSC_
7. GOAL: Card Cage - Model Change	RCDT_
<ul style="list-style-type: none"> <li>Remove Bus Cable</li> <li>Remove Card Cage</li> <li>Install Card Cage</li> <li>Install Bus Cable(s)</li> </ul>	RDBC1 RDCG1 ADCG1 ADBC1
8. GOAL: Card Cage - Card Adds/Connections	
<ul style="list-style-type: none"> <li>Add Card</li> <li>Install Card end Signal Cable(s)</li> <li>Install Console Cable to Loon</li> <li>Install ECS Modem to Line</li> </ul>	ACDT_ ACSC_ ASLC1 ASEM1
9. GOAL: RACK - Prepare for Power	
<ul style="list-style-type: none"> <li>Remove Pwr Seq Cbl Terminator</li> <li>Install Power Sequence Cable</li> <li>Install Pwr Seq Cbl Terminator</li> <li>Install Power Cable</li> <li>Set Circuit breakers "ON"</li> <li>Set Device(s) to READY/ON</li> <li>Install SHORE Battery</li> </ul>	RRST1 (dup) ARSC1 ARST1 ARPC1 SRCB1 SDSR_ ADSBI
10. GOAL: System - Prepare for Operation	
<ul style="list-style-type: none"> <li>Provide AC Power</li> <li>Power Up System Console</li> <li>Power Up System</li> <li>Verify POR sequence</li> <li>Perform IPL &amp; verify sequence</li> <li>Verify Tape Drive Operation</li> <li>Verify ECS Modem Operation</li> </ul>	ASAC1 ASCP1 ASYP1 VPOR_ AIPL_ VSTD1 VSEM1
11. GOAL: System - After Operational	
<ul style="list-style-type: none"> <li>Install remaining W.W. Cables</li> <li>Install remaining Comm Cables</li> </ul>	AWSC2 ACMC2
12. GOAL: System - Dealing with problems	
<ul style="list-style-type: none"> <li>Power-Up problems</li> <li>IPL problems</li> <li>Cable label problems</li> </ul>	SPUP1 SIPP1 SPCL1
Appended Charts	
<ul style="list-style-type: none"> <li>RACK Configuration list</li> <li>Cable Charts</li> </ul>	RCKCL DCABCT

## 1.5 Pseudo Tasks

Definition - Any actions or preparations other than the physical tasks required to perform an installation are "Pseudo Tasks".

- |  |       |
|--|-------|
| ▪ Verify that the order list is complete and correct.            | PVOL_ |
| ▪ Verify that Reference Material callouts are available.         | PVRM_ |
| ▪ Verify that RACK contents match displayed view.                | PVRF_ |
| ▪ Verify that Card Cage contents match displayed view.           | PVCC_ |
| ▪ Notify installer to label the cable <P/N> with cable ID <EID>. | PNLC_ |
| ▪ Notify installer that cable to be installed is labeled <EID>.  | PNCL_ |
| ▪ Notify installer to package removed components for shipment.   | PNPS_ |
| ▪ Notify installer to run IMA option for Upgrade Topology.       | PNUT_ |
| ▪ Notify installer that installation is complete.                | PNSC_ |
| ▪ Notify installer of "System Down Time" <STIME>.                | PNST_ |
| ▪ Provide Education of "how to Handle Cards".                    | PNHC_ |
| ▪ Provide Education of "how to Add Cards".                       | PNAC_ |
| ▪ Provide Education of "how to Remove Cards".                    | PNRC_ |
| ▪ Display RACK front view.                                       | PDRF_ |
| ▪ Display RACK rear view.  | PDRR_ |
| ▪ Display Card Cage rear view.                                   | PDCC_ |

## 1.6 Interpreting the Goal Flow Sequencing Charts

1. There are two types of Goal Flow sequencing relationships. Horizontal sequencing - where the "TASK" is selected and elements are sub-sequenced by position. Vertical sequencing - where the "ELEMENT" is selected by its position and the tasks are sub-sequenced.
  - Goals with numbers ending with "nn" trigger all tasks on the horizontal line simultaneously (horizontal sequencing). The secondary sequencing relationships for the triggered tasks are established by the positional rule for the goal section.
  - Goals with numbers ending in numeric digits may only trigger a single task sequence number (vertical sequencing). For those goals, the primary sequencing relationships are established by the positional rule for the section.
2. Goals with a "G" flag suffixed with the goal number allow grouping of identical tasks. When appropriate, the statement "Repeat this task for "N" elements" will be printed by SUU or "Inline" print processor.
3. Perspective relationships:
  - a. When goals deal with System perspective, the following abbreviations have been used:
    - R - RACK
    - S - System Card cage
  - b. When goals deal with RACK perspective, the following abbreviations have been used:
    - B - Expansion Card cage
    - KA - DASD Controller device
    - KB - DASD device
    - A - DASD device
    - P - Diskette device
    - F - Tape device
    - K - Tape device
    - N - Tape device
    - BS - Tape device
  - c. When goals deal with Card Cage perspective, the following abbreviations have been used:
    - V - "Vanilla" cards w/o tailgate assemblies
    - AF - Air Flow Cards
    - E - Expansion Bus extender Cards
    - SK - Cards w/ Single cable
    - MK - Cards w/ Multi-cables
4. Pseudo tasks have goals beginning with "Xnnnnn". They have no associated entries in the component task file.
  - The first digit of the pseudo task names will always be "P" (Pseudo)
  - The second digit of the pseudo task names define sub-type:
    - "D" - Display information or diagram.
    - "V" - Verify that correct conditions are met.
    - "N" - Notify installer of some process related activity.
  - The remaining digits of the pseudo task names provide uniqueness.

## 2.0 Detailed Goal listings

### 2.1 General - Before Beginning

Goal No	Pseudo Task description	Name	II	UG
X001nnn	Display Entry information: Verify SHORE (System) Ser No. Display "Time" information. 3 CE's req'd Lifter req'd ESD kit req'd & Handling Cards Back-Up DASD Erase DASD	SETM	1	2
	(PNCE) (PNLR,PNLA) (PNKR) (PNBD) (PNED)			

If "Parentage" fields indicate that RACK(s) will be affected by a component ADD or REMOVE upgrade change or Initial Install. Work from RACK A to RACK Z.

Goal No	Pseudo Task description	Name	II	UG
X00211n	Display a line drawing of the RACK front view. (Ask for verification of RACK configuration)	PVRF	2	1

If "Parentage" fields indicate that Card Cage(s) in the above RACK will be affected by the upgrade change or Initial Install. Work from top to bottom of the RACK.

Goal No	Pseudo Task description	Name	II	UG
X00212n	Display a line drawing of the Card Cage view. (Ask for verification of Card Cage contents)	PVCC	2	1

repeat step X00212n until last Card Cage is done.  
repeat steps X00211n through X00212n until last RACK is done

Goal No	Pseudo Task description	Name	II	UG
X0031nn	Display Entry information, Order parts list is complete.	PVOL	1	2
X0032nn	Ask Customer/Installer to verify that all SUU Ref material call-outs are available.	PVRM	1	1

Go to 010nnn



## 2.2 System - RACK Adds

010nnn If no new RACK or RACKS are on the order; go to 020nnn.  
 Else; Add new RACK(s)  
 Establish sub-sequence according to the following priority:  
 Work from RACK A to RACK Z.  
 (For RACK Positioning, use System planning forms as Reference.)

Goal No	Task Description	Name	R	BS
011nnn G	Position RACK(s)	ASRP	1	2
012nnn G	Setup RACK(s)	ASRH	1	2

If no RACK(s) contain devices w/ Element Source field = "P";  
 Go to 020nnn.  
 Else; "Prepare for running" any devices with Element Source  
 field = "P" (only for goals 013nnn, all of the other goals  
 are written for components with Element Source code = "F")  
 For goals 013nnn through 016nnn, establish sub-sequencing  
 according to the following priorities:  
 Work from RACK Z to RACK A.

Goal No	Pseudo Task description	Name	II	UG
X013nnn	Display a line drawing of RACK rear view for perspective.	PDRR	2	2

For goals 0131nn through 0136nn, establish sub-sequencing  
 according to the following priorities:  
 Work from bottom to top of RACK

Goal No	Task Description	Name	B	KA	KB	A	P	N	BS	F	K
0131nn G	Unlock Shipping Wedges	UDSW								1	
0132nn G	Unlock Shipping Clamps	UDCH		1	2					3	
01331n G	Open Cable Guide Arm	ODGH		1							
01332n	Verify Cable Terminators	VDCT		1		2	2			3	4L
01341n G	Verify/Set voltage switches	SDVS			1					2	
01342n G	Unlock Shock protection	UDSH			1						
0135nn	Set address switches	SDAS		1S		2S	3S			4S	5L
0136nn G	Set CB "ON" & chk Pwr Cbl	SDCB	1	5	2	6	7	7	8	3	4

Goal No	Pseudo Task description	Name
X015nnn	For each Inter-RACK cabling task, If it is the first end; label the cable with cable ID No.	PNLC
X015nnn	For each Inter-RACK cabling task, If it is the second end; Supply the cable ID No. previously labeled.	PNCL

For goals 0151nn through 016nnn, establish sub-sequencing according to the following priorities:  
Work from bottom to top of RACK

Goal No	Task Description	Name	KA	KB	A	P	N	BS	F	K
0151nn	Open Cable Guide Arm	ODGH		2					3	
0152nn	Install Device Signal Cbl End	ADSC	1P	2			3	4		
0153nn	Install Device DFCI Cable End	ADDC	1P		2P	2P			3P	4P
0154nn G	Install cables to Guide Arm	ADGH	1	2					3	

Goal No	Task Description	Name	KA	KB	A	P	N	BS	F	K
016nnn G	Close Cable Guide Arm	CDGH	1	2					3	

Repeat steps 013nnn through 016nnn until last RACK is done.

If Initial Installation; go to 0851nn.  
Else; Go to 020nnn.

## 2.3 System - Preparation for change

020nnn If a RACK with "P" element status devices have been added;

Goal No	Pseudo Task description	Name	II	UG
X020nnn	Notify Installer that the next task will require the system for <STIME> hours. (Note - This is a good time for a break)	PNST	-	1

Goal No	Task Description	Name	R	BS	S
021nnn	Power Down the System	RSYP			X
022nnn	Remove all AC System Power	RSAC	1	1	

Go to 030nnn.

## 2.4 RACK - Device removals

030nnn If no RACK mounted Device(s) will be added or removed,  
and if no RACKs will be removed; Go to 060nnn.  
Else; Go to 031nnn.

Establish RACK sequencing according to the following  
priority: Work from RACK A toward RACK Z.

Goal No	Pseudo Task description	Name	II	UG
X031nnn	Display a line drawing of RACK rear view for perspective.	PDRR	-	1
X031nnn	For each Device remove cable end task, if it is the first end; label it with the cbl ID No.	PNLC	-	-

Establish sub-sequence according to the following priorities:  
work from top to bottom of RACK

Goal No	Task Description	Name	B	KA	KB	A	P	N	BS	F	K
0311nn	Open Cable Guide Arm	ODGH		1	2					2	
0312nn	Remove Device Sig cbl end	RDSC		1P	2			3	4		
0313nn	Remove Device DFCI cbl end	RDDC		1P		2P	2P			3P	4P
0314nn	Remove Device power cables	RDPC	1	2	3	4	5	5		6	7L
0315nn	Remove DFCI Terminator(s)	RDDT		1		2	2			3	4L
03161n	Lock Shock Protection	LDSH			1	2	3	5	6	4	
0317nn	Remove cables in Guide Arm	RDGH		1	2					3	
0318nn	Close Cable Guide Arm	CDGH		1	2					3	
0319nn	Lock Shipping clamps	LDCH		1	2					3	
03201n	Assemble lifter to RACK	ALDH	1		1						
03202n	Assemble adapter to lifter	ALAH	1								
03203n	Assemble guiding hardware	ALMH	1								
0321nn	Remove Device(s) from RACK	RDEV	1	2	3	4	4	4		5	6L

If no similar Device(s) will be added back in the open location;

Goal No	Task Description	Name	B	KA	KB	A	P	N	BS	F	K
03221n	Remove guiding hardware	RLMH	1								
03222n	Remove adapter from lifter	RLAH	1								
03223n	Remove lifter from RACK	RLDH	1		1						
0323nn	Remove Mounting hardware	RDMH	1	2	5	1	1	1		3	4

Goal No	Task Description	Name	R
0324nn G	Remove RACK Filler(s)——	RRFH	1

If any devices are being permanently removed;

Goal No	Pseudo Task description	Name	II	UG
X033nnn	Notify the CE to package the components appropriately for shipment or storage.	PNPS	—	1

Go to 040nnn.

## 2.5 System - RACK Removals

040nnn If no RACK(s) are to be removed; Go to 050nnn.

If this is a "Relocate" remove only one end of any Inter-RACK cables. Do not remove any Intra-RACK cables.  
Establish sub-sequence according to the following priorities:  
work from top to bottom of RACK

Goal No	Task Description	Name	KA	KB	A	P	N	BS	F	K
0411nn G	Open Cable Guides	ODGH	1	2					3	
0412nn	Remove Device Signal Cable	RDSC	1P	2			3	4		
0413nn	Remove Device DFCI Cable	RDDC	1P		2P	2P			3P	4P
04141n G	Lock Shock Protection	LDSH		1	2	3	5	6	4	
04142n G	Lock Shipping Wedges	LDSW							1	
0415nn G	Close Cable Guides	CDGH	1	2					3	
0416nn G	Lock Shipping clamps	LDCH	1	2					3	

Goal No	Task Description	Name	R	BS
0417nn	Remove AC Pwr cable end	RRPC	1	1
0418nn	Remove Pwr Seq cable end	RRSC	1P	1P
0419nn	Remove RACK	RSRH	1	2

If this is not the last RACK; Go to 0310nn.

If this process is a system "tear-down"; End here.  
Else; Go to 050nnn.

## 2.6 RACK - Device Adds/Connections

050nnn If any Device(s) are to be ADDED to RACK(s);  
(Devices being moved to a RACK qualify as ADDs)

Establish sub-sequence according to the following priorities:  
work from bottom to top of RACK  
If no previous remove has left mounting hardware in place;

Goal No	Task Description	Name	B	KA	KB	A	P	N	BS	F	K
0521nn	Install mounting hardware	ADMH	1	2	5	1	1	1		3	4

If no previous remove has left lifter in place;

Goal No	Task Description	Name	B	KA	KB	A	P	N	BS	F	K
05221n	Assemble lifter to RACK	ALDH	1		1						
05222n	Assemble adapter to lifter	ALAH	1								
05223n	Assemble guiding hardware	ALMH	1								

If any Device(s) are to be added to RACK(s);

Goal No	Task Description	Name	B	KA	KB	A	P	N	BS	F	K
0523nn	Install device(s) to RACK	ADEV	1	2	3	4	4	4		5	6L
05241n	Remove guiding hardware	RLMH	1								
05242n	Remove adapter from lifter	RLAH	1								
05243n	Remove lifter from RACK	RLDH	1		1						
0525nn	Unlock Shipping clamps	UDCH		1	2					3	
05261n	Open Cable Guides	ODGH		1	2					3	
05262n	Verify Cable Terminator	VDCT		1		2	2			3	4L
0527nn	Unlock Shock Protection	UDSH			1						
0528nn	Verify/Set voltage switches	SDVS			1					2	
0529nn	Set address switch	SDAS		1S		2S	3S			4S	5L
0531nn	Install Power Cbl & set CB	ADPC	1	2	3	4	5	5		6	7L

If there are Intra-RACK Signal cable ends to install;  
(Note - A DFCI cable to a DASD Controller card must be treated as an Inter-RACK cable.)

When one cable end of an Intra-RACK cable is installed, sequence the other end next.

Establish sub-sequence according to the following priority:  
work from bottom to top of RACK

Goal No	Task Description	Name	KA	KB	A	P	N	BS	F	K
0541nn	Install Device Signal Cbl End	ADSC	1P	2			3	4		

If the DFCI terminator will be moved in the same RACK;

Goal No	Task Description	Name	KA	KB	A	P	N	BS	F	K
0542nn	Remove Device DFCI Terminator	RDDT	1		2	2			3	4L
0543nn	Install Device DFCI Terminator	ADDT	1		2	2			3	4L

If the DFCI terminator will be moved to another RACK;

Goal No	Task Description	Name	KA	KB	A	P	N	BS	F	K
0544nn	Remove Device DFCI Terminator	RDDT	1		2	2			3	4L

If there are Intra-RACK DFCI cable ends to install;

Goal No	Task Description	Name	KA	KB	A	P	N	BS	F	K
0545nn	Install Device DFCI Cable End	ADDC	1P		2P	2P			3P	4P

Connect Device Inter-RACK cable ends.

Goal No	Pseudo Task description	Name
X055nnn	For each Inter-RACK cabling task, If it is the first end; label the cable with cable ID No.	PNLC
X055nnn	For each Inter-RACK cabling task, If it is the second end; Supply the cable ID No. previously labeled.	PNCL

Establish sub-sequence according to the following priority:  
work from bottom to top of RACK

Goal No	Task Description	Name	KA	KB	A	P	N	BS	F	K
0551nn	Install Device Signal Cbl End	ADSC	1P	2			3	4		
0553nn	Install Device DFCI Cable End	ADDC	1P		2P	2P			3P	4P
0554nn	Install cables to Guide Arm	ADGH	1	2					3	

Goal No	Task Description	Name	KA	KB	A	P	N	BS	F	K
056nnn	Close Cable Guide Arm	CDGH	1	2					3	

Goal No	Task Description	Name	R
0571nn	Install RACK Filler (1 HI)	ARFH	1
0572nn	Install RACK Filler (3 HI)	ARFH	2
0573nn	Install RACK Filler (5 HI)	ARFH	3

If last RACK is not done; Go to 0310nn.

If Inter-RACK DFCI cable ends were installed, the DFCI terminator may need to be re-added.  
Work from Top to Bottom of Rack.  
Work from RACK Z to RACK A.

Goal No	Task Description	Name	KA	KB	A	P	N	BS	F	K
058nnn	Install Device DFCI Terminator	ADDT	1		2	2			3	4L

Go to 060nnn.



## 2.7 Card Cage - Card Removes

If no model change or card change upgrades remain;  
Go to 0851nn.

060nnn If any Card(s) are to be Added or Removed;  
(Cards being moved qualify as Remove then Add)

Goal No	Pseudo Task description	Name	II	UG
X06001n	Educate installer how to Remove cards	PNRC	—	1
X060021	Educate installer how to Add cards w/ports	PNAC	—	3
X060022	Educate installer how to Add cards w/o ports	PNAC	—	1
X060023	Educate installer how to Add airflow cards	PNAC	—	2

(When earliest PNAC task is triggered by associated "ACDTn—" task, the remaining PNAC task(s) must be discarded)

Establish sub-sequence according to the following priorities:  
work from RACK Z to RACK A.

Goal No	Pseudo Task description	Name	II	UG
X0601nn	Display a line drawing of RACK rear view for perspective.	PDRR	—	1

Establish sub-sequence according to the following priorities:  
work from top to bottom of RACK.

Goal No	Pseudo Task description	Name	II	UG
X0602nn	Display a line drawing of Card Cage rear view for perspective.	PDCC	—	1

Establish primary sequence according to the following priority:  
work from left to right of Card cage.

Goal No	Pseudo Task description	Name
X061nnn	For each card remove cabling task; label the cable with cable ID No.	PNLC

If any card(s) will be permanently removed from this Card Cage;  
For card cabling tasks, establish sub-sequence according to the  
following priority:

Work from top to bottom of Card Tail Gate.

Goal No	Task Description	Name	V	AF	E	SK	MK
061nn2	Remove Card Signal Cable end	RCSC			1G	2G	3G
061nn3	Remove Card	RCDT	1V	2V	3W	3W	3W

## 2.8 Card Cage - Model Change

If this is a model change from "650" to "660":

Goal No	Task Description	Name	B
071nnn	Remove Bus Cable	RDBC	1M
072nnn	Remove Card Cage	RDCG	1
073nnn	Install Card Cage	ADCG	1
074nnn	Install Bus Cable	ADBC	1M

If this is a model change from "630 or 640" to "660":

Goal No	Task Description	Name	B
072nnn	Remove Card Cage	RDCG	1
073nnn	Install Card Cage	ADCG	1
074nnn	Install Bus Cable	ADBC	1M

Reminder note - How will we handle the cables for:

- a) Continuous power
- b) Remote power-on

If this is a model change from "630 or 640" to "650":

Goal No	Task Description	Name	B
074nnn	Install Bus Cable	ADBC	1M

Note - A model change from "630" to "640" will be accomplished by a Card Remove/Add in group 080nnn.

## 2.9 Card Cage - Card Adds/Connections

If any cards will be relocated in the same Card Cage;

Goal No	Pseudo Task description	Name
X08nnnn	For each card cabling task, If it is the second end; supply the cable ID No.	PNCL

Establish PRIMARY sequence according to the following priority:

If cards are being relocated to higher number card slots;  
work from right to left in Card cage.

If cards are being relocated to lower number card slots;  
work from left to right in Card cage.

Goal No	Task Description	Name	V	AF	SK	MK	E
080nn1	Remove Card Signal Cable end	RCSC			1G	2G	3G
080nn2	Remove Card	RCDT	1V	2V	3W	3W	3W
080nn3	Install Card	ACDT	1V	2V	3W	3W	3W
080nn4	Install Card Signal Cable end	ACSC			1G	2G	3G

If any cards are to be ADDED;

Establish primary sequence according to the following priority:  
work from right to left in Card cage.

Goal No	Task Description	Name	V	AF	SK	MK	E
084nnn	Install Card	ACDT	1V	2V	3W	3W	3W

Goal No	Pseudo Task description	Name	II	UG
X0842nn	Display a line drawing of the Card Cage view. (Ask for verification of Card Cage contents)	PVCC	-	3

Repeat Steps 0602nn through 084nnn until last card cage is done.

Repeat Steps 0601nn through 084nnn until last RACK is done.

0851nn If no cable ends need to be attached to card connectors;  
Go To 088nnn.

0852nn If the previous parentage was RACK A; Go To 0861nn.

Establish sub-sequence according to the following priorities:  
work from RACK A to RACK Z.

Goal No	Pseudo Task description	Name	II	UG
X0852nn	Display flat drawing of RACK rear view for perspective.	PDRR	2	2

0861nn If the previous parentage was the lowest Card Cage;  
Go To 087nnn.

Establish sub-sequence according to the following priorities:  
work from bottom to top of RACK.

Goal No	Pseudo Task description	Name	II	UG
X0861nn	Display flat drawing of Card Cage rear view for perspective.	PDCC	2	2

Establish primary sequence according to the following priority:  
work from left to right of Card cage.

Goal No	Pseudo Task description	Name
X087nnn	For each card DFCI Inter-RACK cabling task; supply the previously labeled cable ID No.	PNCL

Establish sub-sequence according to the following priority:  
work from bottom to top of Card Tail Gate.  
(For Initial Install, install only one ECS Comm cable)

Goal No	Task Description	Name	V	AF	SK	MK	E
0872nn	Install Card Signal Cable end	ACSC			1G	2G	3G

Repeat steps 0861nn through 0872nn for next cage.  
Continue until last cage is done.

Repeat steps 0852nn through 0872nn for next RACK.  
Continue until last RACK is done.

088nnn If this is an Initial Installation;

Goal No	Task Description	Name	
0881nn	Install Console Cable to Loon	ASLC	1
0882nn	Install ECS Modem to Line	ASEM	1

## 2.10 RACK - Prepare for Power-Up

If no RACK ADDs or removes have been done; Go to 092nnn.  
 09000n If the previous parentage was RACK A; Go To 0901nn.

Establish sub-sequence according to the following priorities:  
 work from RACK A to RACK Z.

Goal No	Pseudo Task description	Name	II	UG
X09001n	Display flat drawing of RACK rear view for perspective.	PDRR	2	2

Goal No	Task Description	Name	R	BS
0901nn	Remove Pwr Seq cbl Terminator	RRST	1	1
0902nn	Install Pwr Seq cable end	ARSC	1P	1P
0903nn	Install Pwr Seq cbl Terminator	ARST	1	1
0911nn	Install AC pwr Cable end	ARPC	1	1
0913nn	Set RACK C.B.s "ON"	SRCB	1	1

Repeat Steps 09001n through 0913nn until last RACK is done.

092nnn If RACK(s) contain new devices;  
 Establish sub-sequence according to the following priorities:  
 work from RACK Z to RACK A.

Goal No	Pseudo Task description	Name	II	UG
X092nnn	Display flat drawing of RACK front view for perspective.	PDRF	2	2

Establish sub-sequence according to the following priority:  
 work from top to bottom of RACK

Goal No	Task Description	Name	R	B	KA	KB	A	P	N	BS	F	K
0921nn G	Unlock Shock protection	UDSH					2	3	5	6	4	
09221n G	Set Device to READY/ON	SDSR	1							2		
09222n G	Set Device to READY/ON	SDSR			2	3	4	5	7	8	6	
0923nn	Install Shore Battery	ADSB		1								

Repeat Steps 092nnn until last RACK is done.

## 2.11 System - Prepare for Operation

Provide AC Power to all Units of the system.

Goal No	Task Description	Name	II	UG
1001nn G	Provide AC Power	ASAC	1	1
1002nn	Power Up the System Console	ASCP	1	-
1003nn	Power Up the System	ASYP	1	2

If any new RACKs or Devices have been added;  
Sequence from RACK A to RACK Z.  
Sequence from Top to Bottom of RACK.  
(Group the VPORn tasks by RACK for now)

Goal No	Task Description	Name	R	B	KA	KB	A	P	N	BS	F	K
1011nn G	Verify POR Sequence	VPOR	1							2		
1012nn G	Verify POR Sequence	VPOR		2	3	4	5	6	9	A	7	8

Note: Invalid POR indications will reference remedial action task (SPUP)

Goal No	Task Description	Name		B	KA	KB	A	P	N	BS	F	K
1021nn G	Verify Tape Drive	VSTD							3	4	1	2
1022nn	Perform System IPL	AIPL	1*									
1023nn	Verify ECS Modem	VSEM	1									

Note: Failure to IPL properly will reference remedial action task (SIPP)

Goal No	Pseudo Task description	Name	II	UG
X1031nn	Notify Installer to run "IMA" option of SUU to update the system topology file. (Print out new system diagrams and cbl charts, Replace the old versions in PAR library)	PNUT	-	1
X1032nn	Notify customer of system availability.	PNSA	1	1

## 2.12 System - After Operational

Goal No	Pseudo Task description	Name	II	UG
X111nnn	Add remaining Work Station cables. (TCAW)	AWSC	1	2
X112nnn	Add remaining Communications cables. (TCAW)	ACMC	1	2
X113nnn	Notify CE of Parts Disposition (MODEL)	PNPS		1
X114nnn	Notify CE that installation is complete. Replace all reference materials in the appropriate library. Tie all loose cables as required. (CTIE) Close all open RACK covers. Throw away the Installation Instructions.	PNSC	1	1

## 2.13 System - Dealing with Problems

Goal No	Pseudo Task description	Name	II	UG
X121nnn	Deal with Power-On problems.	SPUP	1	1
X122nnn	Deal with failure to IPL problems.	SIPP	1	1
X123nnn	Deal with cable labeling problems. (iff RDSC or RDDC or RCSC)	SPCL		1

## 1.0 HIRS Layer 3 Low Level Design (I1)

The HIRS Layer 3 Low Level Design is based off the "SILVERLAKE HARDWARE CHANGE SEQUENCE" Document, Number ROC-SLS-R0001-002. Refer to this document for information on tasks and task sequencing goals.

### 1.1 HIRSL3 for Upgrades

The following describes the control flow of the HIRS Layer 3 Sequencing Rules for Upgrades/Initial Install.

#### RULE DEFINITION

INITIALIZE Declare Variables, Files, and Buffers.

#### ON ENTRY

1. Allocate a Control Working Memory Element.
2. Turn the Control flag "ON" to retrieve the first/next Intermediate Delta file.
3. Open the HIRS Control file.

REQUEST Retrieve the first/next HIRS Sequencing Request

1. Call RCVRQST to retrieve the first/next Intermediate Delta file.
2. If there are NO more Intermediate Delta files to be processed:
  - a. Free the Control Working Memory Element.
  - b. Terminate HIRS Layer 3 processing.
3. Open the Intermediate Delta file.
4. For each record in the Intermediate Delta file:
  - a. Read the record from the Intermediate Delta file.
  - b. Allocate a Working Memory Element for the record.
  - c. For all Card records, calculate the Card Address.
5. Close the Intermediate Delta file.
6. Turn the Control flag "OFF" to execute the Layer 3 Sequencing Rules.

PSEUDOF Process the preliminary Pseudo Tasks

- The following characteristics govern the selection of Working Memory Elements for this Rule:
  - The type of Task must be:
    - Universal Task
    - Universal Initial Install Task
    - Universal Upgrade Task
    - Adding of a New Rack
    - Modifying an Old Rack
    - Modifying an Old Device
  - The Task Perspective must be "PSEUDO"
  - The Task State must be "Task Precedes All Others"
  - The Task Sequence Number must NOT be assigned yet
- The following characteristics govern the ordering of the Working Memory Elements for this Rule:
  1. The Goal Sequence Step Number is in ascending order
  2. Work from Rack A to Rack Z
  3. The Update Sequence Step Number is in ascending order
  4. Work from the Top to the Bottom of the Rack



- The following characteristics govern the removing of the Working Memory Elements for this Rule:
  - The Task must be "PVERF2"
  - The Rack Location (LCNL) must be "00" (Rack A)

#### RACKADD Process Rack Add Tasks

- The following characteristics govern the selection of Working Memory Elements for this Rule:
  - The type of Task must be Adding of a New Rack
  - The Task Perspective must be "SYSTEM"
  - The Task State must be "Task Precedes All Others"
  - The Task Direction must be from Lowest to Highest
  - The Task Sequence Number must NOT be assigned yet
- The following characteristics govern the ordering of the Working Memory Elements for this Rule:
  1. The Goal Sequence Step Number is in ascending order
  2. The Update Sequence Step Number is in ascending order
  3. Work from Rack A to Rack Z

#### PIDFIDC Process Rack Add Tasks for Plant Installed Devices and Field Installed Device Cables

- The following characteristics govern the selection of Working Memory Elements for this Rule:
  - The type of Task must be Adding of a New Rack
  - The Task Perspective must be "RACK"
  - The Task State must be BLANK or "Only if Cabling Required".
  - The Task Direction is ignored
  - The Task Sequence Number must NOT be assigned yet
  - The WME must be one of the following types:
    - A Tower Element
    - A Plant Installed Device
    - A Field Installed Device Cable
- The following characteristics govern the ordering of the Working Memory Elements for this Rule:
  1. Work from Rack Z to Rack A
  2. The Goal Sequence Step Number is in ascending order
  3. The Update Sequence Step Number is in ascending order
  4. For Plant Installed Devices, work from the Bottom to the Top of the Rack
  5. For Field Installed Device Cables, work from the Bottom to the Top of the Rack
  6. When A Task is sequenced and it is a Group Task (GROUP = 'G'), find all similar Tasks in Its' Group and sequence them next.
- The following characteristics govern the removing of the Working Memory Elements for this Rule:
  - The Task State must be "Only if Cabling Required".
  - There is NOT a Field Installed Device Cable for the particular Device

#### SYSPREP System Preparation for Change

- The following characteristics govern the selection of Working Memory Elements for this Rule:
  - The type of Task must be:
    - Universal Upgrade Task
    - Modifying an Old Rack
  - The Task Perspective must be "SYSTEM"
  - The Task State must be BLANK
  - The Task Direction must be BLANK
  - The Power Status will be Ignored

- The Task Sequence Number must NOT be assigned yet
- The following characteristics govern the ordering of the Working Memory Elements for this Rule:
  1. The Goal Sequence Step Number is in ascending order
  2. Work from Rack A to Rack Z
  3. The Update Sequence Step Number is in ascending order

#### RACKCHGS Process Rack Changes for Device Removes, Rack Removes, and Device Adds/Connections

- The following characteristics govern the selection of Working Memory Elements for this Rule:
  - The type of Task must be:
    - Add a Device
    - Add a Cable
    - Add a Terminator
    - Remove a Rack
    - Remove a Device
    - Remove a Cable
    - Remove a Terminator
  - The Task Perspective must be "RACK"
  - The Task State must be:
    - BLANK
    - Add Only if NOT Added Previously
    - Remove Only if NOT used Again
    - A Numeric value 0-9
  - The Task Direction is Ignored
  - The Power Status must be DOWN
  - The Task Sequence Number must NOT be assigned yet
- The following characteristics govern the ordering of the Working Memory Elements for this Rule:
  1. Work from Rack A to Rack Z
  2. For Removes, work from the Top to the Bottom of the Rack
  3. For Adds, work from the Bottom to the Top of the Rack
  4. The Goal Sequence Step Number is in ascending order
  5. The Update Sequence Step Number is in ascending order
  6. Group All Sequenced Tasks with the same Task ID together
- The following characteristics govern the removing of the Working Memory Elements for this Rule:
  - When the STATE is "Add Only if NOT Added Previously" and there is a matching Device Task that was done previously, remove the Working Memory Element.
  - When the STATE is "Remove Only if NOT used Again" and there is a matching Device Task that will be done later, remove the Working Memory Element.
  - When the STATE is "A Numeric value 0-9" and there is a matching Add/Remove Device Mounting Hardware Task for the same EIA Location, remove both Working Memory Elements.

#### TERMAADS Process Terminator Adds to a Rack

- The following characteristics govern the selection of Working Memory Elements for this Rule:
  - The type of Task must be:
    - Add a Terminator
  - The Task Perspective must be "SYSTEM"
  - The Task State must be BLANK
  - The Task Direction is Low to High
  - The Power Status must be DOWN
  - The Sub Component Code must be T (Terminator)

- The Task Sequence Number must NOT be assigned yet
- The following characteristics govern the ordering of the Working Memory Elements for this Rule:
  1. Work from Rack Z to Rack A
  2. Work from the Top to the Bottom of the Rack

#### CARDMOVE Process Card Moves

- The purpose of this Rule is to assign a Card Movement Direction for the shifting of Cards in a Card Cage and any Cables associated with the Cards.
- The following characteristics govern the selection of Working Memory Elements for this Rule:
  - The type of Task must be "Removing Cards"
  - The Associated type of Task must be
    - Adding Cards
    - Adding Cables
    - Removing Cables
  - The Handling Code is MOVE
  - The Task Perspective must be "CARD CAGE"
  - The Task State must be BLANK
  - The Task Direction must be BLANK
  - The Power Status must be DOWN
  - The Task Sequence Number must NOT be assigned yet
- The following characteristics govern the assigning of a Direction for the Working Memory Elements for this Rule:
  1. If there is an Associated Add Card Task, assign the direction based on the following criteria:
    - If the Card is being added into a Higher Card Slot location, assign a direction of High (H).
    - If the Card is being added into a Lower Card Slot location, assign a direction of Low (L).
  2. If there are Associated Add/Remove Cable Tasks for the Card being moved, assign the direction to be the same as the Associated Add/Remove Card Task.

#### PCHNDL Process Card Handling Information Tasks

- The following characteristics govern the selection of Working Memory Elements for this Rule:
  - The type of Task must be:
    - Universal Upgrade Only
  - The Task Perspective must be "PSEUDO"
  - The Task State must be BLANK
  - The Task Direction is Low to High
  - The Power Status must be DOWN
  - The Task Sequence Number must NOT be assigned yet
- The following characteristics govern the ordering of the Working Memory Elements for this Rule:
  1. The Goal Sequence Step Number is in ascending order
  2. The Update Sequence Step Number is in ascending order
- The following characteristics govern the removing of the Working Memory Elements for this Rule:
  1. If there are Remove Card (RCDTxxx) Tasks, then sequence the Remove Card Info (PNRC1) Task, otherwise remove it from WM.
  2. If there are Add Card 300 (ACDT3xx) Tasks, then sequence the Add Card 300 Info (PNAC3) Task, otherwise remove it from WM.

3. If there are Add Card 100 (ACDT1xx) Tasks and the PNAC3 Task was NOT sequenced, then sequence the Add Card 100 Info (PNAC1) Task, otherwise remove it from WM.
4. If there are Add Card 200 (ACDT2xx) Tasks and the PNAC3 and PNAC1 were NOT sequenced, then sequence the Add Card 200 Info (PNAC2) Task, otherwise remove it from WM.

#### CCUPGDS Process Card Cage Upgrades

- The following characteristics govern the selection of Working Memory Elements for this Rule:
  - The type of Task must be:
    - Removing Cards
    - Model Upgrade
    - Adding Cards
    - Cable Remove
    - Cable Add
    - Modified Card Cage
  - The Task Perspective must be "CARD CAGE"
  - The Task State must be BLANK
  - The Task Direction is High or Low
  - The Power Status must be DOWN
  - The Task Sequence Number must NOT be assigned yet
  - The WME must be one of the following types:
    - A Card to be removed
    - A Signal Cable to be removed from a Card
    - A Card to be added
- The following characteristics govern the ordering of the Working Memory Elements for this Rule:
  1. Work from Rack Z to Rack A
  2. Work from the Top to the Bottom of the Rack
  3. The Goal Sequence Step Number is in ascending order
  4. Work from Left to Right of the Card Cage, if the Direction is LOW
  5. Work from Right to Left of the Card Cage, if the Direction is HIGH
  6. Work from the Top to the Bottom of the Card Tail Gate
  7. The Update Sequence Step Number is in ascending order
  8. For Move Tasks, Group All Associated Add/Remove Card/Cable Tasks together.
  9. For Remove Card/Cable Tasks, Group All Associated Remove Card/Cable Tasks together.

#### FLRCRD Find the System Console LYNX Card and the ECS MODEM REEF Card

- The following characteristics govern the selection of Working Memory Elements for this Rule:
  - The type of Task must be Rack Add
  - The Handling Code must be Add
  - The Task Perspective must be "PSEUDO"
  - The Task State must be "PSEUDO"
  - The Task Direction must be BLANK
  - The Power Status must be BLANK
  - The Task Sequence Number must NOT be assigned yet
- The following characteristics govern the ordering of the Working Memory Elements for this Rule:
  1. Lowest Bus Number
  2. Lowest Board Number
  3. Lowest Card Number
  4. The Specify Code (DVRPQ) must be 9641 for the ECS MODEM Cable.

- If the previous ordering characteristics were NOT met, the Working Memory Element will be removed.

#### CEATCRD Process Cable End Attachment to Card Connector Tasks

- The following characteristics govern the selection of Working Memory Elements for this Rule:
  - The type of Task must be Installing Cables
  - The Task Perspective must be "CARD CAGE"
  - The Task State must be "Last Card Cage Task"
  - The Task Direction must be from Lowest to Highest
  - The Task Sequence Number must NOT be assigned yet
- The following characteristics govern the ordering of the Working Memory Elements for this Rule:
  1. Work from Rack A to Rack Z
  2. Work from the Bottom to the Top of the Rack
  3. Work from the Left to the Right of the Card Cage
  4. Work from the Bottom to the Top of the Card Tail Gate
  5. The Goal Sequence Step Number is in ascending order
  6. The Update Sequence Step Number is in ascending order
- The following characteristics govern the removing of the Working Memory Elements for this Rule:
  - Remove all REEF Cabling Tasks except for the Reef Cable which hooks up to the ECS Modem to be installed. This REEF Cable attaches to the REEF Card found in Rule FLRCRD. Set the MORCOMM flag "ON" if any Cabling Tasks were removed.
  - Remove all LOON Cabling Tasks except for the Loon Cable which hooks up to the System Console to be installed. This LOON Cable attaches to the LYNX Card found in Rule FLRCRD. Set the MORLOON flag "ON" if any LOON Cabling Tasks were removed.

#### UNIVII Process Universal Initial Install Tasks

- The following characteristics govern the selection of Working Memory Elements for this Rule:
  - The type of Task must be Rack Add
  - The Handling Code must be Add
  - The Task Perspective must be "EXTRA"
  - The Task State must be BLANK
  - The Task Direction must be BLANK
  - The Power Status must be "DOWN"
  - The Task Sequence Number must NOT be assigned yet
- The following characteristics govern the ordering of the Working Memory Elements for this Rule:
  1. The Goal Sequence Step Number is in ascending order
  2. The Update Sequence Step Number is in ascending order
  3. Work from Top to Bottom of the Card Tail Gate
- The following characteristics govern the removing of the Working Memory Elements for this Rule:
  - Remove any Communications Cables that don't have a Specify Code of 9641.
  - Remove any Tasks that don't have a matching REEF or LYNX Card.
  - Remove the REEF and LYNX Card Tasks after the matching cables have been sequenced.

#### PRACUPU1 Process RACK (System) Prepare for Power-Up Tasks for Rack Adds

- The following characteristics govern the selection of Working Memory Elements for this Rule:
  - The type of Task must be "Add a New Rack"

- The Task Perspective must be "SYSTEM"
- The Task State must be BLANK
- The Task Direction must be from Lowest to Highest
- The Task Sequence Number must NOT be assigned yet
- The following characteristics govern the ordering of the Working Memory Elements for this Rule:
  1. Work from Rack A to Rack Z
  2. The Goal Sequence Step Number is in ascending order
  3. The Update Sequence Step Number is in ascending order
  4. Work from Left to Right for Power Sequence Cable Connectors

**PRACPUP2** Process RACK Prepare for Power-Up Tasks for Rack Adds

- The following characteristics govern the selection of Working Memory Elements for this Rule:
  - The type of Task must be:
    - Add a New Rack
    - Add a New Device
  - The Task Perspective must be "RACK"
  - The Task State must be "Task Follows All Others"
  - The Task Direction must be from Highest to Lowest
  - The Task Sequence Number must NOT be assigned yet
- The following characteristics govern the ordering of the Working Memory Elements for this Rule:
  1. Work from Rack Z to Rack A
  2. The Goal Sequence Step Number is in ascending order
  3. The Update Sequence Step Number is in ascending order
  4. Work from the Top to the Bottom of the Rack
  5. Group All Tasks with the same Task ID together

**PREFOP1** Process Prepare for Operation (Provide Power) Tasks

- The following characteristics govern the selection of Working Memory Elements for this Rule:
  - The type of Task must be:
    - Add a New Rack
    - Modify a Rack
  - The Task Perspective must be "SYSTEM"
  - The Task State must be "Task Follows All Others"
  - The Task Direction must be from Lowest to Highest
  - The Power Status must be "DOWN"
  - The Task Sequence Number must NOT be assigned yet
- The following characteristics govern the ordering of the Working Memory Elements for this Rule:
  1. The Goal Sequence Step Number is in ascending order
  2. The Update Sequence Step Number is in ascending order
  3. Work from Rack A to Rack Z

**PREFOP2** Process Prepare for Operation (Power Up) Tasks

- The following characteristics govern the selection of Working Memory Elements for this Rule:
  - The type of Task must be:
    - Add a New Rack
    - Universal Task
    - Universal Initial Install Task
    - Universal Upgrade Task
  - The Task Perspective must be "EXTRA"

- The Task State must be "Task Follows All Others"
- The Task Direction must be BLANK
- The Power Status must be "DOWN"
- The Task Sequence Number must NOT be assigned yet
- The following characteristics govern the ordering of the Working Memory Elements for this Rule:
  1. The Goal Sequence Step Number is in ascending order
  2. The Update Sequence Step Number is in ascending order

**PREFOP3 Process Prepare for Operation (Verify) Tasks**

- The following characteristics govern the selection of Working Memory Elements for this Rule:
  - The type of Task must be:
    - Add a New Rack
    - Add a New Device
    - Model Upgrade
  - The Task Perspective must be "SYSTEM"
  - The Task State must be "Task Follows All Others"
  - The Task Direction must be from Highest to Lowest
  - The Power Status must be "UP"
  - The Task Sequence Number must NOT be assigned yet
- The following characteristics govern the ordering of the Working Memory Elements for this Rule:
  1. The Goal Sequence Step Number is in ascending order
  2. Work from Rack A to Rack Z
  3. The Update Sequence Step Number is in ascending order
  4. Work from the Top to the Bottom of the Rack
  5. Group all similar Devices together

**PREFOP4 Process Prepare for Operation (Extra Universal) Tasks**

- The following characteristics govern the selection of Working Memory Elements for this Rule:
  - The type of Task must be:
    - Universal Upgrade
    - Universal Initial Install
    - Rack Add Task
  - The Task Perspective must be "EXTRA"
  - The Task State must be "Task Follows All Others"
  - The Task Direction is ignored
  - The Power Status must be "UP"
  - The Task Sequence Number must NOT be assigned yet
- The following characteristics govern the ordering of the Working Memory Elements for this Rule:
  1. The Goal Sequence Step Number is in ascending order
  2. The Update Sequence Step Number is in ascending order

**PSEUDOL Process the Final Pseudo Tasks**

- The following characteristics govern the selection of Working Memory Elements for this Rule:
  - The type of Task must be:
    - Universal Task
    - Universal Upgrade Task
    - Universal Initial Install Task
  - The Task Perspective must be "PSEUDO"
  - The Task State must be "Task Follows All Others"

- The Task Direction is ignored
- The Power Status must be "UP"
- The Task Sequence Number must NOT be assigned yet
- The following characteristics govern the ordering of the Working Memory Elements for this Rule:
  1. The Goal Sequence Step Number is in ascending order
  2. The Update Sequence Step Number is in ascending order
- The following characteristics govern the removing of the Working Memory Elements for this Rule:
  - If there are NO more LOON and COMM Cables to be Attached and there is a Notify Customer of System Availability (PNSAI) Task, remove it from WM.  
Note: The MORLOON and MORCOMM flags will be "OFF".
  - If there are NO more LOON Cables to be Attached and there is an Add Workstation Cable (AWSCx) Task, remove it from WM.  
Note: The MORLOON flag will be "OFF".
  - If there are NO more COMM Cables to be Attached and there is an Add Communications Cable (ACMCx) Task, remove it from WM.  
Note: The MORCOMM flag will be "OFF".

**CLEANUP** Update the Intermediate Delta file with the Sequenced Tasks.

This is the lowest level rule. It will be activated, when there are no more Sequencing rules to be run.

1. Open the Intermediate Delta file, again.
2. For each Working Memory Element Task:
  - a. Find the Working Memory Element Task with the Lowest Task Sequence Number.
  - b. If the Task Sequence Number is Zero "00000", the Task has not been Sequenced. The Task Sequence Number is set to "99999", to flag the Task as being non-sequenced (did NOT fit into any Rules).
  - c. If the Task Sequence Number is "99998", the LYNX or REEF Task has not been Sequenced. The Task Sequence Number is set to "99999", to flag the Task as being non-sequenced (A LOON or ECS MODEM Cable was NOT found).
  - d. Read a record out of the Intermediate Delta file.
  - e. (Re)Write the New Sequenced record to the Intermediate Delta file.
  - f. Free the Working Memory Element Task.
3. Close the Intermediate Delta file.
4. Turn the Control flag "ON" to activate the REQUEST rule.

**ON IDLE**

- Terminate IIIRS Layer 3 processing.



## 1.2 RCVRQST

The following describes the control flow of HIRS Layer 3 Receive Request, RCVRQST.

1. Include REXPLI, CMSCMD, and CONTROL Declare.
2. Declare Variables and Buffers.
3. Read the first/next record in the Control File.
4. If End-Of-File was reached:
  - a. Close the Control File.
  - b. Set the Return Code for RCVRQST to 1. (End-Of-File)
5. If End-of-File was NOT reached:
  - a. Call CMSCMD to perform a FILEDEF Command for the Intermediate Delta file.
  - b. If the Return Code from the FILEDEF Command is Zero, set the Return Code for RCVRQST to 0. (New Intermediate Delta file to process)
  - c. If the Return Code from the FILEDEF Command is NOT Zero:
    - 1) Display an Error Message to tell the User of the Error.
    - 2) Set the Return Code for RCVRQST to 2. (Error from FILEDEF)
6. Return to the REQUEST rule.

## APPENDIX III

## High End SYSTEM -- List of Variables and Switches

SYSTEM Setup/Upgrade Tasks Summary		Variables																														
		R	D	P	D	C	C	C	C	C	S	S	T	S	T	R	L	C	B	S	D	D	R	R	S	S	S	C	C			
ID	Abbreviated	A	L	V	L	O	L	L	Y	O	L	Y	Y	I	T	Y	T	A	C	N	P	O	O	R	C	C	E	Y	Y	E	E	
Task	Task Title	C	O	A	O	R	P	O	P	R	A	S	S	M	I	P	N	N	W	U	N	T	C	C	D	K	K	R	S	S	C	C
		K	C	D	C	T	N	T	E	T	B	T	N	E	H	E	M	G	T	H	2	T	T	1	N	T	1	N	M	D	T	H
ACCB—Inst/Conn Cable		X	X						X	X	X	X					X															
ACDT—Inst Card		X	X						X	X							X															
ACMC--Inst Rem Comm CbIs																																
ACSC--Inst Cable on Card		X	X						X	X	X						X															
ADBC—Inst Bus Cable		X	X					X																								
ADCG—Inst Card Cage		X	X																													
ADDC--Inst Dv DFCI Cbl End		X	X								X																					
ADDT—Inst Dv DFCI Cbl Trm		X	X																													
ADEV—Inst Device		X	X																													
ADGH--Inst Cables to Arm		X	X															X														
ADMH—Inst Mounting Hdwe		X	X																													
ADPC—Inst Dev Pwr Cable		X	X					X												X												
ADSB--Connect Bat Cable		X	X																													
ADSC--Inst Dev Sig Cable		X	X								X																					
AIPL--Perf IPL																																
ALAH—Inst Hoist Adapt		X																														
ALDH—Inst Hoist		X																														
ALMH—Inst Hoist Adapt Bar		X	X																													
ARCT—Inst Cbl Ties		X																														
ARFH—Inst RACK Filler		X	X																X													
ARPC--Install RACK Pwr Cbl		X																														
ARSC--Inst RK PwrSeqCblEnd		X						X																								
ARST—Inst PwrSeqCbl Term		X																														
ASAC--Provide AC Power		X																	X													
ASCP--Power On Sys Console																																
ASEM--Inst ECS Modem										X																						

SYSTEM Setup/Upgrade Tasks Summary		Variables																														
ID	Abbreviated Task Task Title	R	D	P	D	C	C	C	C	S	S	T	S	T	L	A	C	B	S	D	D	R	R	S	S	C	C					
		A	L	V	L	O	L	L	Y	O	L	Y	I	T	Y	T	A	C	N	P	O	O	O	R	C	C	E	Y	Y	E	E	
		C	O	A	O	R	P	O	P	R	A	S	S	M	I	P	N	N	N	U	N	T	C	C	D	K	K	R	S	S	C	C
		K	C	D	C	T	N	T	E	T	B	T	N	E	H	E	M	G	T	M	2	T	T	1	N	T	1	N	M	D	T	H
ASLC--	Inst System Console										X																					
ASRH--	Set-Up RACK	X															X															
ASRP--	Position RACK															X	X															
ASYP--	Turn System Power ON																					X										
AWSC--	Inst Rem WS Cbls																															
CDGH--	Close Cbl Guide Arm	X	X														X															
LDCH--	Lock Ship Clamps	X	X														X															
LDSH--	Lock Shock Protect	X	X														X															
LDSH--	Inst Ship Bracket	X	X														X															
ODGH--	Open Cbl Guide Arm	X	X														X															
PDCC--	Look at Inst Cards	X	X														X															
PDRF--	Go to the Front	X																														
PDRR--	Go to the Back	X																														
PNAC--	How to Inst Cards																															
PNCL--	Find Labeled Cable	X								X																						
PNHC--	How to Handle Cards																															
PNLC--	Label the Cable	X				X				X																						
PNPS--	Dispose Upgrd Parts																															
PNRC--	How to Rem Cards																															
PNSA--	Tell Cust Sys Avail																															
PNSC--	Setup Complete	X																														
PNST--	Notify of Sys Tkoer												X																			
PNUT--	Update Tplgy File																															
PVCC--	Verify Proper Cards	X	X														X															
PVOL--	Verify Loose Parts															X																
PVRF--	Verify Rack Content	X																														
PVRH--	Verify Ref Material																															

SYSTEM Setup/Upgrade Tasks Summary		Variables																																					
ID	Abbreviated Task Task Title	R	D	P	D	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C	C		
		A	L	V	L	O	L	L	Y	O	L	Y	I	T	Y	T	A	C	N	P	O	O	O	R	C	C	E	Y	Y	E	E	E	E	E	E	E	E	E	E
		C	O	A	O	R	P	O	P	R	A	S	S	M	I	P	N	N	N	U	N	T	C	C	D	K	K	R	S	S	C	C	C	C	C	C	C	C	C
		K	C	D	C	T	N	T	E	T	B	T	N	E	M	E	M	G	T	M	Z	T	T	1	N	T	1	N	M	D	T	M							
RCCB	Rem/Discon CbIs	X	X					X	X	X	X					X																							
RCDT	Rem Card	X	X					X	X							X																							
RCSC	Rem Cable from Card	X	X					X	X							X																							
RDBC	Rem Bus Cable	X	X																																				
RDCG	Rem Card Cage	X	X																																				
RDDC	Rem Dev DFCI Cbl End	X	X																																				
RDDT	Rem Dv DFCI Cbl Term	X	X																																				
RDEV	Rem Device	X	X																																				
RDGH	Rem Cables from Arm	X	X																																				
RDMH	Rem Mounting Hdwe	X	X																																				
RDPC	Rem Dev Pwr Cable	X	X																																				
RDSC	Rem Dev Sig Cable	X	X																																				
RLAH	Rem Hoist Adapt	X																																					
RLDH	Rem Hoist	X																																					
RLMH	Rem Hoist Adapt Bar	X	X																																				
RRCT	Rem Cbl Ties	X																																					
RRFH	Rem RACK Filler	X	X																																				
RRPC	Rem RACK Power Cable	X																																					
RRSC	Rem RK PwrSeqCblEnd	X																																					
RRST	Rem PwrSeqCbl Term	X																																					
RSAC	Rem all AC Power	X																X																					
RSRH	Rem RACK	X																																					
RSYP	Turn Sys Power Off																																						
SDAS	Verify/Set Address	X	X	X												X																							
SDCB	Set Device CB ON	X	X															X																					
SDSR	Set Device Switches	X	X															X																					
SDVS	Verify/Set Voltage	X	X															X																					

SYSTEM Setup/Upgrade Tasks Summary		Variables																														
ID	Abbreviated Task Task Title	R	D	E	P	P	B	S	T	P	B	S	S	T	S	T	R	L	C	B	S	D	D	R	R	S	S	S	C	C		
		A	L	V	L	O	L	L	Y	O	L	Y	Y	I	T	Y	T	A	C	N	P	O	O	O	R	C	C	E	Y	E	E	
		C	O	A	O	R	P	O	P	R	A	S	S	M	I	P	N	N	N	U	N	T	C	C	D	K	K	R	S	S	C	C
		K	C	D	C	T	N	T	E	T	B	T	N	E	M	E	M	G	T	M	Z	T	T	I	N	T	I	N	M	D	T	M
SETH--Entry Module		X	X									X	X	X	X		X							X			X	X	X	X	X	
SIPP--IPL Prob . . .																	X						X									
SMAC--Move Card		X	X					X	X								X						X	X		X						
SMCE--Move a cable end		X	X					X																								
SMCT--Move Dev Sig Cbl Trm		X	X																													
SMPT--Move Pwr Seq Term		X																							X							
SMTF--Modem Test Prob. . .																																
SPUP--Power Up Prob . . .																								X			X					
SRCB--Vrfy Dev Pwr Cbl/CBs		X																														
SSCF--Turn SysCons Pwr OFF																																
UDCH--Unlk Shipping Clamps		X	X															X														
UDSH--Unlk Shock Protect		X	X															X														
UDSH--Rem Ship Hedges		X	X															X														
VDCT--Verify Cbl Term		X	X																													
VPOR--Verify POR Ind		X	X															X														
VSEM--Test ECS Modem																								X								
VSTD--Verify Tape Load		X	X															X														
PARHDR--PAR header																																
RCKCL--PAR module 1		X																														
DCABCT--PAR module 2																																



SYSTEM Setup/Upgrade Tasks Summary		Switches Set to 'YES or to OFF															
ID	Abbreviated	M	M					F	L			N					
Task	Task Title	S	R	O	R	P	P	P	C	R	R	T	P	U	P	R	F
		I	A	D	O	N	N	N	N	T	A	A	C	N	P	N	A
		C	C	E	L	L	C	B	E	I	C	C	A	L	G	K	C
		E	K	L	L	R	E	D	D	E	K	K	H	A	R	R	K
ASLC--	Inst System Console																
ASRH--	Set-Up RACK				X												
ASRP--	Position RACK		X														
ASYP--	Turn System Power ON																
AHSC--	Inst Rem WS Cbls																
CDGH--	Close Cbl Guide Arm				X												
LDCH--	Lock Ship Clamps				X												
LDSH--	Lock Shock Protect				X												
LDSN--	Inst Ship Bracket				X												
ODGH--	Open Cbl Guide Arm				X												
PDCC--	Look at Inst Cards																
PDRF--	Go to the Front																
PDRR--	Go to the Back																
PNAC--	How to Inst Cards																
PNCL--	Find Labeled Cable																
PNHC--	How to Handle Cards																
PNLC--	Label the Cable																
PNPS--	Dispose Upgrd Parts			X													
PNRC--	How to Rem Cards																
PNSA--	Tell Cust Sys Avail																
PNSC--	Setup Complete	X			X				X			X	X				
PNST--	Notify of Sys TkoVer																
PNUT--	Update Tplgy File																
PVCC--	Verify Proper Cards																
PVOL--	Verify Loose Parts	X												X	X		
PVRF--	Verify Rack Content																
PVRM--	Verify Ref Material																

SYSTEM  
Setup/Upgrade  
Tasks Summary

		Switches Set to 'YES or to OFF															
ID	Abbreviated Task Task Title	M	M					F	L			N					
		S	R	O	R	P	P	P	C	R	R	T	P	U	P	R	F
		I	A	D	O	N	N	N	N	T	A	A	C	N	P	N	A
		C	C	E	L	L	C	B	E	I	C	C	A	L	G	K	C
		E	K	L	L	R	E	D	D	E	K	K	W	A	R	R	K
	RCCB—Rem/Disconn Cbls																
	RCDT—Rem Card																
	RCSC—Rem Cable from Card																
	RDBC—Rem Bus Cable																
	RDCG—Rem Card Cage																
	RDDC—Rem Dev DFCI Cbl End	X															
	RDDT—Rem Dv DFCI Cbl Term																
	RDEV—Rem Device																
	RDGH—Rem Cables from Arm																
	RDMH—Rem Mounting Hdwe																
	RDPC—Rem Dev Pwr Cable																
	RDSC—Rem Dev Sig Cable	X															
	RLAH—Rem Hoist Adapt																
	RLDH—Rem Hoist																
	RLMH—Rem Hoist Adapt Bar																
	RRCT—Remove Cbl Ties																
	RRFH—Rem RACK Filler				X												
	RRPC—Rem RACK Power Cable																
	RRSC—Rem RK PwrSeqCblEnd									X	X						
	RRST—Rem PwrSeqCbl Term									X							
	RSAC—Rem all AC Power				X												
	RSRH—Rem RACK																
	RSYP—Turn Sys Power Off	X															
	SDAS—Verify/Set Address																
	SDCB—Set Device CB ON				X												
	SDSR—Set Device Switches				X												
	SDVS—Verify/Set Voltage				X												



SYSTEM  
Setup/Upgrade  
Tasks Summary

ID      Abbreviated  
Task    Task Title

SYSTEM Setup/Upgrade Tasks Summary		Switches Set to 'YES or to OFF																					
		S	I	C	E	K	L	L	R	E	D	D	E	K	K	W	A	R	R	K	R	A	
ID	Abbreviated Task Task Title	M	R	O	E	L	L	R	P	P	P	C	R	R	T	P	U	P	R	F	F		
		H	A	D	I	C	E	L	L	R	E	D	D	E	K <th>K</th> <th>W</th> <th>A</th> <th>R</th> <th>R</th> <th>K</th> <th>R</th> <th>A</th>	K	W	A	R	R	K	R	A
	SETH--Entry Module								X	X	X	X					X	X					
	SIPP--IPL Prob . . .																						
	SMAC--Move Card																						
	SMCE--Move a cable end																						
	SMCT--Move Dev Sig Cbl Trm																						
	SMPT--Move Pwr Seq Term													X				X					
	SMTP--Modem Test Prob. . .																						
	SPUP--Power Up Prob . . .	X																X					
	SRCB--Vrify Dev Pwr Cbl/CBs																						
	SSCF--Turn SysCons Pwr OFF																						
	UDCH--Unlk Shipping Clamps							X															
	UDSH--Unlk Shock Protect							X															
	UDSH--Rem Ship Wedges							X															
	VDCT--Verify Cbl Term																						
	VPOR--Verify POR Ind							X															
	VSEM--Test ECS Modem																						
	VSTD--Verify Tape Load							X															
	PARHOR--PAR header																						
	RCKCL--PAR module 1																						
	DCABCT--PAR module 2																						

VARIABLE/SWITCH <sup>1</sup>	SYMBOL CODED	ALLOWABLE VALUES
Art Number	&ARTNM.	3-digits; numbers assigned
Cable Label	&CBLAB.	3-digit element ID
Cable P/N	&CBLPN.	NNNNNNN
Cable P/N (2nd)	&CBLPN2.	NNNNNNN
Card Cage Number	&CCNUM.	01 - 18
CEC Type	&CECT. <sup>3</sup>	NNNN
CEC Model	&CECM. <sup>3</sup>	NNN
Count of devices	&CNT.	2-N
Card Port	&CPORT.	1 - 4
Card Slot	&CSLOT.	1 - 14
Card Slot (to)	&CSLOTT.	1 - 14
Card Type	&CTYPE.	XXXX
Device Address <sup>2</sup>	&DEVAD.	0-7
Device Location	&DLOC.	1 - 32; string of values
Device Location (to)	&DLOCT.	1 - 32
CEC Loc in Rack A	&DLOC1. <sup>3</sup>	1 - 32
Device Port	&DPORT.	In, Out, 1, 2, 3, 4
Language	&LANG. <sup>3</sup>	0-9; A-Z (1-digit/lang)
Line Type	&LTYPE.	AAAAAAAAAAAAAAAAAAAA
Order Number	&ORDN. <sup>3</sup>	NNNNNNNNN
Pwr Plug Location	&PPLOC.	J1 - J10
Rack	&RACK.	A, B, C, D, etc.
Rack (to)	&RACKT.	A, B, C, D, etc.
Last Rack	&RACK1. <sup>3</sup>	B, C, D, etc.
Release Version	&RELVER. <sup>3</sup>	NNNN
CEC Serial Number	&SERN. <sup>3</sup>	NN-NNNNNNN
Dedicated Sys Time	&STIM. <sup>3</sup>	NN.N (hours)
System Date (build)	&SYSD. <sup>3</sup>	YYYYMMDD
System Type	&SYSM. <sup>3</sup>	NNNN
System Model	&SYSN. <sup>3</sup>	NNNNNNN
System Time (build)	&SYST. <sup>3</sup>	HHMMSS
Time to complete	&TIME. <sup>3</sup>	NN.N (hours)
Install Cable Ties	&CTIE. <sup>3</sup>	'YES/OFF
First hoist adapt use	FNLA	'YES/OFF
First hoist use	FNLR	'YES/OFF
First Rack	FRACK	'YES/OFF
Last Rack	LRACK	'YES/OFF
Model Upgrade	MODEL <sup>3</sup>	'YES/OFF
Multiple Racks	MRACK <sup>3</sup>	'YES/OFF
New Rack	NRACK <sup>3</sup>	'YES/OFF
Back up DASD	PNBD <sup>3</sup>	'YES/OFF
2-people Required	PNCE <sup>3</sup>	'YES/OFF
Erase Sens Matl	PNED <sup>3</sup>	'YES/OFF
ESD Kit Required	PNKR <sup>3</sup>	'YES/OFF
Lifter Adapter Req'd	PNLA <sup>3</sup>	'YES/OFF
Lifter Required	PNLR <sup>3</sup>	'YES/OFF
Rollup	ROLL	'YES/OFF
2nd Int cable end	SICE	'YES/OFF
More Cables to Install	TCAW <sup>3</sup>	'YES/OFF
Upgrade	UPGR <sup>3</sup>	'YES/OFF

## NOTES:

- <sup>1</sup> Variables symbols start with &. Set variable to allowed value.  
Set switch to 'YES before task; to OFF after task  
(The apostrophe is CRUCIAL)
- <sup>2</sup> The DASD IPL device must be at address 0 on Bus 0.  
The TAPE IPL device must be at address 7 on Bus 0.
- <sup>3</sup> Can be set at beginning of run; does not change during processing

Totals: VARIABLES = 32; SWITCHES = 18

## APPENDIX IV

SYSTEM Setup/Upgrade Tasks Summary		Devices								Cards								V A N I L A
ID	Abbreviated Task Task Title	S Y S T E M	R A C C E C U K	C C E E U A	9 3 3 5 5 — B	9 3 3 3 3 2	9 9 3 3 4 1	9 9 3 3 4 7	9 9 3 3 4 8	6 6 1 1 0 0	6 6 0 0 4 0	6 6 0 0 4 X	6 6 0 0 1 1	6 6 0 0 3 2	6 6 0 0 3 9	6 0 1 8 / 9	6 0 1 8 / 9	
ACCB—Inst/Conn Cable	1									100	100	100		200	200	200	300	SP
	1									101	101	101	101	101	101	101	101	MP
ACDT—Inst Card	1																	LC
																		AFC
																		Grp
										300	300	300	300	300	300	300	300	TGC
ACMC—Inst Rem Comm Cbls											100		100	100	100	100		II
											200		200	200	200	200		UPG
ACSC—Inst Cable on Card										100	100	100		200	200	200		SP
																300		MP
																		EUR
ADBC—Inst Bus Cable			100															A30
			200															A40
ADCG—Inst Card Cage			100															
ADDC—Inst Dv DFCI Cbl End				110		210	210	310	411									I-L
				120		220	220	320	421									O-L
									412									I-R
									422									O-R
ADDT—Inst Dv DFCI Cbl Trm				100		200	200	300	401									L
									402									R
ADEV—Inst Device			100	200	300	400	700	500	601									L
			111						602									R
			121															
ADGH—Inst Cbls to Arm 2				100	200			300										
ADMH—Inst Mounting Hdwe			100	200	500	100	100	300	400									
ADPC—Inst Dev Pwr Cbl 2			100	200	300	400	500	600	701									L
			800						702									R
ADSB—Connect Bat Cable			100															
ADSC—Inst Dev Sig Cbl				110	200													P 1
				120														P 2
				130														P 3
				140														P 4
AIPL—Perf IPL/Verify Ind	100																	TSP
	200																	DISK
	300																	TAPE
ALAH—Inst Hoist Adapt			100															
ALDH—Inst Hoist			100		100													
ALMH—Inst Hoist Adapt Bar			100															

SYSTEM Setup/Upgrade Tasks Summary		Devices												Cards											
ID	Abbreviated Task Task Title	S Y S T E M	R A C E K	C C E U	9 3 3 5 — A	9 3 3 5 B	9 9 3 3 2	9 9 3 3 1	9 9 3 3 7	9 9 3 3 8	6 6 1 1 0	6 6 0 4 0	6 6 0 3 4	6 6 0 4 X	6 6 0 3 1	6 6 0 3 2	6 0 1 8 / 9	V A N I L A							
ARCT	Inst Cable Ties	100																							
ARFH	Inst RACK Filler 2	100 200 300																1 3 5							
ARPC	Inst RACK Pwr Cbl	100																							
ARSC	Inst RK PwrSeqCblEnd	110 120																J9 J10							
ARST	Inst PwrSeqCbl Term	100																							
ASAC	Provide AC Power 2	100																							
ASCP	Pwr on Sys Cons	100																							
ASEM	Inst ECS Modem	100																							
ASLC	Inst System Console	100																							
ASRH	Set-Up RACK 2	100																							
ASRP	Position RACK 2	100																							
ASYP	Turn Sys Power ON	100 200																							
ANSC	Inst Rem WS Cbls									100 200	100 200		100 200					II UPG							
CDGH	Close Cbl Gd Arm 2				100 200			300																	
LDCH	Lock Ship Clamps 2				100 200			300																	
LDSH	Lock Shock Prot 2					100 200	300 400																		
LDSH	Inst Ship Brkt 2							100																	
ODGH	Open Cbl Gd Arm 2				100 200			300																	
PDCC	Look at Inst Cards 1			100 200														BEF AFT							
PDRF	Go to the Front 1	100 200																BEF AFT							
PDRR	Go to the Back 1	100 200																BEF AFT							
PNAC	How to Inst a Card	100 200 300																Log Fil TG							

SYSTEM Setup/Upgrade Tasks Summary		Devices												Cards									
ID Task	Abbreviated Task Title	S			9	9												6	V				
		Y			3	3												0	A				
		R			3	3	9	9	9	9	6	6	6	6	6	6	6	1	N				
		A	C	C	5	5	3	3	3	3	1	0	0	0	0	0	0	8	I				
		E	C	E	E	-	3	3	4	4	1	4	3	4	3	3	/	L					
		H	K	C	U	A	B	2	1	7	8	0	0	4	X	1	2	9	A				
PNCL--Find Labeled Cable		111																	DF-I				
		113																	CO-I				
		114																	EU-I				
		121																	DF-O				
		124																	EU-O				
PNHC--How to Handle Cards		100																					
PNLC--Label the Cable <sup>4</sup>		111																	DF-I				
		114																	EU-I				
		121																	DF-O				
		122																	LN-O				
		123																	CO-O				
		124																	EU-O				
		211																	1DFI				
		221																	1DFO				
		214																	1EUI				
		224																	1EUO				
PNPS--Disp Upgrd Parts <sup>1</sup>		100																					
PNRC--How to Rem a Card		100																	All				
PNSA--Tell Cust Sys Avail		100																					
PNSC--Setup Complete		100																	II				
		300																	UPG				
		400																	UPG				
PNST--Notify of Sys Tkover		100																					
PNUT--Update Tplgy File		100																					
PVCC--Verify Proper Cds <sup>1</sup>			100																BEF				
			200																II				
			300																AFT				
PVOL--Verify Loose Parts <sup>1</sup>		100																	II				
		200																	UPG				
PVRF--Verify RK Cont <sup>1</sup>		100																	BEF				
		200																	II				
		300																	AFT				
PVRM--Verify Ref Matl <sup>1</sup>		100																					
RCCB--Disconn/Rem Cable												100	100	100					SP				
	1														200	200	200	300	MP				
	1											101	101	101	101	101	101	101	Grp				
RCDT--Rem Card																			100	LC			
																			200	AFC			
	1																		201	Grp			
												300	300	300	300	300	300	300		TGC			

SYSTEM Setup/Upgrade Tasks Summary		Devices										Cards										S Y S T E M	V A N I L A		
ID Task	Abbreviated Task Title	S R T A C K	C C E E C U	9 3 3 5 -	9 3 3 5 B	9 3 3 3 2	9 9 3 3 1	9 9 3 4 7	9 9 3 4 8	6 1 1 0 0	6 0 0 4 0	6 0 0 3 4	6 0 0 4 X	6 0 0 3 1	6 0 0 3 2	6 0 0 3 9	6 0 0 3 9	6 0 0 3 9	6 0 0 3 9	6 0 0 3 9	6 0 0 3 9			6 0 0 3 9	6 0 0 3 9
RCSC	Rem Cable from Cd									100	100	100		200	200	200								SP MP EUR	
RDBC	Rem Bus Cable			100 200																				A30 A40	
RDCG	Rem Card Cage			100																					
RDDC	Rem Dev DFCI Cbl End			110 120		210 220	210 220	310 320	411 421 421 422															I-L O-L I-R O-R	
RDDT	Rem Dv DFCI Cbl Trm			100		200	200	300	401 402															L R	
RDEV	Rem Device			100 111 121	200	300	400	700	500 601 602															L R	
RDGH	Rem Cbls from Arm			100	200			300																	
RDMH	Rem Mounting Hdwe			100	200	500	100	100	300	400															
RDPC	Rem Dev Pwr Cable			100 800	200	300	400	500	600	701 702														L R	
RDSC	Rem Dev Sig Cable			110 120 130 140	200																			P 1 P 2 P 3 P 4	
RLAH	Rem Hoist Adapt			100																					
RLDH	Rem Hoist			100	100																				
RLMH	Rem Hoist Adapt Bar			100																					
RRCT	Remove Cable Ties	100																							
RRFH	Rem RACK Filler	100																							
RRPC	Rem RACK Power Cbl	100																							
RRSC	Rem RK PwrSeqCblEnd	110 120																						J9 J10	
RRST	Rem PwrSeqCbl Term	100																							
RSAC	Rem all AC Power 2	100																							
RSRH	Rem RACK	100																							
RSYP	Turn Sys Power Off	100																							

[illegible]

NOTES:

- <sup>1</sup> Flat line drawing or list required.
- <sup>2</sup> Rollup multiples in sequence; set ROLL variable to YES
- <sup>3</sup> Uses variables &SYSD, &SYSM, &SYSN, &SYST, &CECM, &CECT, &SERN, &ORDN, &TIME, &STIM, and &RELYER; and switches PNLA, PNKR, PNLR, PNCE, PNBO, and PNED.
- <sup>4</sup> Both ends of the cable get labeled.
- <sup>5</sup> Tasks needed only if we do the MOVE tasks; not firm yet; not counted in totals
- <sup>6</sup> Automatically added at end; count as 1 task, 1 version



K1	04	02	M	B1	B6	B3	B7												
K2	PNLC1K0	1C0	122	123	1C0														
K2	PNLC2K0	2C0			2C0														
K2	PNCL1K0	1C0	991	113	1C0														
C1	04	04	M	6019	6018	6110													
C2	PNLC1C0	114	124	121	1P1														
C2	PNLC2C0	214	224		2P1														
C2	PNCL1C0	114	124	121	1P1														
P1	16	04	M	0101	0001	0C01	0C02	0C03	0C04	PWSI	PWSO	CC01	CC02	CC03	CC04	CC05	CC06	CC07	CC08
P2	PNLC1P1	111	121	111	111	111	111					888							
P2	PNLC2P1	211	221	211	211	211	211					887							
P2	PNCL1P1	111	121	111	111	111	111					886							
P2	RDESC1P0			110	120	130	140												
P2	ADSC1P0			110	120	130	140												
P2	RDOC1P0	110	120																
P2	ADOC1P0	110	120																
P2	RDOC2P0	210	220																
P2	ADOC2P0	210	220																
P2	RDOC3P0	310	320																
P2	ADOC3P0	310	320																
P2	RDOC4P0	41L	42L																
P2	ADOC4P0	41L	42L																
P2	RRSC1P0									110	120								
P2	ARSC1P0									110	120								
L1	02	01	M	L	R														
L2	RDPC7L0	701	702																
L2	ADPC7L0	701	702																
L2	RDDT4L0	401	402																
L2	ADDT4L0	401	402																
L2	RDEV6L0	601	602																
L2	ADEV6L0	601	602																
L2	RDDC41L	411	412																
L2	ADDC41L	411	412																
L2	RDDC42L	421	422																
L2	ADDC42L	421	422																
L2	SDASS10	5S1	5S2																
L2	VDCT4L0	401	402																
M1	09	03	M	630	640	650	660	F10	F20	F30	F40	F50							
M2	RDBC1M0			100	200														
M2	ADBC1M0			100	200														
V1	24	04	G	6030	6130	3054	3055	3030	2500	2501	2502	2503	2504	2505	2506	AF12	AF04		
V2	RCDT1V0	110	111	112	113	114	120	121	122	123	129	130	131						
V2	ACDT1V0	110	111	112	113	114	120	121	122	123	129	130	131						
V2	RCDT2V0																210	211	
V2	ACDT2V0																210	211	
M1	08	04	G	6019	6018	6110	6040	6034	6050	6031	6032								
M2	RCDT3W0	316	317	310	311	312	313	314	315										
M2	ACDT3W0	316	317	310	311	312	313	314	315										
G1	08	04	G	6019	6018	6110	6040	6034	6050	6031	6032								
G2	RCSC3G0	610	611																
G2	ACSC3G0	610	611																
G2	RCSC1G0			410	411	412													
G2	ACSC1G0			410	411	412													
G2	RCSC2G0							51X	52X	53X									
G2	ACSC2G0							51X	52X	53X									
X1	04	04	G	CC01	CC02	CC03	CC04												
X2	RCSC51X	510	511																
X2	ACSC51X	510	511																
X2	RCSC52X	512	513																
X2	ACSC52X	512	513																
X2	RCSC53X	514	515	516	517														
X2	ACSC53X	514	515	516	517														
S1	08	01	G	0	1	2	3	4	5	6	7								
S2	SDAS1S0	100	110	120	130	140	150	160	170										
S2	SDAS2S0	100	110	120	130	140	150	160	170										
S2	SDAS3S0	100	110	120	130	140	150	160	170										
S2	SDAS4S0	400	410	420	430	440	450	460	470										
S2	SDAS5S1	500	510	520	530	540	550	560	570										
S2	SDAS5S2	500	510	520	530	540	550	560	570										
PS	PDRR200	061*		YN															
PS	PDCC100	061*		NY															
PS	PDRR100	07*		YN															
PS	PDCC100	07*		NY															
PS	PDRR200	087*		YN															
PS	PDCC200	087*		NY															
PS	PDRR100	031*		YN															
PS	PDRR200	090*		YN															

# TOPOLOGY FILE 0630100

```

001109390063010019870812104157 010316 IVT1
002600019309001 0000375989 TIPNEW0000050000000000AC000 1 E
003400029332200 0008265500 U3PNEW00000200000000004LM0201 00E021
00444003 0008265527 B2P002P0030009500670003PI010004500025
028440039803 0006495301 B1P007D0010022200060003DI010042500057
005400029332200 0008265500 U3PNEW00000300000000001LM0100 10E021
00644005 0008265527 B2P002P0020009500600005PI010004500025
030440059801 0006495304 B1P003D0010040000057005DI010042500057
007400029347001 0006370462 U4PNEW0000040000000015LM0417 00E021
00844007 0006200478 B2P002P0040009500740007PI010022500120
029440079803 0006495301 B1P021CC01000000000007DI010022200085
019400099396630 0006369639 C9BNEW0000010013100062CS0409 E
020400099396630 0006369640 C9BNEW0000010016100062CS0508 E
017400099396630 00066X4124 C8BNEW0000010011100062CS0302 E
009400029396630 00092X4601 U1PNEW00000100000000007LM03 00E
01044009 0008265527 B2P002P0010009500530009PI010002500150
0184000993966303055 00066X4125 C8PNEW0000010009100062CS0200 E
0324000993966304591 0006369617 CAPNEW0000010040100062CS1308 I
0314000993966304592 0006369616 CAPNEW0000010007100062CS0108 I
0244000993966306031 0006258601 C3PNEW0000010028100062CS0902 I023
0264000993966306032 0006258605 C3PNEW0000010034100062CS1101 I025
0224000993966306034 0006258604 C3PNEW0000010025100062CS0801 I023
0114000993966306040 0002438495 C1PNEW0000010037100062CS1200 E
012440096040 00059X3872 B6F011CC010000000000 0000000000
0214000993966306110 0005563616 C1PNEW0000010019100062CS0600 I
0754000993966306130 00085X2075 C2PNEW0000010031100062CS10008 I
0134000993966306130 00085X2075 C2PNEW0000010022100062CS0700A I
013440099200 0006240648 B3F022CC010000000000 0000000000
014440099410 00092X2815 B3F026CC010000000000 0000000000
015440099540 0006240593 B3F024CC020000000000 0000000000
016440099661 0006240646 B3F024CC010000000000 0000000000
002609111 0019201 0019951 001999X 001 000 000 000 000 000 000
003609951 001999X 001 000 000 000 000 000 000 000 000 000
005609951 001999X 001 000 000 000 000 000 000 000 000 000
007609951 001999X 001 000 000 000 000 000 000 000 000 000
009605503 001999X 0019951 001 000 000 000 000 000 000 000 000
02260C19200001 000 000 000 000 000 000 000 000 000 000
02460C29540001C19661001 000 000 000 000 000 000 000 000 000
02660C19410001 000 000 000 000 000 000 000 000 000 000

```

10 - HEADER RECORD  
 40 - ELEMENT RECORD  
 44 - CABLE RECORD  
 60 - SPECIFY RECORD

## INTERMEDIATE DELTA FILE

063424

98 00001SETM1	000	P001000F	00000	00000	00000	
01A00002PVCC2	025	P002120F	002AC0000900007LM03	00000	00000	BG
98 00003PVCL1	050	P003100F	00000	00000	00000	
99 00004PVRM1	005	P003200F	00000	00000	00000	
01A00005ASRP1	020010	S011000FL	002AC00	00000	00000	G
01A00006ASRH1	080060	S012000FL	002AC00	00000	00000	GA
01A00007PDRR2	005	R013000 H	002AC00	00000	00000	A
01A00008UDSW1	010050	R013100 H	002AC0000700015LM04	00000	00000	GB
01A00009UDCH3	008005	R013200 H	002AC0000700015LM04	00000	00000	GB
01A00010VDC2	T001	R013320 H	002AC0000500001LM01	00000	00000	B
01A00011SDVS2	007003	R013410 H	002AC0000700015LM04	00000	00000	GB
01A00012SDAS2S	007	R013500 H	002AC0000500001LM01	00000	00000	D
01A00013SDAS2S	007	R013500 H	002AC0000300004LM02	00000	00000	D
01A00014SDAS4S	010	R013500 H	002AC0000700015LM04	00000	00000	D
01A00015SDCB6	007002	R013600 H	002AC0000500001LM01	00000	00000	GB
01A00016SDCB6	007002	R013600 H	002AC0000300004LM02	00000	00000	GB
01A00017SDCB1	007002	R013600 H	002AC0000900007LM03	00000	00000	GB
01A00018SDCB3	007002	R013600 H	002AC0000700015LM04	00000	00000	GB
01A00019ACSC2G	D 010	C087200LL	002AC0000900007LM0302400062CS0901600000CC016031			FD
01A00020ACSC1G	D 030	C087200LL	002AC0000900007LM0301100062CS1201200000CC016040			FD
01A00021ASLC1	D 050	X088100	002AC0000900007LM0301100062CS1201200000CC016040			A
01A00022ASEM1	D 080	X088200	002AC0000900007LM0302400062CS0901600000CC016031			A
01A00023ARPC1	D 025	S091100 L	002AC00	00000	00000	A
01A00024SRCB1	D 010	S091300 L	002AC00	00000	00000	A
01A00025PORF2	D 000	R092000LH	002AC00	00000	00000	A
01A00026UDSH4	D 050040	R092100LH	002AC0000700015LM04	00000	00000	GB
01A00027UDSH2	D 012001	R092100LH	002AC0000300004LM02	00000	00000	GB
01A00028UDSH2	D 012001	R092100LH	002AC0000500001LM01	00000	00000	GB
01A00029SDSR1	D 010001	R092210LH	002AC00	00000	00000	GB
01A00030SDSR6	D 010001	R092220LH	002AC0000700015LM04	00000	00000	GB
01A00031SDSR4	D 010001	R092220LH	002AC0000300004LM02	00000	00000	GB
01A00032SDSR4	D 010001	R092220LH	002AC0000500001LM01	00000	00000	GB
01A00033ADSB1	D 010	R092300LH	002AC0000900007LM03	00000	00000	B
01A00034ASAC1	D 012008	S100100LL	002AC00	00000	00000	GA
01A00035ASCP1	D 020	X100200L	002AC0000900007LM03	00000	00000	
98A00036ASYP1	D 010	X100300L	00000	00000	00000	
01A00037VPOR1	U 008001	S101100LH	002AC00	00000	00000	GB
01A00038VPOR7	U 008001	S101200LH	002AC0000700015LM04	00000	00000	GB
01A00039VPOR5	U 008001	S101200LH	002AC0000300004LM02	00000	00000	GB
01A00040VPOR5	U 008001	S101200LH	002AC0000500001LM01	00000	00000	GB
01A00041VSTD1	U 050050	S102100LH	002AC0000700015LM04	00000	00000	GB
01A00042AIPL1	U 040	X102200L	002AC0000900007LM03	00000	00000	
98A00043VSEM1	U 030	X102300L	00000	00000	00000	
99A00044PNSA1	U 005	P103200L	00000	00000	00000	
98A00045ACMC1	U 000	P112000L	00000	00000	00000	
99A00046PNSC1	U 050	P114000L	00000	00000	00000	
99A00047SPUP1	U 000	P121000L	00000	00000	00000	
99A00048SIPP1	U 000	P122000L	00000	00000	00000	
01A00000AIPL1	U 040	X102200L	002AC0000900007LM03	00000	00000	
01A00000REEF	100	P000000P	002AC0000900007LM0302400062CS09	00000	00000	
01A00000LYMX	100	P000000P	002AC0000900007LM0301100062CS12	00000	00000	
01A00000ACSC1G	D 030	C087200LL	002AC0000900007LM0301100062CS1201200000CC016040			FD
01A00000ASLC1	D 050	X088100	002AC0000900007LM0301100062CS1201200000CC016040			A
01A00000ACSC1G	D 010	C087200LL	002AC0000900007LM0302200062CS0801300000CC016034			FD
01A00000ACSC2G	D 010	C087200LL	002AC0000900007LM0302600062CS1101400000CC016032			FD
01A00000ACSC2G	D 010	C087200LL	002AC0000900007LM0302400062CS0901500000CC026031			FD
01A00000ASEM1	D 080	X088200	002AC0000900007LM0302400062CS0901500000CC026031			A
01A00000ACSC2G	D 010	C087200LL	002AC0000900007LM0302400062CS0901600000CC016031			FD
01A00000ASEM1	D 080	X088200	002AC0000900007LM0302400062CS0901600000CC016031			A

# DELTA HARDWARE HANDLING FILE

## 0630100

98 00001SETM100	000	00000	00000	00000	000
01A00002PVCC200	025	002AC0000900007LM03	00000	00000	000 BG
98 00003PVOL100	050	00000	00000	00000	000
99 00004PVRM100	005	00000	00000	00000	000
01A00005ASRP100	020010	002AC00	00000	00000	000G
01A00006ASRH100	080060	002AC00	00000	00000	000GA
01A00007PORR200	005	002AC00	00000	00000	000 A
01A00008UDSH100	010050	002AC0000700015LM04	00000	00000	000GB
01A00009UDCH300	008005	002AC0000700015LM04	00000	00000	000GB
01A00010VDC200	T001	002AC0000500001LM01	00000	00000	000 B
01A00011SDVS200	007003	002AC0000700015LM04	00000	00000	000GB
01A00012SDAS200	007	002AC0000500001LM01	00000	00000	100 D
01A00013SDAS200	007	002AC0000300004LM02	00000	00000	110 D
01A00014SDAS400	010	002AC0000700015LM04	00000	00000	470 D
01A00015SDCB600	007002	002AC0000500001LM01	00000	00000	000GB
01A00016SDCB600	007002	002AC0000300004LM02	00000	00000	000GB
01A00017SDCB100	007002	002AC0000900007LM03	00000	00000	000GB
01A00018SDCB300	007002	002AC0000700015LM04	00000	00000	000GB
01A00019PDC2000	010	002AC0000900007LM0302400062CS0901600000CC016031	00000	00000	000 BG
01A00019PNLC123D	010	002AC0000900007LM0302400062CS0901600000CC016031	00000	00000	000 CA
01A00019ACSC2000	010	002AC0000900007LM0302400062CS0901600000CC016031	00000	00000	512 FD
01A00020PNLC122D	030	002AC0000900007LM0301100062CS1201200000CC016040	00000	00000	000 CA
01A00020ACSC1000	030	002AC0000900007LM0301100062CS1201200000CC016040	00000	00000	411 FD
01A00021ASLC1000	050	002AC0000900007LM0301100062CS1201200000CC016040	00000	00000	000 A
01A00022ASEM1000	080	002AC0000900007LM0302400062CS0901600000CC016031	00000	00000	000 A
01A00023ARPC1000	025	002AC00	00000	00000	007 A
01A00024SRCB1000	010	002AC00	00000	00000	00J A
01A00025PDRF2000	000	002AC00	00000	00000	000 A
01A00026UDSH4000	050040	002AC0000700015LM04	00000	00000	000GB
01A00027UDSH2000	012001	002AC0000300004LM02	00000	00000	000GB
01A00028UDSH2000	012001	002AC0000500001LM01	00000	00000	000GB
01A00029SDSR1000	010001	002AC00	00000	00000	000GB
01A00030SDSR6000	010001	002AC0000700015LM04	00000	00000	000GB
01A00031SDSR4000	010001	002AC0000300004LM02	00000	00000	000GB
01A00032SDSR4000	010001	002AC0000500001LM01	00000	00000	000GB
01A00033ASCB1000	010	002AC0000900007LM03	00000	00000	000 B
01A00034ASAC1000	012008	002AC00	00000	00000	000GA
01A00035ASCB1000	020	002AC0000900007LM03	00000	00000	000
98A00036ASYP1000	010	00000	00000	00000	000
01A00037VPOR1000	008001	002AC00	00000	00000	000GB
01A00038VPOR7000	008001	002AC0000700015LM04	00000	00000	000GB
01A00039VPOR5000	008001	002AC0000300004LM02	00000	00000	000GB
01A00040VPOR5000	008001	002AC0000500001LM01	00000	00000	000GB
01A00041VSTD1000	050050	002AC0000700015LM04	00000	00000	000GB
01A00042AIP1000	040	002AC0000900007LM03	00000	00000	000
98A00043VSEM1000	030	00000	00000	00000	000
99A00044PNSA1000	005	00000	00000	00000	000
98A00045ACMC1000	000	00000	00000	00000	000
99A00046PNSC1000	050	00000	00000	00000	000
99A00047SPUP1000	000	00000	00000	00000	000
99A00048SIPP1000	000	00000	00000	00000	000

# TGIANT SCRIPT

063000

```
.SE LANG = 0
.SE MRACK OFF
.SE MODEL OFF
.SE NRACK OFF
.SE UPGR OFF
.SE ROLL OFF
.SE PNLR OFF
.SE PNLA OFF
.SE TCAW 'YES'
.SE PNCE OFF
.SE PNBD OFF
.SE PNED OFF
.SE PNKR OFF
.SE CTIE 'YES'
.SE SYSM = '9390'
.SE SYSN = '0630100'
.SE ORDN = 'IVT1'
.SE SYSD = '19870812'
.SE SYST = '104157'
.SE CECT = '9396'
.SE CECM = '630'
.SE SERN = 'NE-W0000001'
.SE TIME = '1.4'
.SE STIM = '1.4'
.SE RACK = 'A'
.SE RACK1 = 'A'
.SE DLOC1 = '07'
.IM RELEAS
.SE ARTNM = 100
.IM SETM100
.SE RACK = 'A'
.SE DLOC = '07'
.SE CCNUM = '01'
.IM PVCC200
.IM PVOL100
.IM PVRM100
.SE CNT = '1'
.IM ASRP100
.SE RACK = 'A'
.SE CNT = '1'
.IM ASRH100
.SE RACK = 'A'
.IM PDRR200
.SE RACK = 'A'
.SE DLOC = '15'
.SE CNT = '1'
.IM UDSW100
.SE RACK = 'A'
.SE DLOC = '15'
.SE CNT = '1'
.IM UDCH300
.SE RACK = 'A'
.SE DLOC = '01'
.IM VDCT200
.SE RACK = 'A'
.SE DLOC = '15'
.SE CNT = '1'
.IM SDVS200
.SE RACK = 'A'
.SE DLOC = '01'
.SE DEVAD = '0'
.SE ARTNM = '100'
.IM SDAS200
.SE RACK = 'A'
.SE DLOC = '04'
.SE DEVAD = '1'
.SE ARTNM = '110'
.IM SDAS200
.SE RACK = 'A'
.SE DLOC = '15'
.SE DEVAD = '7'
.SE ARTNM = '470'
.IM SDAS400
.SE RACK = 'A'
```

```

.SE DLOC = '01'
.SE ROLL 'YES'
.SE CNT = '2'
.IM SDCB600
.SE ROLL OFF
.SE RACK = 'A'
.SE DLOC = '07'
.SE CNT = '1'
.IM SDCB100
.SE RACK = 'A'
.SE DLOC = '15'
.SE DLOC = '15'
.SE CNT = '1'
.IM SDCB300
.SE RACK = 'A'
.SE DLOC = '07'
.SE CCNUM = '01'
.IM PDCC200
.SE RACK = 'A'
.SE DLOC = '07'
.SE CBLPN = '70X8659'
.SE CBLAB = '016'
.IM PNLC123
.SE RACK = 'A'
.SE DLOC = '07'
.SE CSLOT = '09'
.SE CPORT = '01'
.SE CBLAB = '016'
.SE ARTNM = '512'
.SE CTYPE = '6031'
.IM ACSC200
.SE RACK = 'A'
.SE DLOC = '07'
.SE CBLPN = '2438316'
.SE CBLAB = '012'
.IM PNLC122
.SE RACK = 'A'
.SE DLOC = '07'
.SE CSLOT = '12'
.SE CPORT = '01'
.SE CBLAB = '012'
.SE ARTNM = '411'
.SE CTYPE = '6040'
.IM ACSC100
.SE CBLAB = '012'
.IM ASLC100
.SE CBLAB = '016'
.IM ASEM100
.SE RACK = 'A'
.IM ARPC100
.SE RACK = 'A'
.IM SRCB100
.SE RACK = 'A'
.IM PDRF200
.SE RACK = 'A'
.SE DLOC = '15'
.SE CNT = '1'
.IM UDSH400
.SE RACK = 'A'
.SE DLOC = '04'
.SE ROLL 'YES'
.SE CNT = '2'
.IM UDSH200
.SE ROLL OFF
.SE RACK = 'A'
.SE DLOC = '00'
.SE CNT = '1'
.IM SDR100
.SE RACK = 'A'
.SE DLOC = '15'
.SE CNT = '1'
.IM SDR600
.SE RACK = 'A'
.SE DLOC = '04'

```

.SE ROLL 'YES'  
.SE CNT = '2'  
.IM SDSR400  
.SE ROLL OFF  
.SE RACK = 'A'  
.SE DLOC = '07'  
.IM ADSB100  
.SE RACK = 'A'  
.SE CNT = '1'  
.IM ASAC100  
.IM ASCP100  
.IM ASYP100  
.SE RACK = 'A'  
.SE DLOC = '00'  
.SE CNT = '1'  
.IM VPOR100  
.SE RACK = 'A'  
.SE DLOC = '15'  
.SE CNT = '1'  
.IM VPOR700  
.SE RACK = 'A'  
.SE DLOC = '04'  
.SE ROLL 'YES'  
.SE CNT = '2'  
.IM VPOR500  
.SE ROLL OFF  
.SE RACK = 'A'  
.SE DLOC = '15'  
.SE CNT = '1'  
.IM VSTD100  
.IM AIPL100  
.IM VSEM100  
.IM PNSA100  
.IM ACMC100  
.IM PHSC100  
.IM SPUP100  
.IM SIPPI00  
.IM PARHDR  
.SE RACK = 'A'  
.IM RCKCL  
.IM DCABCT

---

## System Installation Guide

F System identification: 9390-O630100-19870812-104157  
F Processor type-model number: 9396-630  
F Processor serial number: NE-W000001

F The job of installing a system has been divided into small units of work, named F tasks. Most tasks have several steps. Each task in these instructions has a small F box beside the task number. Read and follow all steps in each task carefully.  
F Mark the box when a task has been completed. Perform all tasks in sequence.

One service representative is needed to install this system.

The approximate service representative time needed to install this system is 1.5 hours. The approximate system time needed is 1.5 hours.

### DANGER

An incorrectly wired outlet could place hazardous voltage on metal parts of the system and/or the products that attach to the system. It is the customer's responsibility to ensure that the outlet is properly grounded to prevent an electrical shock.

1. When installing the system do not plug in any power cables until instructed to do so. All signal connections must be made first.
2. When adding any hardware products to the system (additional racks, work stations, printers, modems, etc.), do not plug in the power cables for that hardware until ALL signal connections have been made.

F Before starting the installation, check that the customer-supplied power receptacle F is correctly grounded. Then, measure the voltage at that receptacle and record that voltage here: \_\_\_\_\_ volts.



(SETM100)

F The number in the upper right corner of each page is the task identification F number; make reference to it when requesting aid.

The numbers at the bottom right of illustrations are publishing control numbers and are not part of the technical content of these instructions.

**CAUTION:**

These instructions will tell you how to install a stabilizer to the front bottom of each rack to prevent the rack from tipping over when you slide or pull out the system units. **DO NOT** try to slide out or install any system units until the stabilizer is properly installed. Use caution when moving the rack and its system units.

**DANGER**

Never handle cables (communications, workstation, printer, or phone), connectors, or station protectors during an electrical storm.


**Federal Communications Commission (FCC) Statement**

**Warning:** This equipment generates, uses, and can radiate radio frequency energy and if not installed and used in accordance with the instruction manual, may cause interference to radio communications. It has been tested and found to comply with the limits for a Class A computing device pursuant to Subpart J of Part 15 of FCC Rules, which are designed to provide reasonable protection against such interference when operated in a commercial environment. Operation of this equipment in a residential area is likely to cause interference in which case the user at his own expense will be required to take whatever measures may be required to correct the interference.

(SETM100)

## □ 1 Getting started -- How to identify racks.

Identification from the front of the rack is done by rack serial number.




RSLD139-0

From the back, racks are identified by a letter, located inside the rack.

To open the back cover:


1. Put your fingers between the upper left corner of the cover and the rack, or under the lower left corner.
2. Pull the cover open.



RSLD141-0

On the right side, near the top is a square patch with a black letter.

- The primary rack is always identified by the letter A.
- Additional racks are identified by the letters B, C, D, and so on. They should be physically installed in the same sequence.




RSLD142-0

(SETM100)


## □ 2 How to locate devices.

Inside each rack, there are four strips (named EIA Unit Labels), numbered from bottom to top. Two of the strips are visible from the back of the rack (one on each side) when the cover is open; two are visible from the front (one on each side) when a filler cover (a cover with no device behind it) is removed.



RSLD163-0

Each number represents a vertical space equal to one Electronics Industries Associates (EIA) unit. Each EIA unit has three holes, spaced at a constant distance, as shown.




RSLD168-3

(SETN1100)

The EIA number at the bottom of a device is used to specify the EIA location of that device.

F For example, if an  
F instruction said "Find the  
F 9396 unit at EIA 7.", that  
F means you should look  
F for a 9396 unit, the  
F bottom of which is at  
F EIA number 7, as shown.  
F (This is an example only;  
F do not try to verify it on  
F your system hardware.)



R8LD175-0

Some devices are small enough to be placed side-by-side, so two devices can have the same EIA number. In this case, the  
F devices are identified as  
F the rightmost and leftmost  
F device, from where you  
F are standing.

(SETM100)


### F □ 3 Verify the content of rack A from the front.

F From the front, verify  
F that rack A has contents  
F as shown.

The machine type is  
located in the upper left  
corner of each device.

F The numbers to the right  
F in this figure are the EIA  
F values, indicating the  
F device locations. These  
F numbers are shown in this  
F view for reference only;  
F these numbers are  
F normally visible only  
F from the back of the rack.

If the content of your  
rack does not match what  
is shown here, you cannot  
go any farther with this  
F installation. Inform your  
F sales representative.




(SETM100)

#### □ 4 Verify the serial number.

These installation instructions were printed for a specific system. To verify that you have the correct system for these instructions, do the following:

1. Locate the device at EIA 07 in rack A that has 9396 on the Unit ID Plate in the upper left corner of the device cover.
2. Locate the control panel on that device.
3. Compare the serial number on that control panel with this number:  
NE-W000001.

The numbers must match exactly. If they do not, you cannot go any farther with this installation. Inform your sales representative.



(PVCC200)

- F □ 5 From the back of rack A, verify that the correct cards  
F are installed in the card enclosure located at EIA 07.

Compare the cards in the  
card enclosure to this  
F chart. Verify that each  
F slot has the correct card  
F installed.

Back View

A	3	3	2	2	6	6	6	6	6	6	6	6	A
F	0	0	5	5	0	1	0	0	1	0	0	0	F
0	5	5	0	0	1	3	3	3	3	3	4	1	
4	5	4	0	4	0	0	4	1	0	2	0	2	
1 2 3 4 5 6 7 8 9 10 11 12 13													
9396-630													

F Slot numbers —————→  
F are found across the  
F bottom of the enclosure.

Card Enclosure

If the cards in the card  
enclosure do not match  
this chart, do not go any  
farther with this installa-  
F tion. Inform your sales  
F representative.

October 5th, 1987

9390-0630100-19870812-104157

8

## F □ 6 Verify the shipping group parts.

### CAUTION:


Be careful when moving the boxes in the ship group; some boxes are heavy. The stabilizer weighs approximately 9 kilograms (20 pounds).

F For each rack, you should  
F have the following parts:

- F Stabilizer (1)
- F Stabilizer screws (2)
- F Tightening rod (1)
- F Wrench (1)
- F Acoustic panels (2)
- F Cable ties (25)
- F Rack power cord (1)
- F Clamp (1)
- F Thumbscrews (2)

F If the stabilizer or  
F stabilizer screws are  
F missing, do not start the  
F installation. Inform your  
F sales representative.

F If any other parts are  
F missing, you can start the  
F installation, but you can  
F not complete it until you  
F get the missing parts.  
F Inform your sales repre-  
F sentative.



RSL0273-1



(PVOL100)

For the total system, you  
should have one box with  
these parts. —————>

---P/N---	---CABLE NAME---	QTY
02438316	WORK STATION ATT	1
06165837	COMMUNICATIONS	1
092X2785	COMMUNICATIONS	1
070X8655	COMMUNICATIONS	2

F If any parts are missing,  
F you can not complete the  
F installation until you get  
F the missing parts. Inform  
F your sales representative.

October 5th, 1987

9390-0630100-19870812-104157

10

(PVRM100)

F ☐ 7 Verify the system reference material.

F Check all items listed on  
F the shipping group to  
F ensure that all required  
F parts have been received.

October 5th, 1987

9390-O630100-19870812-104157

11

(ASRP100)

F □ 8 Move the rack to its planned location.


F CAUTION:

F If the system is on a raised floor, be careful around cable cutouts in the floor.

F See the *High End Olympic Planning Guide*, GA21-9913 for service clearance space  
F needed.

□ 9 Lock the casters.

1. Lock each caster by turning the screw clockwise until it is finger tight.
2. Ensure that you lock all casters.



RSLD004-0

(ASRII100)

# F □ 10 Install the stabilizer on rack A.


F 1. From the ship group  
F parts, get the  
F stabilizer, the  
F stabilizer screws, the  
F wrench, and the tight-  
F ening rod.

F 2. Line up the stabilizer  
F holes with the holes  
F in the front of the  
F rack, as shown.


3. Ensure that the base  
of the stabilizer is on  
the floor.

F 4. Use the two screws to  
F fasten the stabilizer to  
F the frame. Turn the  
F screws clockwise. Use  
F the wrench to get  
F these screws VERY  
F TIGHT. (Do not  
F stand on the wrench).


F 5. Put the wrench and  
F the tightening rod in  
F their holder inside the  
F rear cover, as shown.



RSLD337-0



RSLD337-0



RSLD335-0


(ASRH100)

## F □ 11 Install the side panels on rack A

Note: If the location of the rack prevents installation of one or both of these side panels, you can leave the panel(s) off.

The arrows inside the frame of each panel indicate the top and front of the panel.

1. Identify the side of the rack to which each panel attaches.
- F 2. Line up the clips on the side panel with the holes on the side of the rack, as shown.
- F 3. Press the panel clips against the rack until they seat.
- F 4. Repeat steps 2 and 3 for the other side of the rack.



RSL0J35-0

(PDRR200)


F □ 12 Go to the back of rack A for the next tasks.

F Detailed verification of the  
F rack contents is not neces-  
F sary.

F However, to become  
F familiar with the rack  
F contents, observe where  
F each device is located;  
F note the EIA numbers on  
F the strips on both sides of  
F the rack.

F The machine type number  
F is indicated on the back  
F of each device.


F Go to the next task.



(UDSW100)

- F ☐ 13 Remove the shipping blocks from the 9347 device  
F located at EIA 15 in rack A.

F Pull up and remove the  
F shipping blocks, as shown.  
F They may be discarded.



October 5th, 1987

9390-O630100-19870812-104157


16

(UDCH300)

- F □ 14 Unlock the shipping clamp bar for the 9347 at EIA 15 in  
F rack A.

- F 1. Loosen the two  
F thumbscrews from the  
F shipping clamp bar  
F on the right side of  
F the rack. (Use the  
F tightening rod.)


Note: Do not remove the thumbscrews; just loosen them enough so the bar can slide.



RSLC017-1

- F 2. Slide the bar to the  
F left, turn it counter-  
F clockwise, and let it  
slide down.

3. Tighten the two  
thumbscrews finger  
tight.



RSLC018-1




(VDCT300)

- F □ 15 Verify that a cable terminating plug is present in the  
F 9347 device located at EIA 15 in rack A.

There must be a cable terminating plug present as shown for correct system operation.


F If the cable terminating  
F plug is missing, you can  
F not complete this installa-  
F tion. Inform your sales  
F representative.



RSLD281-1

F □ 16 Set the voltage switches for the 9347 at EIA 15 in rack  
F A.


F 1. Locate the voltage  
F switches at the back  
F of the unit.



F 2. In the chart shown,  
F find the voltage range  
F that includes the  
F voltage you recorded  
F on the first page of  
F these instructions.


Recorded Voltage	Switch Settings
95 to 110 Volts	
111 to 126 Volts	
190 to 225 Volts	
226 to 252 Volts	

F 3. Set the switches, as  
F shown in the chart for  
F that voltage range.  
F Use a ball point pen  
F or other pointed  
F object and press the  
F switch to the right or  
F to the left, as neces-  
F sary.




F □ 17 Set the address of the 9332 at EIA 01 in rack A to 1.

- F 1. Locate the address
- F switch at the back of
- F the unit.




- F 2. Set the address to 1
- by pressing one of the
- pushbuttons (above or
- below the displayed
- number) as often as
- necessary.



(SDAS200)


F □ 13 Set the address of the 9332 at EIA 04 in rack A to 0.

- F 1. Locate the address
- F switch at the back of
- F the unit.



RSLO147-0

- F 2. Set the address to 0
- by pressing one of the
- pushbuttons (above or
- below the displayed
- number) as often as
- necessary.




RC-D100-0


(SDAS-400)

F □ 19 Set the address of the 9347 at EIA 15 in rack A to 7.

- F 1. Locate the address  
F switches at the back  
F of the unit.



- F 2. Set the switches as  
F shown for an address  
F of 7. Use a ball point  
pen to slide the  
switches up or down.




RC4D473-1

(SDCB600)

F □ 20 Verify correct seating of the power cables for all 9332s  
F in rack A.

- F 1. For the 9332 at EIA  
F 01, push in the power  
cable to ensure that it  
is correctly seated.  
2. Perform this task for  
each 9332 unit in this  
F rack; there are 2.



RSLD1-9-1

October 5th, 1987


9390-O630100-19S70812-104157

23


(SDCB100)

- F □ 21 Check the circuit breaker and power cable of the card enclosure at EIA 07 in rack A.
- F

1. Locate the circuit breaker on the card enclosure.
2. Verify that the circuit breaker is set to the On (I) position. If it is not on, set it to the On (I) position.
3. Push in the power cable to ensure that it is correctly seated.



RSLD145-0



RSLD161-0

October 5th, 1987


9390-O630100-19870812-104157

24


(SDCB300)

- F ☐ 22 Check the circuit breaker and power cable of the 9347  
F at EIA 15 in rack A.


1. Locate the circuit breaker on the 9347.



2. Verify that the circuit breaker is set to the On (I) position. If it is not on, set it to the On (I) position.



3. Push in the power cable to ensure that it is correctly seated.





(PDCC200)

F □ 23 Observe the cards in the card enclosure at EIA 07 in  
F rack A.

F Detailed verification is not  
F necessary. However, some  
F of these cards are used in  
F the next tasks.

F To become familiar with  
F the card enclosure con-  
F tents, observe approxi-  
F mately where the various  
F cards are.

F Slot numbers —————→  
F are found across the  
F bottom of the enclosure.

F Go to the next task.

Back View

A	3	3	2	2	6	6	6	6	6	6	6	A
F	0	0	5	5	0	1	0	0	1	0	0	F
0	5	5	0	0	1	3	3	3	3	3	4	1
4	5	4	0	4	0	0	4	1	0	2	0	2
1 2 3 4 5 6 7 8 9 10 11 12 13												
9396-630												

Card Enclosure


(PNLC123)

## □ 24 Locate, label, and place a communications cable.

1. Find a cable with part number 70X8655.
2. Get 2 cable labels from the parts in the shipping group.
3. Print the following information on both labels:

EID: 016

4. Fasten one label to each end of the cable, as shown. Fold the label around the cable and press together.





RSLD2C3-1



RSLD2C2-1

5. Select the end of the cable with holes visible.
6. Push this end of the cable into rack A, as shown.




RSLD0C6-1

This end of the cable will be installed by the task on the next page. The other end will be connected later.

(ACSC200)

F □ 25 Attach the cable to port 01 on the 6031 card in slot 09  
F of the card enclosure at EIA 07 in rack A.


- F 1. Find the 6031 card in  
F slot 09 in the card  
F enclosure at EIA 07.
2. Connect the cable  
F labeled EID: 016 to  
F port 01 on the 6031  
F card, as shown.
3. Turn the thumbscrews  
on the connector  
F clockwise until they  
are finger tight.
4. Verify that the cable  
is held tightly.



RCSDS12-0

F □ 26 Locate, label, and place a cable with a twinaxial work station attachment.

- F 1. Find a cable with part  
F number 2438316.  
F This cable has a  
F twinaxial work station  
F attachment on one  
F end.



RSLD011-0

2. Get 2 labels from the parts in the shipping group.
3. Print the following information on both labels:

EID: _____	F	EID: _____
_____	O	_____
_____	D	_____


  

EID: _____	F	EID: _____
_____	O	_____
_____	D	_____

RSLD023-1


EID: 012

4. Fasten one label to each end of the cable, as shown. Fold the label around the cable and press together.



RSLD270-0

5. Put the twinaxial work station attachment on the floor, out of the way.
6. Push the loose end of the cable into rack A, as shown.



RSLC038-1

This end of the cable will be installed by the task on the next page.

(ACSC100)


F □ 27 Attach the cable to the 6040 card in slot 12 of the card enclosure at EIA 07 in rack A.

F 1. Find the 6040 card in  
F slot 12 of the card  
F enclosure at EIA 07.

2. Connect the cable  
F labeled EID: 012 to  
F the port on the 6040  
F card, as shown.

3. Turn the thumbscrews  
on the connector  
F clockwise until they  
are finger tight.

4. Verify that the cable  
is held tightly.



RCS0411-0

F □ 28 Prepare a twinaxial work station attachment for  
F connection to the system console device.

F 1. Find the twinaxial  
F work station attach-  
F ment that has a cable  
F labeled EID: 012




F 2. Remove the cover, as  
F shown.

F 3. Find the customer's  
F twinaxial cable that is  
F to be used to connect  
F the console display to  
F the twinaxial work  
F station attachment.

F 4. Connect one end of  
F the twinaxial cable to  
F socket 0, as shown.  
F The other end of this  
F cable will be con-  
F nected by the task on  
F the next page.

F 5. Reinstall the cover, as  
F shown.

F 6. Place the twinaxial  
F work station attach-  
F ment where it will be  
F out of the way.




(ASLC100)

## F □ 29 Prepare the system console device.

F Many different device  
F types can be used as the  
F system console. For the  
F following instructions, see  
F the setup manual for the  
F device type that is being  
F used as the system  
F console on this system.

F 1. Ensure that the  
F console display is  
F unplugged from its  
F outlet.



F 2. Connect the loose end  
F of the twinaxial cable  
F to the console display  
F (one end was con-  
F nected to the  
F twinaxial work station  
F attachment by the  
F task on the previous  
F page).

F 3. Ensure that the  
F twinaxial cable is cor-  
F rectly terminated.

F 4. If the system console  
F device has address  
F switches, ensure that  
F they are set to 0.

F □ 30 Install the system support modem.

- F 1. Locate the system support modem and the installation documentation for  
F that modem.
- F 2. Ensure that the modem power cable is unplugged from the power source.
- F 3. Find the end of a communications cable labeled:  
F EID: 016
- F 4. Connect the cable labeled EID: 016 to the modem. Tighten the  
F thumbscrews finger tight and ensure that the cable is fastened tightly.
- F 5. Connect the modem to the telephone network.
- F 6. Connect the modem to the telephone, if a telephone is present for that  
F purpose.
- F 7. Plug the modem power cable into the power source.
- F 8. Use the modem documentation to determine if the modem has switches  
F (internal or external) that must be set.
- F • The modem may have no switches. If that is the case, ignore the steps  
F below where you are told to "Set the switches . . .".
- F • The modem may have switches for some or all of the following func-  
F tions.
- F 9. Set the switches, if present, to provide the following functions:
- F a. Circuit 108 (Data Terminal Ready) is controlled through the V.24 inter-  
F face.
- F b. Circuit 106 (Clear to Send) follows Circuit 105 (Request to Send).
- F c. Circuit 109 (DCD) going inactive forces Circuit 104 (RXD) inactive.
- F d. Circuit 126 (Channel Select) is disabled.
- F e. Data rate is controlled by the Data Terminating Equipment (DTE)  
F through Circuit 111.



(ASEM1100)

- F f. Transmit and Receive clocks are supplied by the modem.
- F g. Auto answer is enabled.
- F h. Circuit 112 (Data Rate Indicate) is not supported.
- F i. Neither Circuit 107 nor Circuit 109 should be forced on all the time.
- F j. Dialing is bit synchronous.
- F k. Protocol is high-level data link control (HDLC) with American  
F National Standard Code for Information Interchange (ASCII) code.
- F l. Call origination by the modem is enabled.
- F m. Local digital loopback in response to a remote test request should occur  
F automatically.
- F 10. If the modem has switches for the following, contact the telephone company  
F (or Postal Telephone and Telegraph) about how to set the switches for the  
F following:
  - F a. Injected tone
  - F b. Answer tone
  - F c. Carrier disconnect wait time
  - F d. Time to wait after start of ring before the modem goes off hook
  - F e. Receiver sensitivity
- F 11. Any other switches that may be present should be left as set by the modem  
F manufacturer.

October 5th, 1987

9390-0630100-19870812-104157

3-



# F □ 31 Install the rack power cable in rack A.

1. Ensure that the main circuit breaker (CB1) in the power control section is set to Off.


- F 2. Find the rack power cable. One is shipped with each rack.

- F 3. Select the end with slots visible.


- F 4. This cable goes over the bar, as shown.

- F 5. Align the slots with the pins in the main line connector.

- F 6. Push the power cable end into the main line connector and turn the power cable end clockwise as far as you can (it will not turn very far; less than 1/16 turn).




RSLD137-0



RSLD1C3-1

(ARPC100)


- F 7. Fasten the power  
F cable to the rear bar  
F of the rack:
- F a. Place the power  
F cable between the  
F holes in the bar,  
F as shown.
- F b. Use the  
F thumbscrews to  
F fasten the clamp  
F over the cable.
- F c. Tighten the  
F thumbscrews with  
F the tightening  
F rod.
- F 8. Check to ensure the  
F cable is held tight.



(SRCB100)

- F □ 32 Verify proper seating of the device power cables in  
F rack A.

Ensure that all device power cables plugged into sockets in the power control section are correctly seated.




(SRCB100)

F □ 33 Set the circuit protectors On in rack A.

F For CP1 through CP6 in  
F the power control section:

F Set each circuit protector  
F switch to On (I) if there is  
F a power cable plugged in  
F beside it. *Do this if a  
F power sequence control  
F cable is, or is not, present.*

If there is no power cable,  
leave the switch set to Off  
(O).



(PDRF200)

F □ 34 Go to the front of rack A for the next tasks.

F Detailed verification of the  
F rack contents is not neces-  
F sary.


F However, to become  
F familiar with the rack  
F contents, observe where  
F each device is located.

F The machine type number  
F of each device is located  
F in the upper left corner  
F on the front of each  
F device.

F The numbers to the right  
F in this figure are the EIA  
F values, indicating the  
F device locations. They  
F are shown for reference  
F only; these numbers are  
F normally visible only  
F from the back of the rack.

F Go to the next task.

Front View -- Rack A




9309 Rack Enclosure

(UDSH400)


F □ 35 Prepare the 9347 at EIA 15 in rack A for operation.

1. Pull the release lever under the front bottom left side of the front panel of the 9347, as shown. Pull the 9347 out of the rack until the slide locking tabs lock.



RSLC005-0

2. Open the top cover:
  - Lift and hold the top cover.
  - Set the support arm, as shown.



RF1CC08-2

October 5th, 1987


9390-O630100-19S70812-10-1157

40

(UDSH400)


**Warning:** Do not let go of the tachometer while holding it away from the take-up hub. The tachometer may become damaged if it hits the hub.

- F 3. *Carefully* pivot the  
F tachometer away from  
F the take-up hub and  
hold it tightly. The  
tachometer does not  
lift up.



RSLD274-0

- F 4. Remove the packing  
F material and discard  
F it.




RF1CC50-0

- F 5. *Carefully* pivot the  
F tachometer back  
F against the take-up  
hub.



(UDSH-400)


6. Close the top cover.
  - a. Lift the cover.
  - b. Push the support arm to the rear.
  - c. Lower the cover.




RF1CC31-1

(UDSH-400)

7. Press the slide locking  
F tab on the outside of  
each slide, as shown.




8. Push the 9347 into  
the rack until the  
release lever locks.




(UDSIH200)

# F □ 36 Prepare all 9332s in rack A for operation.


- F 1. For the 9332 located
- F at EIA 04, remove the
- F front cover, as shown.



2. Unlock the shock protection by turning the locking stud counterclockwise at least 10 full turns.



3. Reinstall the front cover, as shown.



4. Perform all steps in this task for each 9332 unit in this rack; there are 2.

October 5th, 1987

9390-O630100-19870812-104157


44

(SDSR100)

- 37 Set the Unit Emergency switch for rack A to the On position.

Set the Unit Emergency switch to the On position.

Nothing occurs; system power has not been turned on yet.




RSLD185-0

(SDSR600)

F □ 38 Set the Power switch on the 9347 at EIA 15 in rack A.

F Set the Power switch to  
F the On position, as  
F shown.

Nothing occurs; the  
system has not been  
powered on yet.




(SDSR400)

## F □ 39 Set the Power switches on all 9332s in rack A.

- F 1. Set the Power switch  
F on the 9332 at EIA 04  
F to the On position, as  
F shown.

Nothing occurs; the  
system has not been  
powered on yet.


2. Perform this task for  
each 9332 unit in this  
F rack; there are 2.




(ADSB100)

- F □ 40 Connect the battery cable and put the key in the 9396  
F at EIA 07 in rack A.

1. Remove the front cover from the 9396 located at EIA 07.



2. Connect the battery cable, as shown.




- F 3. Cut the cable tie, as  
F shown, and remove  
F the keys.


(ADSB100)

F 4. Insert the key into the  
F 9396 keylock.

F 5. Turn the key so that  
F the small black tri-  
F angle on the keylock  
F points to the Manual  
F Power On/Off posi-  
F tion, as shown.



6. Reinstall the 9396  
front cover.






(ASAC100)

# F □ 41 Provide AC power to rack A.

- F 1. Plug the rack power
- F cable into the custom-
- F er's receptacle for AC
- F power.




RSLD003-0

2. Set CP7, the circuit protector for the power supply, to the On (I) position, as shown.



3. Set the main circuit breaker (CB1) in the power control section to the On (I) position, as shown.




RSLD140-0


(ASCP100)

## F □ 42 Power on the system console display.

- F 1. Plug the power cable
- F for the console
- F display into a
- F customer-supplied
- F electrical outlet.



- F 2. Set the Power switch
- F for the display to the
- F On (I) position.




(ASYP100)

F □ 43 Power on the system from the 9396 at EIA 07 in rack A.

On the 9396 device  
located at EIA 07:

- F 1. Verify that 01 A is  
F visible in the control  
F panel windows, as  
F shown.
- F If 01 A is not visible  
F in the windows, go to  
F *Analyzing Problems,*  
F SY31-9063.




2. Push the 9380 Power  
switch up, as shown.

This switch will  
return to the center  
position when you  
release it.

- F The Power On light  
F will come on. If it  
F does not, go to Task  
F 54.

Fans and disk drives will  
start to turn, making  
noise; other lights will  
also go on.




(VPOR100)

F □ 44 Verify rack power-on status from the front of rack A.

The Rack Power Ready light will flash until all devices in the rack have started to power up.

F Wait for the Rack Power Ready  
F Ready light to remain on  
F continuously before going  
F to the next task.

F If the Rack Power Ready  
F light is not on contin-  
F uously after 2 minutes, go  
F to Task 54.



RSLDC07-0


(VPOR700)

F □ 45 Verify power-on status for the 9347 at EIA 15 in rack A.

F Observe the indicators for  
F the 9347 at EIA 15:

1. In 2 minutes or less from power-on time for this rack, the Power light and control panel light 2 should be on continuously. If not, go to Task 54.
2. During part of those 2 minutes, control panel light 2, the Reset light, and the Write Enable light will blink sometimes.

F It is not important  
F that this be observed.



# F □ 46 Verify power-on status for all 9332s in rack A.


F Observe the indicators for  
F the 9332 at EIA 04:

1. In 2 minutes or less from power-on time for this rack, the Power On light and the Unit Ready light should be on continuously. If not, go to Task 54.

2. During part of those 2 minutes, the Unit Ready light will flash.

F It is not important  
F that this be observed.

- F 3. Perform this task for  
F each 9332 in the rack;  
F there are 2.






RSLO152-0


F □ 47 Verify tape load operation for the 9347 at EIA 15 in rack  
F A.

For the 9347 at EIA 15:

- F 1. Locate a scratch tape
- F (one that does not
- F contain valuable
- F information).
2. Remove any covering
- from around the reel.
3. Verify that the tape is
- wound completely on
- the reel.
4. Ensure that a write-
- enable ring is on the
- reel.
5. Open the front door
- of the 9347 unit.
6. Insert the tape reel:
  - Hold the tape reel
  - in a horizontal
  - position with the
  - write-enable ring
  - facing downward.
  - Insert the tape
  - reel into the 9347,
  - as shown.




7. Close the front door.



RF1C038-0


8. Push the Load/Rewind push-button. Control panel light 1 will flash for a short time, then remain on.

Control panel light 4 will come on if a write-enable ring has not been placed on the tape.



RF1C017-0

9. Push the Online push-button. Control panel light 3 will come on after approximately 15 to 30 seconds.




RF1C010-0




(VSTD100)

10. Push the Online pushbutton again. Control panel light 3 will go off.




11. Push the Unload pushbutton. Control panel light 2 will flash as the tape unloads, and will remain on when unloading is complete.



(VSTD100)

12. When control panel light 2 remains on, remove the tape from the 9347 unit and close the front door. Put the covering back on the reel to protect the tape.



13. If any condition in this task does not occur correctly, repeat the task at least once. If the problem

F problem analysis on  
F the 9347, using *Ana-*  
F *lyzing Problems Guide*,  
F SY31-9063.

(AIPL100)

□ 48 Verify that IPL is complete.

When IPL is complete,  
the sign-on display  
appears on the system  
console. If this does not  
occur in a reasonable  
time interval, go to Task  
55.

A reasonable time interval  
would be 3 minutes multi-  
plied by the number of  
racks in the system.


Sign On	
System . . . . .	:
Subsystem . . . . .	: QBASE
Display . . . . .	: QCONSOLE
User ID . . . . .	_____
Program/procedure . . . . .	_____
Menu . . . . .	_____
Current library . . . . .	_____

(C) COPYRIGHT IBM CORP. 1980, 1988.


(VSEM100)

# F □ 49 Test the system support modem.

- F 1. Power off the system  
 F from the 9396 at EIA  
 F 07 in rack A.



- F 2. Turn the key so that  
 F the small black tri-  
 F angle points to the  
 F Normal position, as  
 F shown.
- F 3. Power on the system.



October 5th, 1987

9390-O630100-19870812-104157

61

הַיְיָ אֱלֹהֵינוּ

14

- F  
F  
F  
F**

FF

# History

134 134,134

- F

FF

```

Sign On

System . . . . . :
Subsystem . . . . . : QBASE
Display . . . . . : QCONSOLL

User ID . . . . . CE _____

Program/procedure . . . . . _____
Menu . . . . . _____
Current library . . . . . _____
  
```

(VSEM1100)

7. On the Command line on the next display, type chgctlappc ctld(qesctl) cnnnbr(X), as shown, where X stands for all the digits in the data telephone number of RETAIN. Type the number as you would dial it.

Note: If you do not have this telephone number, contact your support group.

8. Verify that you have typed this information correctly.
9. Press Enter.

10. On the command line of the next display, type sndsrvrqs \*tst, as shown.

11. Verify that you have typed this information correctly.

12. Press Enter.

MAIN		System/3X Main Menu		System: SHW00001
Select one of the following:				
1. User tasks 2. Office tasks 3. General system tasks 4. Files, libraries, and folders 5. Programming 6. Communications 7. Define or change the system 8. Problem handling 9. Display a menu  98. Sign off				
Selection or command				
==> chgctlappc ctld(qesctl) cnnnbr(X) _____				
F3=Exit	F4=Prompt	F13=User support	F23=Set initial menu	(C) COPYRIGHT 1988 IBM CORP. 19XX. 19YY

MAIN		System/3X Main Menu		System: SHW00001
Select one of the following:				
1. User tasks 2. Office tasks 3. General system tasks 4. Files, libraries, and folders 5. Programming 6. Communications 7. Define or change the system 8. Problem handling 9. Display a menu  98. Sign off				
Selection or command				
==> sndsrvrqs *tst _____				
F3=Exit	F4=Prompt	F13=User support	F23=Set initial menu	(C) COPYRIGHT 1988 IBM CORP. 19XX. 19YY

October 5th, 1987

9390-O630100-19870812-104157

63

(VSEMI100)

13. Wait a few minutes for the telephone connection to be made.
14. The message Test request successful. should appear.
15. If any other message appears, or if any problem occurs, go to Task &MTP..

MAIN	System/3X Main Menu	System: SMH00001
Select one of the following:		
1. User tasks 2. Office tasks 3. General system tasks 4. Files, libraries, and folders 5. Programming 6. Communications 7. Define or change the system 8. Problem handling 9. Display a menu  90. Sign off		
Test request successful.		
Selection or command		
====> _____		
F3=Exit	F4=Prompt	F13=User support F23=Set initial menu
(C) COPYRIGHT 1968 IBM CORP. 19XX. 19YY		

October 5th, 1987

9390-0630100-19870812-10-157

64

F ☐ 50 System is available.

F Although some cables remain to be attached, the system is available for customer use.

F NOTE: If any rack or device shows that it is not powered on, go to Task 54, then return here.

F 1. Inform the customer that the system is available for use.

F 2. Explain that you will be attaching the remaining cables.

F 3. Inform the customer to begin with the manual *Attaching Work Station Cables to Your System*, SA21-9957.

F 4. Continue with the next task in these instructions.



## F □ 51 Install remaining communications cables.

- F 1. Locate the Communication Cable Chart on page 75 at the back of these instructions.
- F 2. Note that cables with an \* by the EID number have already been installed.
- F 3. For each additional cable listed in that chart:
  - F a. Find a cable (in the shipping group parts) with the specified part number.
  - F b. Get 2 labels from the shipping group parts.
  - F c. Print the EID number (from the chart) on each label.
  - F d. Fasten a label near each end of the cable.
  - F e. Find the card enclosure at the specified EIA location.
  - F f. Find the card in the specified slot.
  - F g. Compare the ends of the cable with the port on the card.
    - F • If the port has holes visible, select the cable end with pins visible.
    - F • If the port has pins visible, select the cable end with holes visible.
  - F h. Push the selected end of the cable under the bar and into the rack.
  - F i. Attach the cable to the specified port on that card.
  - F j. Verify that the cable is fastened tightly.
- F If you are not sure about how to do any of the above steps, see Task 24 and Task 25 in these instructions. (Make reference to those tasks as examples only; do not use the specific information given there.)

## F □ 52 Install cable ties in the rack.


F ALL cables entering or  
F leaving a rack should be  
F tied tightly to the bar at  
F the bottom of the rack.

F They do not have to be  
F tied separately; they can  
F be tied in groups.

F Do not pull the cables  
F tight; let them hang  
F naturally.

F 1. Get the cable ties  
F from the shipping  
F group parts.

F 2. Tie the cables to the  
F bar, as shown.



October 5th, 1987

9390-O630100-19870812-104157

67

F ☐ 53 Job is complete.

F If any rack or device  
F shows that it is not  
F powered on, go to Task  
F 54.

F 1. Close all open covers.


F 2. Inform the customer  
F that system hardware  
F installation is com-  
F plete.

F 3. Inform the customer  
F to use the manual  
F *Attaching Work*  
F *Station Cables to Your*  
F *System, SA21-9957.*

F 4. Perform normal clean  
F up tasks.

F 5. Keep the last few  
F pages of these  
F instructions (starting  
F with page 72) with the  
F system. Put them in  
F the binder supplied  
F for the *Analyzing*  
F *Problems Guide,*  
F SY31-9063.

F 6. Destroy the other  
F pages of these  
F instructions.



RSLD184-0

## □ 54 If there is a problem at power-on time . . .

F Decide which condition below best describes the conditions and follow the  
F instructions given.

F 1. If the display windows on the operator's control panel showed something  
F but nothing else occurred, or if nothing at all occurred when you attempted  
F to power on the system, do the following:

F a. Verify that:

- F ☐ The Keylock switch is set to the Manual Power On/Off position.
- F ☐ The rack Unit Emergency switch is set On.
- F ☐ There is a terminating plug correctly installed in socket J10.
- F ☐ The rack power cable is correctly installed and plugged in to the  
F power source.
- F ☐ CB1 and CP7 in the rack power control section are set On.
- F ☐ A device power cable is plugged into the 9396 located at EIA 07  
F with the other end plugged in the rack power control section.
- F ☐ CP1-CP6 circuit protectors are set On for all devices plugged into  
F the power control section.
- F ☐ The device CB on the back of the 9396 located at EIA 07 in rack A  
F is set On.
- F ☐ Correct AC voltage is present at the power source.

F b. Attempt to power on the system once more. If the failure remains,  
F perform analysis using the *Analyzing Problems Guide*, SY31-9063.

F c. If the problem has been corrected, return to the task that sent you here.

F 2. If some, but not all, racks powered on, perform the following steps:

F a. Note which rack(s) did not power on.

F b. Power off the system at the operator's control panel of the 9396 located  
F at EIA 07 in rack A.

(SPUP100)

- F c. For each rack that did not power on correctly, verify that:
- F ☐ The rack power cable is correctly installed and plugged into the
- F power source.
- F ☐ CBI and CP7 in the power control section are set On.
- F ☐ Correct AC voltage is present at the power source.
- F d. Attempt to power on the system once more. If the failure remains,
- F perform analysis using the *Analyzing Problems Guide*, SY31-9063.
- F e. If the problem has been corrected, return to the task that sent you here.
- F 3. If all racks powered on, and some, but not all, devices powered on, do the
- F following:
- F a. Make a note of any device(s) that failed to power on as expected.
- F b. Power off the system at the operator's control panel of the 9396 located
- F at EIA 07 in rack A.
- F c. For each device that did not power on correctly, verify that:
- F ☐ The power switch on the front of the device is set On.
- F ☐ The circuit breaker on the device is set On.
- F ☐ The power cable is installed and both ends are correctly seated (at
- F the device and in the power control section).
- F ☐ The circuit protector in the rack power control section is set On.
- F d. Power on the system.
- F ☐ If any of the devices that did not power on correctly are card enclo-
- F sures, press their Power On switch upward (the switch will return to
- F the center position when released).
- F e. If the failure remains, perform analysis using the *Analyzing Problems*
- F *Guide*, SY31-9063.
- F f. If the problem has been corrected, return to the task that sent you here.
- F 4. If any of the device Unit Ready lights do not remain on continuously after
- F flashing, perform analysis using the *Analyzing Problems Guide*, SY31-9063.

□ 55 If there is a problem at IPL time . . .

F If power on occurred correctly for all devices but the system failed to IPL, do  
F the following:

F 1. Power off the system at the operator's control panel on the 9396 located at  
F EIA 07 in rack A.

F 2. Verify that:

F □ The Keylock switch is set to the Manual Power On/Off position.

F □ The signal cables that go from one device to another device are cor-  
F rectly installed. All connections must be tight. See the Cable List on  
F page 74 at the back of these instructions.

F □ The signal cable terminating plugs are correctly installed and are tight.  
F See the Cable List on page 74 at the back of these instructions.

F □ The address switches on all devices are set correctly. See the Cable List  
F on page 74 at the back of these instructions.

F DANGER

F If a disconnected cable is found in the next step, DO NOT attempt to connect  
F it until the work station console device (and all other devices connected to it)  
F are powered off and unplugged.

F □ The system console signal cable is attached correctly to the twinaxial  
F work station attachment that is connected to a 6040 card in the card  
F enclosure located at EIA 07 in rack A. See the Cable List on page 74  
F at the back of these instructions.

F □ The system console power cable is plugged into the power source and  
F the system console power switch is set to the On position.

F 3. Power on the system from the operator's control panel on the 9396 located  
F at EIA 07 in rack A. IPL occurs as part of the power on process.

F 4. If the problem remains, use *Analyzing Problems*, SY31-9063 to analyze fail-  
F ures.

F 5. If the problem has been corrected, return to the task that sent you here.

(PARHIDR)

The remaining pages of these instructions should be used for problem analysis resolution purposes during installation.

October 5th, 1987


9390-O630100-19870S12-104157

72

(RCKCL)

# Rack Configuration List

## Back View -- Rack A



9309 Rack Enclosure

Card Enc = 9396

EIA Loc = 07

ADDR SLOT CARD

	01	AF04
	02	3055
	03	3054
	04	2500
	05	2504
0010	06	6010
0020	07	6130
0030	08	6034
0040	09	6031
0050	10	6130
0060	11	6032
0070	12	6040
	13	AF12



(DCABCT)

## Cable List

## Signal Cable Chart

EID#	Cable P/N	Path	Rack ID	Device Type-Model	EIA Loc	Card FN Slot	Port	System Address
029*	6495254	from	A	9396-630	07	6010 06	1	
		to	A	9332-200	04		In	0
030*	6495253	from	A	9332-200	04		Out	0
		to	A	9332-200	01		In	1
028*	6495250	from	A	9332-200	01		Out	1
		to	A	9347-001	15		In	7
	TERM	term	A	9347-001	15		Out	7

TERM = Terminating plug

EID# = Element ID number which uniquely identifies each cable.  
Inter-rack cables may have been labeled.

FN = Feature Number.

\* = Previously Installed Cable.

(DCABCT)

## Cable List

## Communication Cable Chart

EID#	Cable P/N	Path	Rack ID	Device Type-Model	EIA Loc	Card FN Slot	Port	System Address
016*	70X8655	from	A	9396-630	07	6031 09	1	
015	70X8655	from	A	9396-630	07	6031 09	2	
014	92X2785	from	A	9396-630	07	6032 11	1	
013	6165837	from	A	9396-630	07	6034 08	1	

TERM = Terminating plug

EID# = Element ID number which uniquely identifies each cable.

Inter-rack cables may have been labeled.

FN = Feature Number.

\* = Previously Installed Cable.

## Cable List

## Work Station Attachment Cable Chart

EID#	Cable P/N	Path	Rack ID	Device Type-Model	EIA Loc	Card FN Slot	Port	System Address
012*	2438316	from	A	9396-630	07	6040 12	1	

TERM = Terminating plug

EID# = Element ID number which uniquely identifies each cable.  
Inter-rack cables may have been labeled.

FN = Feature Number.

\* = Previously Installed Cable.

RU987-022

## HIGH LEVEL FLOW DIAGRAM




FIG. 1

R0987-022




FIG. 2

R0987-022

## HPCS RECORD DESCRIPTION

FILE NAME: STSTOPOL      DESC NAME: SYSTEM TOPOLOGY DESCRIPTION  
 RECORD NAME: STDHEADR      DESC NAME: STD HEADER RECORD

CHARACTER	ZONED DEC	PACKED DEC	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X				3	001-003	ELMID	ELEMENT IDENTIFIER
X				2	004-005	RCDTP	RECORD TYPE
X				4	006-009	IDSYS	SYSTEM TYPE
X				7	010-016	SYNUM	SYSTEM NUMBER
X				8	017-024	DTELU	DATE LAST UPDATE
X				6	025-030	TMENT	TIME LAST UPDATE
X				3	031-033	WTCTN	WORLD TRADE COUNTRY
X				6	034-039	RLLVL	RULES LEVEL
X		X		4	040-043	BOXSD	BOX SHIP DATE
X				4	044-047	UPCID	UPGRADE CONTROL ID
X				4	048-051	PLUPC	PREV LEVEL UPCID
X				1	052-052	SPTYP	SERVICE PROCESSOR TYPE
X				48	053-100	FIL78	EXPANSION AREA

FIG. 3A

R0987-022

## HPCS RECORD DESCRIPTION

FILE NAME: STSTOPOL

DESC NAME: SYSTEM TOPOLOGY DESCRIPTION

RECORD NAME: STDELEMT

DESC NAME: STD ELEMENT RECORD

CHARACTER	ZONED DEC	PACKED DEC	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X				3	001-003	ELMID	ELEMENT IDENTIFIER
X				2	004-005	RCDTP	RECORD TYPE
X				3	006-008	ELMFR	PARENT ELEMENT IDENTIFIER
X				4	009-012	IDMAC	MACHINE TYPE
X				3	013-015	IDSMN	SALES MODEL
X				6	016-021	DVRPQ	DEVICE/RPQ CODE
X				10	022-031	BMNUM	BILL OF MATERIAL NUMBER
X				4	032-035	FILO4	FILLER
X				1	036-036	ELMTP	ELEMENT TYPE
X				1	037-037	ELMST	ELEMENT SUBTYPE
X				1	038-038	ELSCD	ELEMENT SOURCE CODE
X				9	039-047	MACSR	MACHINE SERIAL#/ORDER#
X	X			5	048-052	CORDX	X-COORDINATE LOCATION
X	X			5	053-057	CORDY	Y-COORDINATE LOCATION
X				4	058-061	LOCCD	LOCATION DESCRIPTION
X				1	062-062	MGOFF	MOUNTING GROUP OFFSET
X				1	063-063	DFSWA	DFCI SWITCH A SETTING
X				1	064-064	DFSWB	DFCI SWITCH B SETTING
X				1	065-065	DFTRA	DFCI TERMINATOR A STRING
X				1	066-066	DFTRB	DFCI TERMINATOR B STRING
X				1	067-067	DEVST	DEVICE STATUS
X				3	068-070	DRIVA	DRIVER-'A' STRING OR ONLY
X				3	071-073	DRIVB	DRIVER-'B' STRING
X				10	074-083	SDATA	S/370 ADDRESS DATA
X				1	084-084	IPLDC	IPL DEVICE
X				1	085-085	PSDVC	PRIMARY/SECONDARY DEVICE CODE
X				15	086-100	FIL16	FILLER -- EXPANSION AREA

FIG. 3B

R0987-022

## HPCS RECORD DESCRIPTION

FILE NAME: SYSTOPOL      DESC NAME: SYSTEM TOPOLOGY DESCRIPTION  
 RECORD NAME: STDCABLE    DESC NAME: STD CABLE RECORD

CHARACTER	ZONED DEC	PACKED DEC	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X				3	001-003	ELMID	ELEMENT IDENTIFIER
X				2	004-005	RCDTP	RECORD TYPE
X				3	006-008	MACID	ID OF MACHINE ORDER
X				6	009-014	DVRPQ	DEVICE/RPQ CODE
X				10	015-024	BMNUM	BILL OF MATERIAL NUMBER
X				4	025-028	FILO4	FILLER
X				1	029-029	ELMTP	ELEMENT TYPE
X				1	030-030	ELMST	ELEMENT SUBTYPE
X				1	031-031	ELSCD	ELEMENT SOURCE CODE
							'FROM' LOC DATA
X				3	032-034	ELMFR	'FROM' ELEMENT IDENTIFIER
X				4	035-038	LOCCD	LOCATION DESCRIPTION
	X			5	039-043	CORDX	X- COORDINATE LOCATION
	X			5	044-048	CORDY	Y- COORDINATE LOCATION
							END 'FROM' LOC DATA
							'TO' LOC DATA
X				3	049-051	ELMTO	'TO' ELEMENT IDENTIFIER
X				4	052-055	LOCCD	LOCATION DESCRIPTION
	X			5	056-060	CORDX	X- COORDINATE LOCATION
	X			5	061-065	CORDY	Y- COORDINATE LOCATION
							END 'TO' LOC DATA
							2ND 'TO' LOC DATA
X				3	066-068	ELMTO	'TO' ELEMENT IDENTIFIER
X				4	069-072	LOCCD	LOCATION DESCRIPTION
	X			5	073-077	CORDX	X- COORDINATE LOCATION
	X			5	078-082	CORDY	Y- COORDINATE LOCATION
							END 2ND 'TO' LOC DATA
X					083-083	DEVST	DEVICE STATUS
X					084-084	PSDVC	PRIMARY/SECONDARY DEVICE CODE
X					085-100	FIL17	FILLER -- EXPANSION AREA

FIG. 3C



R0987-022

## HPCS RECORD DESCRIPTION

1.1.6 FILE NAME: ELEMDESC      DESC NAME: ELEMENT DESCRIPTION FILE

1.1.6.1 RECORD NAME: LEVELCTL      DESC NAME: RELEASE LEVEL CONTROL RECORD

CHARACTER	ZONED DEC	PACKED DEC	BINARY	SIGNED	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X						1	001-001	RCDTP	RECORD TYPE
X						4	002-005	FIL04	FILLER- EXPANSION AREA
X						15	006-020	FIL15	FILLER- TEXT AREA
X						6	021-026	RLLVL	RELEASE LEVEL
X						23	027-049	FIL23	FILLER- TEXT AREA
X						6	050-055	DEVNU	RULES LEVEL SPECIFY
X						195	056-250	FL195	FILLER

FIG. 4A

R0987-022

## HPCS RECORD DESCRIPTION

FILE NAME: ELEMDESC      DESC NAME: ELEMENT DESCRIPTION FILE

1.1.6.2 RECORD NAME: DEVTABLE      DESC NAME: DEVICE TO B/M CONVERS TABLE

CHARACTER	ZONED DEC	PACKED DEC	BINARY	SIGNED	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X						1	001-001	RCDTP	RECORD TYPE
X						4	002-005	FILO4	FILLER- EXPANSION AREA
X						4	006-009	IDMAC	MACHINE TYPE
X						3	010-012	IDSMN	SALES MODEL
X	X					2	013-014	SEQNM	SEQUENCE NUMBER
X						11	015-025	FIL11	EXPANSION AREA
225 BYTES---ARRAY OF 9 SETS OF DEVICE CODES									
X						6	026-	DVRPQ	DEVICE/RPQ CODE
X						2		BMSEQ	BILL OF MATERIAL SEQUENCE
X						10		BMNUM	BILL OF MATERIAL NUMBER
X						7	-250	FIL07	EXPANSION AREA

FIG. 4B

R0987-022

## HPCS RECORD DESCRIPTION

FILE NAME: ELEMDESC      DESC NAME: ELEMENT DESCRIPTION FILE  
 RECORD NAME: BASELEMT    DESC NAME: BASIC ELEMENT RECORD

CHARACTER	ZONED DEC	PACKED DEC	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X				1	001-001	RCDTP	RECORD TYPE
X				4	002-005	FILO4	FILLER - EXPANSION AREA
X				10	006-015	BMNUM	BILL OF MATERIAL NUMBER
X				8	016-023	FIL10	EXPANSION AREA
X	X			2	024-025	FNLVL	FUNCTIONAL LEVEL
X				1	026-026	ELMTP	ELEMENT TYPE
X				1	027-027	ELMST	ELEMENT SUBTYPE
X				10	028-037	ELMNM	DESCRIPTIVE NAME
X				10	038-047	HPCDN	HPCS DEVICE NAME
X				10	048-057	ACCES	ACCESSORY PART NUMBER
	X			4	058-061	EXWDT	EXTERNAL WIDTH
	X			4	062-065	INWDT	INTERNAL WIDTH
	X			2	066-067	EHGHT	HEIGHT (EIA UNITS)
	X			5	068-072	MLGHT	LENGTH OR HEIGHT (MM)
	X			4	073-076	MDPTH	DEPTH (MM)
	X		1	4	077-080	KWGHT	WEIGHT (KILOGRAMS)
	X			3	081-083	PWRVL	POWER VALUE (KVA)
	X			1	084-084	MGOFF	MOUNTING GROUP OFFSET
	X			4	085-088	MCBIN	CABLE LGTH INCREM (MM)
	X			2	089-090	PWOCT	POWER OUTLETS COUNT
	X			2	091-092	ARMCT	DASD ARMS COUNT
	X			2	093-094	CPTCT	CONTROL OF PORT COUNT
	X			2	095-096	DEVCT	COUNT OF DEVICES CARD CAN DRIVE
	X			1	097-097	BUSCT	COUNT OF BUSES
	X			4	098-101	INTWL	INTERNAL WIRING LENGTH
X				3	102-104	FILO3	FILLER - EXPANSION AREA
X	X			2	105-106	FWCSN	FIRST WIDE CARD SLOT NUMBER
X				1	107-107	SWDEV	SWITCHED DASD DEVICE FLAG
X				1	108-108	TRMTP	TERMINATOR TYPE
X				1	109-109	HPADD	DEVICE ADDED BY HPCS
X				4	110-113	IDMAC	MACHINE TYPE (HPCS ADDS ONLY)
X				3	114-116	IDSMN	SALES MODEL (HPCS ADDS ONLY)
X				6	117-122	DVRPQ	DEVICE/RPQ CODE (HPCS ADDS ONLY)
X				1	123-123	CBEXL	CABLE EXIT LOCATION
X				1	124-124	TOWMT	TOWER MOUNTED DEVICE
X				1	125-125	DPOCD	DELAYED POWER OFF CODE
	X			3	126-128	LVKVA	110V RACK KVA OVERRIDE
	X			3	129-131	COGRX	CENTER OF GRAVITY X COORDINATE
	X			3	132-134	COGRY	CENTER OF GRAVITY Y COORDINATE
	X			3	135-137	COGRZ	CENTER OF GRAVITY Z COORDINATE
X				4	138-141	STCAP	DASD STORAGE CAPACITY
X				13	142-154	FIL17	FILLER - EXPANSION AREA
96				BYTES---ARRAY OF 6 SETS OF COORDINATES			
X				4	155-	LOCCD	LOCATION DESCRIPTION
X				4		JAKNM	JACK NUMBER FOR PLUG
	X			4		CORDX	X- COORDINATE LOCATION
	X			4	-250	CORDY	Y- COORDINATE LOCATION
				END OF ARRAY			

FIG. 4C

R0987-022

## HPCS RECORD DESCRIPTION

FILE NAME: ELEMDESC DESC NAME: ELEMENT DESCRIPTION FILE

RECORD NAME: COMMSPEC DESC NAME: COMM SPECIFY CODE DEFINITION.

CHARACTER	ZONED DEC	PACKED DEC	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X				1	001-001	RCDTP	RECORD TYPE
X				4	002-005	IDSYS	SYSTEM TYPE
X				2	006-007	SEQNM	SEQUENCE NUMBER
X				35	008-042	FIL35	FILLER AREA FOR KEY
208 BYTES---ARRAY OF 8 SETS OF COMMUNICATION LINES---							
X				3	043-	SPCPF	SPECIFY CODE PREFIX
X				1		FIL01	FILLER - EXPANSION AREA
X				1		ELEIF	ELECTRICAL INTERFACE
X				1		PROTO	COMMUNICATIONS PROTOCOL
X				1		CNNCT	CONNECTION 'TO' PARAMETER
X				1		LSCAT	LINE SPEED CATEGORY
X				1		CSSTP	COMMUNICATION SUBSYSTEM TYPE
X				1		FIL02	EXPANSION AREA
X				10		BMNUM	BILL OF MATERIAL NUMBER
X				06	-250	FIL06	FILLER - EXPANSION AREA
END OF ARRAY							

FIG. 4D

R0987-022

## HPCS RECORD DESCRIPTION

FILE NAME: ELEMDESC      DESC NAME: ELEMENT DESCRIPTION FILE  
 RECORD NAME: LNSPDCAT    DESC NAME: LINE SPEED CATEGORY RECORD

CHARACTER	ZONED DEC	PACKED DEC	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X				1	001-001	RCDTP	RECORD TYPE
X				4	002-005	IDSYS	SYSTEM TYPE
X				2	006-007	SEQNM	SEQUENCE NUMBER
X				18	008-025	FIL18	FILLER AREA FOR KEY
-220 BYTES---ARRAY OF 22 SETS OF LINE SPEED PARAMETERS-							
X				1	026-	SPCSF	SPECIFY CODE PREFIX
X				1		LSCAT	LINE SPEED CATEGORY
X	X			4		LNSPD	LINE SPEED
X				4	-245	FIL04	FILLER - EXPANSION AREA
END OF ARRAY							
X				05	246-250	FIL05	FILLER - EXPANSION AREA

FIG. 4E

R0987-022

## HIRS RECORD DESCRIPTION

FILE NAME: COMON TASK

DESC NAME: COMPONENT TASK FILE

RECORD NAME: CPTASKIT

DESC NAME: COMPONENT TASK INCLUDE

CHARACTER	ZONED DEC	PACKED DEC	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X				2	001-002	TTYPE	TASK TYPE TO EXECUTE
X				1	003-003	HANCD	HANDLING CODE
X				10	004-013	HPCDN	HPCS DEVICE NAME
X				1	014-014	ELMTP	ELEMENT TYPE
X				1	015-015	ELMST	ELEMENT SUBTYPE
X				1	016-016	FILL1	RESERVED -- EXPANSION AREA
X				1	017-017	GROUP	TASK GROUP FLAG (GROUPED IF "G")
X				4	018-021	TIXRF	TASK ID - CROSS REFERENCE NO.
X				3	022-024	TIGRP	TASK ID - GENERAL GROUPING NO.
X				8	025-032	FILL2	RESERVED -- EXPANSION AREA
X				1	033-033	PERSP	TASK PERSPECTIVE
X	X			3	034-036	GLSQN	GOAL SEQUENCE STEP NUMBER
X	X			3	037-039	UPDSQ	UPDATE SEQUENCE STEP NUMBER
X				1	040-040	STATE	TASK STATE
X				1	041-041	DIRET	TASK DIRECTION
X				1	042-042	POWST	POWER STATUS
X				1	043-043	SUBCP	SUB COMPONENT IDENTIFICATION
X					044-	TCMTM	TASK COMPLETION TIME
X				3	044-046	TCMTP	PRIMARY TIME TO COMPLETE TASK
X				3	047-049	TCMTA	ALTERNATE TIME IF TASK IS IN A GROUP
X				1	050-050	MUPID	MODEL UPGRADE INDICATOR
X				10	051-060	PHPDN	PARENT DEVICE NAME
X				1	061-061	CABRL	CABLE RELATIONSHIP
X				1	062-062	HANLR	HANDLER CODE
X				1	063-063	CINTK	CHARACTERIZE INDEPENDENT TASK
X				1	064-064	CLASS	CLASS OF VALUES TO BE SET FOR TASK
X				1	065-065	SPCLS	SPECIAL CLASS OF VALUES TO BE SET
X				15	066-080	FIL15	RESERVED -- EXPANSION AREA

FIG. 5

R0987-022

## HIRS RECORD DESCRIPTION

FILE NAME: ITDELTA

DESC NAME: INTERMEDIATE DELTA FILE

RECORD NAME: ITDELTA

DESC NAME: INTERMEDIATE DELTA

CHARACTER	ZONED DEC	PACKED DEC	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X				2	001-002	TTYPE	TASK TYPE TO EXECUTE
X				1	003-003	HANCD	HANDLING CODE
	X			5	004-008	TSEQN	TASK SEQUENCE NUMBER
					009-	TSKID	TASK IDENTIFICATION NUMBER
X				4	009-012	TIXRF	TASK ID- CROSS REFERENCE NUMBER
X				3	013-015	TIGRP	TASK ID- GENERAL GROUPING NUMBER
X				1	016-016	POWST	POWER STATUS
X				1	017-017	SUBCP	SUB COMPONENT CODE
					018-	TCMTM	TASK COMPLETION TIME
	X			3	018-020	TCMTP	PRIMARY TIME TO COMPLETE TASK
	X			3	021-023	TCMTA	ALTERNATE TIME IF TASK IS IN A GROUP
X				1	024-024	RPERM	REMOVE PERMANENTLY FLAG
X				1	025-025	HANLR	HANDLER CODE
X				1	026-026	PERSP	TASK PERSPECTIVE
X				3	027-029	GLSQN	GOAL SEQUENCE STEP NUMBER
X				3	030-032	UPDSQ	UPDATE SEQUENCE STEP NUMBER
X				1	033-033	STATE	TASK STATE
X				1	034-034	DIRET	TASK DIRECTION
X				1	035-035	MUPID	MODEL UPGRADE INDICATOR
					036-	HPAGE	PARENTAGE
X				3	036-038	ELIL1	ELEMENT IDENTIFIER LEVEL 1 (RACK)
X				4	039-042	LOCL1	LOCATION CODE LEVEL 1
X				3	043-045	ELIL2	ELEMENT IDENTIFIER LEVEL 2 (DEVICE)
	X			5	046-050	CORY2	COORDINATE Y LEVEL 2
X				4	051-054	LOCL2	LOCATION CODE LEVEL 2
X				3	055-057	ELIL3	ELEMENT IDENTIFIER LEVEL 3 (CARD)
	X			5	058-062	CORY3	COORDINATE Y LEVEL 3
X				4	063-066	LOCL3	LOCATION CODE LEVEL 3
X				3	067-069	ELIL4	ELEMENT IDENTIFIER LEVEL 4 (CABLE)
	X			5	070-074	CORY4	COORDINATE Y LEVEL 4
X				4	075-078	LOCL4	LOCATION CODE LEVEL 4
X				6	079-084	CPFC4	CABLE'S PARENT FEATURE CODE NUMBER
X				1	085-085	CABRL	CABLE RELATIONSHIP
X				1	086-086	NCBLE	NUMBER OF CABLE ENDS
X				1	087-087	GROUP	TASK GROUP FLAG (GROUPED IF "G")
X				1	088-088	CLASS	CLASS OF VALUES TO BE SET FOR TASK
X				1	089-089	SPCLS	SPECIAL CLASS OF VALUES TO BE SET
X				31	090-120	FILLR	RESERVED -- EXPANSION AREA

THE REMAINDER OF THIS RECORD FORMAT CONSISTS OF THE STDELEMT RECORD FROM THE SYSTOPOL FILE. PLEASE REFER TO IT FOR THE REST OF THE FORMAT.

FIG. 6

R0987-022

NOVEMBER 3RD, 1987 4:52 P.M.

FILE: "TRANSLAT TABLE A"

XXXXXXXXXXXXXXXXXXXXX TASK MODULE CHARTS XXXXXXXXXXXXXXXXXXXXXXXX

"K" = KABLING CHART FOR PSEUDO TASKS

	B1	B3	B6
PNLC1K	1C	123	122
PNLC2K	2C		
PNCL1K	1C		

FIG. 7A

(ELMTP &amp; ELMST FIELDS)

B1 - DFCI OR BUS EXTEND CABLE

B3 - COMMUNICATIONS CABLE

B6 - TWIN-AX CABLE

"C" = CARD CHART FOR PSEUDO TASK EXTENSIONS

	6019	6018	6010	
PNLC1C	114	124	121	1P
PNLC2C	214	224		2P
PNCL1C	114	124	121	1P

FIG. 7B

(DVRPQ FIELD OF PARENT ELEMENT)

6018 - BUS EXTEND DRIVER CARD

6019 - BUS EXTEND RECV'R CARD

---- - ELEMENTS WHICH ARE NOT CARDS

"P" = PORT CHART

	PWSI	PWSO	DI01	DO01	DC01	DC02	DC03	DC04
PNLC1P			111	121	111	111	111	111
PNLC2P			211	221	211	211	211	211
PNCL1P			111	121	111	111	111	111
RDSC1P					110	120	130	140
ADSC1P					110	120	130	140
RDDC1P			110	120				
ADDC1P			110	120				
RDDC2P			210	220				
ADDC2P			210	220				
RDDC3P			310	320				
ADDC3P			310	320				
RDDC4P			41L	42L				
ADDC4P			41L	42L				
RRSC1P	110	120						
ARSC1P	110	120						

(LOCFR/LOCTO FIELD)

PWSI - PWR SEQ (IN)

PWSO - PWR SEQ (OUT)

DI01 - DFCI (IN)

DO01 - DFCI (OUT)

DC01 - SIGNAL PORT 1

DC02 - SIGNAL PORT 1

DC03 - SIGNAL PORT 1

DC04 - SIGNAL PORT 1

FIG. 7C

"L" = LOCATION CHART

	L	R
RDPC7L	701	702
ADPC7L	701	702
RDDT4L	401	402
ADDT4L	401	402
RDEV6L	601	602
ADEV6L	601	602
RDDC41L	411	412
ADDC41L	411	412
RDDC42L	421	422
ADDC42L	421	422
SDAS5L	551	552
VDCT4L	401	402

(LOCCD FIELD)

L - LEFT MOUNTED LOCATION

R - RIGHT MOUNTED LOCATION

FIG. 7D

"M" = MODEL CHART

	B10	B20	B30	B40	F10	F20	F30	F40	F50
RDBC1M			100	200					
ADBC1M			100	200					

(IDSMN FIELD)

FIG. 7E



K0987-022

XXXXXXXXXXXXXXXXXXXXXXXXXXXXX TASK GRAPHICS CHARTS XXXXXXXXXXXXXXXXXXXXXXXXXXXXXXXX  
"V", "W" & "G" CHARTS ARE ROTATED 90 DEGREES (DVRPG FIELD)

"V" CHART	R C D T 1 V	A C D T 1 V	R C R T 2 V	A C D T 2 V
6030	110	110		
XXXX	111	111		
4004	112	112		
4008	113	113		
4012	114	114		
XXXX	115	115		
XXXX	116	116		
XXXX	117	117		
XXXX	118	118		
XXXX	119	119		
2500	120	120		
2501	121	121		
2502	122	122		
2503	123	123		
XXXX	124	124		
XXXX	125	125		
XXXX	126	126		
XXXX	127	127		
XXXX	128	128		
2504	129	129		
2505	130	130		
2506	131	131		
AF12			210	210
AF04			211	211

FIG. 7F

```

COMM  CNTLR
      (ENHANCED)
      STORAGE
      |
      V
      STORAGE
IMPI  1
IMPI  2
IMPI  3
IMPI  4
FA1
FA2
FA3
FA4
FA5
C1 (BA/SP1)
C2 (BA/SP2)
C3 (BA)
AF 1.2 (4592)
AF 0.7 (4591)

```

"W" CHART	R	A
	C	C
	D	D
	T	T
	3	3
	W	W
6018	316	316
6019	317	317
6010	310	310
6040	311	311
6034	312	312
6050	313	313
6031	314	314
6032	315	315

FIG. 7G

```
BUS EXT DVR
BUS EXT RCV
DFCI CNTLR
W.S. CNTLR
LAN ADPTR
W.S. CNTLR
SDLC COMM
ASYC COMM
```

"G" CHART	R C S C 3 G	A C S C 3 G	R C S C 1 G	A C S C 1 G	R C S C 2 G	A C S C 2 G
6019	610	610				
6018	611	611				
6010			410	410		
6040			411	411		
6034			412	412		
6050					51X	51X
6031					52X	52X
6032					53X	53X

FIG. 7H

```
BUS EXT DVR
BUS EXT RCV
DFCI CNTLR
W.S. CNTLR
LAN ADPTR
W.S. CNTLR
SDLC COMM
ASYC COMM
```

"X" = EXTENSIONS CHART FOR PORTS

	C C O 1	C C O 2	C C O 3	C C O 4
RCSC51X	510	511		
ACSC51X	510	511		
RCSC52X	512	513		
ACSC52X	512	513		
RCSC53X	514	515	516	517
ACSC53X	514	515	516	517

```
(LOC FM FIELD)
CC01 - PORT 1
CC02 - PORT 2
CC03 - PORT 3
CC04 - PORT 4
```

FIG. 7I

"S" = SWITCH SETTING CHART

	0	1	2	3	4	5	6	7
SDAS1S	100	110	120	130	140	150	160	170
SDAS2S	100	110	120	130	140	150	160	170
SDAS3S	100	110	120	130	140	150	160	170
SDAS4S	400	410	420	430	440	450	460	470
SDAS5S1	500	510	520	530	540	550	560	570
SDAS5S2	500	510	520	530	540	550	560	570

```
(DFSWA FIELD)
0 - DFCI ADDRESS 0
1 - DFCI ADDRESS 1
2 - DFCI ADDRESS 2
3 - DFCI ADDRESS 3
4 - DFCI ADDRESS 4
5 - DFCI ADDRESS 5
6 - DFCI ADDRESS 6
7 - DFCI ADDRESS 7
```

FIG. 7J

R0987-022

## HIRS RECORD DESCRIPTION

FILE NAME: DELTAHHF

DESC NAME: DELTA HARDWARE HANDLING FILE

RECORD NAME: DELTAHHI

DESC NAME: DELTA HARDWARE HANDLING

CHARACTER	ZONED DEC	PACKED DEC	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X				2	001-002	TTYPE	TASK TYPE TO EXECUTE
X				1	003-003	HANCD	HANDLING CODE
	X			5	004-008	TSEQN	TASK SEQUENCE NUMBER
					009-	TSKID	TASK IDENTIFICATION NUMBER
X				4	009-012	TIXRF	TASK ID- CROSS REFERENCE NUMBER
X				3	013-015	TIGRP	TASK ID- GENERAL GROUPING NUMBER
X				1	016-016	POWST	POWER STATUS
X				1	017-017	SUBCP	SUB COMPONENT INDICATOR
					018-	TCMTM	TASK COMPLETION TIME
	X			3	018-020	TCMTP	PRIMARY TIME TO COMPLETE TASK
	X			3	021-023	TCMTA	ALTERNATE TIME IF TASK IS IN A GROUP
X				1	024-024	RPERM	REMOVE PERMANENTLY FLAG
X				1	025-025	HANLR	HANDLER CODE
					026-	HPAGE	PARENTAGE
X				3	026-028	ELIL1	ELEMENT IDENTIFIER LEVEL 1 (RACK)
X				4	029-032	LOCL1	LOCATION CODE LEVEL 1
X				3	033-035	ELIL2	ELEMENT IDENTIFIER LEVEL 2 (DEVICE)
	X			5	036-040	CORY2	COORDINATE Y LEVEL 2
X				4	041-044	LOCL2	LOCATION CODE LEVEL 2
X				3	045-047	ELIL3	ELEMENT IDENTIFIER LEVEL 3 (CARD)
	X			5	048-052	CORY3	COORDINATE Y LEVEL 3
X				4	053-056	LOCL3	LOCATION CODE LEVEL 3
X				3	057-059	ELIL4	ELEMENT IDENTIFIER LEVEL 4 (CABLE)
	X			5	060-064	CORY4	COORDINATE Y LEVEL 4
X				4	065-068	LOCL4	LOCATION CODE LEVEL 4
X				6	069-074	CPFC4	CABLE'S PARENT FEATURE CODE NUMBER
X				1	075-075	NCBLE	NUMBER OF CABLE ENDS
X				3	076-078	GRAPHID	GRAPHICS MODULE ID NUMBER FOR PUBS
X				1	079-079	GROUP	TASK GROUP FLAG (GROUPED IF "G")
X				1	080-080	CLASS	CLASS OF VALUES TO BE SET FOR TASK
X				1	081-081	SPCLS	SPECIAL CLASS OF VALUES TO BE SET
X				19	082-100	FILLR	RESERVED -- EXPANSION AREA
THE REMAINDER OF THIS RECORD FORMAT CONSISTS OF THE STDELEMT RECORD FROM THE SYSTOPOL FILE.							

FIG. 8

R0987-022

## LOGIC FLOW OF HIRSU00




FIG. 9A

R0987-022

## LOGIC FLOW OF HIRSU00




FIG. 9B

R0987-022

## LOGIC FLOW OF HIRSU00




FIG. 9C

R0987-022

## LOGIC FLOW OF HIRSU00




FIG. 9D

R0987-022

## HIRS LAYER 3 PROGRAM FLOW DIAGRAM




FIG. 10A

RU987-022

## HIRS LAYER 3 PROGRAM FLOW DIAGRAM




FIG. 10B



R0987-022

## RCVRQST - RECEIVE THE NEXT FILE REQUEST

RCVRQST		
SET UP CONTROL, REXPLI, AND CMSCMD DECLARES. DECLARE VARIABLES AND BUFFERS.		
READ THE FIRST/NEXT RECORD IN THE CONTROL FILE.		
YES \ IF END-OF-FILE WAS NOT REACHED, /NO		
CALL CMSCMD TO PERFORM A FILEDEF COMMAND FOR THE NEW INTERMEDIATE DELTA FILE.		CLOSE THE CONTROL FILE.
\ IF THE RETURN CODE FROM THE / YES \ FILEDEF COMMAND IS ZERO (0) / NO		SET RETURN CODE TO 1, EOF.
SET RETURN CODE TO 0, OKAY.	SET RETURN CODE TO 1, ERROR. DISPLAY ERROR MESSAGE.	
RETURN TO THE REQUEST RULE.		

218

FIG. 10C

R0987-022


FORMATTER 56 11/14 -  
TRANSLATOR PROGRAM

FIG. 11

R0987-022

## LOGIC FLOW OF TGIMU00




FIG. 12A

R0987-022

## LOGIC FLOW OF TGIMU00




FIG. 12B

R0987-022

## HIGH LEVEL FLOW DIAGRAM




FIG. 1

R0987-022




FIG. 2

R0987-022

## HPCS RECORD DESCRIPTION

FILE NAME: STSTOPOL

DESC NAME: SYSTEM TOPOLOGY DESCRIPTION

RECORD NAME: STDHEADR

DESC NAME: STD HEADER RECORD

CHARACTER	ZONED DEC	PACKED DEC	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X				3	001-003	ELMID	ELEMENT IDENTIFIER
X				2	004-005	RCDTP	RECORD TYPE
X				4	006-009	IDSYS	SYSTEM TYPE
X				7	010-016	SYNUM	SYSTEM NUMBER
X				8	017-024	DTELU	DATE LAST UPDATE
X				6	025-030	TMENT	TIME LAST UPDATE
X				3	031-033	WTCTN	WORLD TRADE COUNTRY
X				6	034-039	RLLVL	RULES LEVEL
X		X		4	040-043	BOXSD	BOX SHIP DATE
X				4	044-047	UPCID	UPGRADE CONTROL ID
X				4	048-051	PLUPC	PREV LEVEL UPCID
X				1	052-052	SPTYP	SERVICE PROCESSOR TYPE
X				48	053-100	FIL78	EXPANSION AREA

FIG. 3A

R0987-022

## HPCS RECORD DESCRIPTION

FILE NAME: STSTOPOL      DESC NAME: SYSTEM TOPOLOGY DESCRIPTION  
 RECORD NAME: STDELEMT    DESC NAME: STD ELEMENT RECORD

CHARACTER	ZONED DEC	PACKED DEC	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X				3	001-003	ELMID	ELEMENT IDENTIFIER
X				3	004-006	RCDTP	RECORD TYPE
X				4	006-009	ELMFR	PARENT ELEMENT IDENTIFIER
X				4	009-012	IDMAC	MACHINE TYPE
X				4	013-016	IDSNN	SALES MODEL
X				10	016-021	DVRPQ	DEVICE/RPQ CODE
X				4	022-031	BMNUM	BILL OF MATERIAL NUMBER
X				1	032-035	FIL04	FILLER
X				1	036-036	ELMTP	ELEMENT TYPE
X				1	037-037	ELMST	ELEMENT SUBTYPE
X				1	038-038	ELSCD	ELEMENT SOURCE CODE
X				9	039-047	MACSR	MACHINE SERIAL#/ORDER#
X	XX			4	048-052	CORDX	X-COORDINATE LOCATION
X				4	053-057	CORDY	Y-COORDINATE LOCATION
X				1	058-061	LOCDD	LOCATION DESCRIPTION
X				1	062-062	MGDOFF	MOUNTING GROUP OFFSET
X				1	063-063	DFSWA	DFCI SWITCH A SETTING
X				1	064-064	DFSWB	DFCI SWITCH B SETTING
X				1	065-065	DFTRA	DFCI TERMINATOR A STRING
X				1	066-066	DFTRB	DFCI TERMINATOR B STRING
X				1	067-067	DEVST	DEVICE STATUS
X				3	068-070	DRIVA	DRIVER-'A' STRING OR ONLY
X				3	071-073	DRIVB	DRIVER-'B' STRING
X				10	074-083	SDATA	S/370 ADDRESS DATA
X				1	084-084	IPLDC	IPL DEVICE
X				1	085-085	PSDVC	PRIMARY/SECONDARY DEVICE CODE
X				15	086-100	FIL16	FILLER -- EXPANSION AREA

FIG. 3B



R0987-022

## HPCS RECORD DESCRIPTION

FILE NAME: SYSTOPOL      DESC NAME: SYSTEM TOPOLOGY DESCRIPTION  
 RECORD NAME: STDCABLE    DESC NAME: STD CABLE RECORD

CHARACTER	ZONED DEC	PACKED DEC	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X X X X X X X X X X X				3 3 3 6 10 4 1 1 1 1	001-003 004-005 006-008 009-014 015-024 025-028 029-029 030-030 031-031	ELMID RCOTP MACID DVRPQ BMNUM FILO4 ELMTP ELMST ELSCD	ELEMENT IDENTIFIER RECORD TYPE ID OF MACHINE ORDER DEVICE/RPQ CODE BILL OF MATERIAL NUMBER FILLER ELEMENT TYPE ELEMENT SUBTYPE ELEMENT SOURCE CODE
X X				3 4 5 5	032-034 035-038 039-043 044-048	ELMFR LOCCD CORDX CORDY	'FROM' LOC DATA 'FROM' ELEMENT IDENTIFIER LOCATION DESCRIPTION X- COORDINATE LOCATION Y- COORDINATE LOCATION END 'FROM' LOC DATA
X X				3 4 5 5	049-051 052-055 056-060 061-065	ELMTO LOCCD CORDX CORDY	'TO' LOC DATA 'TO' ELEMENT IDENTIFIER LOCATION DESCRIPTION X- COORDINATE LOCATION Y- COORDINATE LOCATION END 'TO' LOC DATA
X X				3 4 5 5	066-068 069-072 073-077 078-082	ELMTO LOCCD CORDX CORDY	2ND 'TO' LOC DATA 'TO' ELEMENT IDENTIFIER LOCATION DESCRIPTION X- COORDINATE LOCATION Y- COORDINATE LOCATION END 2ND 'TO' LOC DATA
X X X					083-083 084-084 085-100	DEVST PSDVC FIL17	DEVICE STATUS PRIMARY/SECONDARY DEVICE CODE FILLER -- EXPANSION AREA

FIG. 3C

R0987-022

## HPCS RECORD DESCRIPTION

1.1.6 FILE NAME: ELEMDESC      DESC NAME: ELEMENT DESCRIPTION FILE

1.1.6.1 RECDRD NAME: LEVELCTL      DESC NAME: RELEASE LEVEL CONTROL RECORD

CHARACTER	ZONED DEC	PACKED DEC	BINARY	SIGNED	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X						1	001-001	RDTP	RECORD TYPE
X						4	002-005	FILO4	FILLER- EXPANSION AREA
X						15	006-020	FIL15	FILLER- TEXT AREA
X						6	021-026	RLLVL	RELEASE LEVEL
X						23	027-049	FIL23	FILLER- TEXT AREA
X						6	050-055	DEVNU	RULES LEVEL SPECIFY
X						195	056-250	FL195	FILLER

FIG. 4A

R0987-022

## HPCS RECORD DESCRIPTION

FILE NAME: ELEMDESC      DESC NAME: ELEMENT DESCRIPTION FILE

1.1.6.2 RECORD NAME: DEVTABLE      DESC NAME: DEVICE TO B/M CONVERTS TABLE

CHARACTER	ZONED DEC	PACKED DEC	BINARY	SIGNED	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X						1	001-001	RCOTP	RECORD TYPE
X						4	002-005	FILO4	FILLER- EXPANSION AREA
X						3	006-009	IDMAC	MACHINE TYPE
X	X					2	010-012	IDSMN	SALES MODEL
X						11	013-014	SEQNM	SEQUENCE NUMBER
							015-025	FIL11	EXPANSION AREA
225 BYTES---ARRAY OF 9 SETS OF DEVICE CODES									
X						6	026-	DVRPQ	DEVICE/RPQ CODE
X						10		BMSEQ	BILL OF MATERIAL SEQUENCE
X						7	-250	BMNUM	BILL OF MATERIAL NUMBER
								FIL07	EXPANSION AREA

FIG. 4B

R0987-022

## HPCS RECORD DESCRIPTION

FILE NAME: ELEMDESC      DESC NAME: ELEMENT DESCRIPTION FILE  
 RECORD NAME: BASELEMT    DESC NAME: BASIC ELEMENT RECORD

CHARACTER	ZONED DEC	PACKED DEC	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X	X			1	001-001	RCDTP	RECORD TYPE
X				4	002-005	FIL04	FILLER - EXPANSION AREA
X	X			10	006-015	BMNUM	BILL OF MATERIAL NUMBER
X				8	016-023	FIL10	EXPANSION AREA
X	X			2	024-025	FNLVL	FUNCTIONAL LEVEL
X				1	026-026	ELMTP	ELEMENT TYPE
X				1	027-027	ELMST	ELEMENT SUBTYPE
X				10	028-037	ELMMN	DESCRIPTIVE NAME
X				10	038-047	HPCDN	HPCS DEVICE NAME
X				10	048-057	ACCES	ACCESSORY PART NUMBER
	X			4	058-061	EXWDT	EXTERNAL WIDTH
	X			4	062-065	INWDT	INTERNAL WIDTH
	X			4	066-069	EHGHT	HEIGHT (EIA UNITS)
	X			4	068-072	MLGHT	LENGTH OR HEIGHT (MM)
	X			4	073-076	MDPTH	DEPTH (MM)
	X			4	077-080	KWGHT	WEIGHT (KILOGRAMS)
	X			3	081-083	PWRVL	POWER VALUE (KVA)
	X			4	084-087	MGOFF	MOUNTING GROUP OFFSET
	X			4	088-091	MCBIN	CABLE LGTH INCREM (MM)
	X			2	089-090	PWOUT	POWER OUTLETS COUNT
	X			2	091-092	ARMCT	DASD ARMS COUNT
	X			2	093-094	CPTCT	CONTROL OF PORT COUNT
	X			2	095-096	DEVCT	COUNT OF DEVICES CARD CAN DRIVE
	X			1	097-097	BUSCT	COUNT OF BUSES
	X			4	098-101	INTWL	INTERNAL WIRING LENGTH
	X			3	102-104	FIL03	FILLER - EXPANSION AREA
	X			2	105-106	FWCSN	FIRST WIDE CARD SLOT NUMBER
	X			1	107-107	SWDEV	SWITCHED DASD DEVICE FLAG
	X			1	108-108	TRMTP	TERMINATOR TYPE
	X			4	109-109	HPADD	DEVICE ADDED BY HPCS
	X			4	110-113	IDMAC	MACHINE TYPE (HPCS ADDS ONLY)
	X			4	114-116	IDSMN	SALES MODEL (HPCS ADDS ONLY)
	X			6	117-122	DVRPQ	DEVICE/RPQ CODE (HPCS ADDS ONLY)
	X			1	123-123	CBEXL	CABLE EXIT LOCATION
	X			1	124-124	TOWMT	TOWER MOUNTED DEVICE
	X			1	125-125	DPDCD	DELAYED POWER OFF CODE
	X			3	126-128	LVKVA	110V RACK KVA OVERRIDE
	X			3	129-131	COGRX	CENTER OF GRAVITY X COORDINATE
	X			3	132-134	COGRY	CENTER OF GRAVITY Y COORDINATE
	X			3	135-137	COGRZ	CENTER OF GRAVITY Z COORDINATE
	X			4	138-141	STCAP	DASD STORAGE CAPACITY
	X			13	142-154	FIL17	FILLER - EXPANSION AREA
				96	BYTES---ARRAY OF 6 SETS OF COORDINATES		
X	X			4	155-	LOCCD	LOCATION DESCRIPTION
				4		JAKNM	JACK NUMBER FOR PLUG
				4		CORDX	X- COORDINATE LOCATION
				4	-250	CORDY	Y- COORDINATE LOCATION
					END OF ARRAY		

FIG. 4C

R0987-022

## HPCS RECORD DESCRIPTION

FILE NAME: ELEMDESC      DESC NAME: ELEMENT DESCRIPTION FILE

RECORD NAME: COMMSPEC      DESC NAME: COMM SPECIFY CODE DEFINITION.

CHARACTER	ZONED DEC	PACKED DEC	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X				1	001-001	RDTP	RECORD TYPE
X				4	002-005	IDSYS	SYSTEM TYPE
X				3	006-007	SEQNM	SEQUENCE NUMBER
X				35	008-042	FIL35	FILLER AREA FOR KEY
208 BYTES---ARRAY OF 8 SETS OF COMMUNICATION LINES---							
X				3	043-	SPCPF	SPECIFY CODE PREFIX
X				1		FIL01	FILLER - EXPANSION AREA
X				1		ELEIF	ELECTRICAL INTERFACE
X				1		PROTO	COMMUNICATIONS PROTOCOL
X				1		CNNCT	CONNECTION 'TO' PARAMETER
X				1		LSCAT	LINE SPEED CATEGORY
X				1		CSSTP	COMMUNICATION SUBSYSTEM TYPE
X				1		FIL02	EXPANSION AREA
X				10		BMNUM	BILL OF MATERIAL NUMBER
X				06	-250	FIL06	FILLER - EXPANSION AREA
END OF ARRAY							

FIG. 4D

R0987-022

## HPCS RECORD DESCRIPTION

FILE NAME: ELEMDESC      DESC NAME: ELEMENT DESCRIPTION FILE  
 RECORD NAME: LNSPOCAT    DESC NAME: LINE SPEED CATEGORY RECORD

CHARACTER	ZONED DEC	PACKED DEC	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X				1	001-001	RDTP	RECORD TYPE
X				4	002-005	IDSYS	SYSTEM TYPE
X				2	006-007	SEQNM	SEQUENCE NUMBER
X				18	008-025	FI18	FILLER AREA FOR KEY
-----220 BYTES-----ARRAY OF 22 SETS OF LINE SPEED PARAMETERS-----							
X				1	026-	SPCSF	SPECIFY CODE PREFIX
X				1		LSCAT	LINE SPEED CATEGORY
X	X			4		LNSPD	LINE SPEED
X				4	-245	FI04	FILLER - EXPANSION AREA
-----END OF ARRAY-----							
X				05	246-250	FI05	FILLER - EXPANSION AREA

FIG. 4E

R0987-022

## HIRS RECORD DESCRIPTION

FILE NAME: COMCON TASK

DESC NAME: COMPONENT TASK FILE

RECORD NAME: CPTASKIT

DESC NAME: COMPONENT TASK INCLUDE

CHARACTER	ZONED DEC	PACKED DEC	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X				2	001-002	TTYPE	TASK TYPE TO EXECUTE
X				1	003-003	HANCD	HANDLING CODE
X				10	004-013	HPCDN	HPCS DEVICE NAME
X				1	014-014	ELMTP	ELEMENT TYPE
X				1	015-015	ELMST	ELEMENT SUBTYPE
X				1	016-016	FILL1	RESERVED -- EXPANSION AREA
X				1	017-017	GROUP	TASK GROUP FLAG (GROUPED IF "G")
X				4	018-021	TIXRF	TASK ID - CROSS REFERENCE NO.
X				3	022-024	TIGRP	TASK ID - GENERAL GROUPING NO.
X				8	025-032	FILL2	RESERVED -- EXPANSION AREA
X				1	033-033	PERSP	TASK PERSPECTIVE
X	X			3	034-036	GLSQN	GOAL SEQUENCE STEP NUMBER
X	X			3	037-039	UPDSQ	UPDATE SEQUENCE STEP NUMBER
X				1	040-040	STATE	TASK STATE
X				1	041-041	DIRET	TASK DIRECTION
X				1	042-042	POWST	POWER STATUS
X				1	043-043	SUBCP	SUB COMPONENT IDENTIFICATION
					044-	TCMTM	TASK COMPLETION TIME
X				3	044-046	TCMTP	PRIMARY TIME TO COMPLETE TASK
X				3	047-049	TCMTA	ALTERNATE TIME IF TASK IS IN A GROUP
X				1	050-050	MUPID	MODEL UPGRADE INDICATOR
X				10	051-060	PHPDN	PARENT DEVICE NAME
X				1	061-061	CABRL	CABLE RELATIONSHIP
X				1	062-062	HANLR	HANDLER CODE
X				1	063-063	CINTK	CHARACTERIZE INDEPENDENT TASK
X				1	064-064	CLASS	CLASS OF VALUES TO BE SET FOR TASK
X				1	065-065	SPCLS	SPECIAL CLASS OF VALUES TO BE SET
X				15	066-080	FILL5	RESERVED -- EXPANSION AREA

FIG. 5

R0987-022

## HIRS RECORD DESCRIPTION

FILE NAME: ITDELTA

DESC NAME: INTERMEDIATE DELTA FILE

RECORD NAME: ITDELTA

DESC NAME: INTERMEDIATE DELTA

CHARACTER	ZONED DEC	PACKED DEC	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X				2	001-002	TTYPE	TASK TYPE TO EXECUTE
X				1	003-003	HANCD	HANDLING CODE
	X			5	004-008	TSEQN	TASK SEQUENCE NUMBER
X					009-	TSKID	TASK IDENTIFICATION NUMBER
X				4	009-012	TIXRF	TASK ID- CROSS REFERENCE NUMBER
X				3	013-015	TIGRP	TASK ID- GENERAL GROUPING NUMBER
X				2	016-016	POWST	POWER STATUS
X				1	017-017	SUBCP	SUB COMPONENT CODE
					018-	TCMTM	TASK COMPLETION TIME
	X			3	018-020	TCMTP	PRIMARY TIME TO COMPLETE TASK
	X			3	021-023	TCMTA	ALTERNATE TIME IF TASK IS IN A GROUP
X				1	024-024	RPERM	REMOVE PERMANENTLY FLAG
X				1	025-025	HANLR	HANDLER CODE
X				1	026-026	PERSP	TASK PERSPECTIVE
X				3	027-029	GLSQN	GOAL SEQUENCE STEP NUMBER
X				3	030-032	UPDSQ	UPDATE SEQUENCE STEP NUMBER
X				1	033-033	STATE	TASK STATE
X				1	034-034	DIRET	TASK DIRECTION
X				1	035-035	MUPID	MODEL UPGRADE INDICATOR
					036-	HPAGE	PARENTAGE
X				3	036-038	ELIL1	ELEMENT IDENTIFIER LEVEL 1 (RACK)
X				4	039-042	LOCL1	LOCATION CODE LEVEL 1
X				3	043-045	ELIL2	ELEMENT IDENTIFIER LEVEL 2 (DEVICE)
	X			5	046-050	CORY2	COORDINATE Y LEVEL 2
X				4	051-054	LOCL2	LOCATION CODE LEVEL 2
X				3	055-057	ELIL3	ELEMENT IDENTIFIER LEVEL 3 (CARD)
	X			5	058-062	CORY3	COORDINATE Y LEVEL 3
X				4	063-066	LOCL3	LOCATION CODE LEVEL 3
X				3	067-069	ELIL4	ELEMENT IDENTIFIER LEVEL 4 (CABLE)
	X			5	070-074	CORY4	COORDINATE Y LEVEL 4
X				4	075-078	LOCL4	LOCATION CODE LEVEL 4
X				6	079-084	CPFC4	CABLE'S PARENT FEATURE CODE NUMBER
X				1	085-085	CABRL	CABLE RELATIONSHIP
X				1	086-086	NCBLE	NUMBER OF CABLE ENDS
X				1	087-087	GROUP	TASK GROUP FLAG (GROUPED IF "G")
X				1	088-088	CLASS	CLASS OF VALUES TO BE SET FOR TASK
X				1	089-089	SPLCS	SPECIAL CLASS OF VALUES TO BE SET
X				31	090-120	FILLR	RESERVED -- EXPANSION AREA

THE REMAINDER OF THIS RECORD FORMAT CONSISTS OF THE STDELEMENT RECORD FROM THE SYSTOPOL FILE, PLEASE REFER TO IT FOR THE REST OF THE FORMAT.

FIG. 6



R0987-022

NOVEMBER 3RD, 1987 4:52 P.M.

FILE: "TRANSLAT TABLE A"

XXXXXXXXXXXXXXXXXXXXX TASK MODULE CHARTS XXXXXXXXXXXXXXXXXXXXXXXX

"K" = KABLING CHART FOR PSEUDO TASKS

	B1	B3	B6
PNLC1K	1C	123	122
PNLC2K	2C		
PNCL1K	1C		

FIG. 7A

(ELMTP &amp; ELMST FIELDS)

B1 - DFCI OR BUS EXTEND CABLE

B3 - COMMUNICATIONS CABLE

B6 - TWIN-AX CABLE

"C" = CARD CHART FOR PSEUDO TASK EXTENSIONS

	6019	6018	6010	
PNLC1C	114	124	121	1P
PNLC2C	214	224		2P
PNCL1C	114	124	121	1P

FIG. 7B

(OVRPQ FIELD OF PARENT ELEMENT)

6018 - BUS EXTEND DRIVER CARD

6019 - BUS EXTEND RECY'R CARD

--- - ELEMENTS WHICH ARE NOT CARDS

"P" = PORT CHART

	PWSI	PWSO	DIO1	DOO1	DCO1	DCO2	DCO3	DCO4
PNLC1P			111	121	111	111	111	111
PNLC2P			211	221	211	211	211	211
PNCL1P			111	121	111	111	111	111
ROSC1P					110	120	130	140
ADSC1P					110	120	130	140
RDDC1P			110	120				
ADDC1P			110	120				
RDDC2P			210	220				
ADDC2P			210	220				
RDDC3P			310	320				
ADDC3P			310	320				
RDDC4P			41L	42L				
ADDC4P			41L	42L				
RRSC1P	110	120						
ARSC1P	110	120						

(LOCPR/LOCTO FIELD)

PWSI - PWR SEQ (IN)

PWSO - PWR SEQ (OUT)

DIO1 - DFCI (IN)

DOO1 - DFCI (OUT)

DCO1 - SIGNAL PORT 1

DCO2 - SIGNAL PORT 1

DCO3 - SIGNAL PORT 1

DCO4 - SIGNAL PORT 1

FIG. 7C

"L" = LOCATION CHART

	L	R
RDPC7L	701	702
ADPC7L	701	702
RDDT4L	401	402
ADDT4L	401	402
RDEV6L	601	602
ADEV6L	601	602
RDDC41L	411	412
ADDC41L	411	412
RDDC42L	421	422
ADDC42L	421	422
SDAS5L	551	552
VDCT4L	401	402

(LOCCD FIELD)

L - LEFT MOUNTED LOCATION

R - RIGHT MOUNTED LOCATION

FIG. 7D

"M" = MODEL CHART

	B10	B20	B30	B40	F10	F20	F30	F40	F50
RDBC1M			100	200					
ADBC1M			100	200					

(IDSMN FIELD)

FIG. 7E

REF CHART	RCDT1 V	ACDT1 V	RCDT2 V	ACDT2 V
6030	110	110		
XXXX	111	111		
4004	112	112		
4008	113	113		
4012	114	114		
XXXX	115	115		
XXXX	116	116		
XXXX	117	117		
XXXX	118	118		
XXXX	119	119		
2500	120	120		
2501	121	121		
2502	122	122		
2503	123	123		
XXXX	124	124		
XXXX	125	125		
XXXX	126	126		
XXXX	127	127		
XXXX	128	128		
2504	129	129		
2505	130	130		
2506	131	131		
AF12			210	210
AF04			211	211

FIG. 7F

```

COMM  CNTLR
      (ENHANCED)
      4M  STORAGE
      8M
      12M
      16M
      32M
      64M
      128M
      256M STORAGE
      IMPI 1
      IMPI 2
      IMPI 3
      IMPI 4
      FA1
      FA2
      FA3
      FA4
      FA5
      C1 {BA/SP1}
      C2 {BA/SP2}
      C3 {BA}
      AF 1.2 {4532}
      AF 0.7 {4591}

```

CHART	ADT	
	W	W
6018	316	316
6019	317	317
6010	310	310
6040	311	311
6034	312	312
6050	313	313
6031	314	314
6032	315	315

FIG. 7G

```
BUS EXT DVR
BUS EXT REV
DFCI CNTLR
W.S. CNTLR
LAN ADPTR
W.S. CNTLR
SDLC COMM
ASYC COMM
```

NO CHART	R		A		R		A	
	6010	6011	410	411	410	411	51X	51X
6019	610	611						
6018	611							
6010			410	411	410	411		
6040			411	412	412			
6034			412				51X	51X
6050							52X	52X
6031							53X	53X
6032								

FIG. 7H

```
BUS EXT DVR
BUS EXT RCY
DFCI CNTLR
W.S. CNTLR
LAN ADPTR
W.S. CNTLR
SDLC COMM
ASYC COMM
```

	C 0 1	C 0 2	C 0 3	C 0 4
RCSC51X	510	511		
ACSC51X	510	511		
RCSC52X	512	513		
ACSC52X	512	513		
RCSC53X	514	515	516	517
ACSC53X	514	515	516	517

```
(LOC FM FIELD)
CC01 - PORT 1
CC02 - PORT 2
CC03 - PORT 3
CC04 - PORT 4
```

FIG. 7I

	0	1	2	3	4	5	6	7
SDAS13	100	110	120	130	140	150	160	170
SDAS23	100	110	120	130	140	150	160	170
SDAS33	100	110	120	130	140	150	160	170
SDAS43	400	410	420	430	440	450	460	470
SDAS53	500	510	520	530	540	550	560	570
SDAS63	500	510	520	530	540	550	560	570

```

(DFSWA FIELD)
0 - DFCI ADDRESS 0
1 - DFCI ADDRESS 1
2 - DFCI ADDRESS 2
3 - DFCI ADDRESS 3
4 - DFCI ADDRESS 4
5 - DFCI ADDRESS 5
6 - DFCI ADDRESS 6
7 - DFCI ADDRESS 7

```

FIG. 7J

R0987-022

## HIRS RECORD DESCRIPTION

FILE NAME: DELTAHHF

DESC NAME: DELTA HARDWARE HANDLING FILE

RECORD NAME: DELTAHHI

DESC NAME: DELTA HARDWARE HANDLING

CHARACTER	ZONED DEC	PACKED DEC	DECIMALS	FIELD LENGTH	POSITIONS FR-TO	FIELD NAME	FIELD DESCRIPTIVE NAME
X				2	001-002	TTYPE	TASK TYPE TO EXECUTE
X				1	003-003	HANCD	HANDLING CODE
	X			5	004-008	TSEQN	TASK SEQUENCE NUMBER
					009-	TSKID	TASK IDENTIFICATION NUMBER
X				4	009-012	TIXRF	TASK ID- CROSS REFERENCE NUMBER
X				3	013-015	TIGRP	TASK ID- GENERAL GROUPING NUMBER
X				1	016-016	POWST	POWER STATUS
X				1	017-017	SUBCP	SUB COMPONENT INDICATOR
					018-	TCMTM	TASK COMPLETION TIME
	X			3	018-020	TCMTP	PRIMARY TIME TO COMPLETE TASK
	X			3	021-023	TCMTA	ALTERNATE TIME IF TASK IS IN A GROUP
X				1	024-024	RPERM	REMOVE PERMANENTLY FLAG
X				1	025-025	HANLR	HANDLER CODE
					026-	HPAGE	PARENTAGE
X				3	026-028	ELIL1	ELEMENT IDENTIFIER LEVEL 1 (RACK)
X				4	029-032	LOCL1	LOCATION CODE LEVEL 1
X				3	033-035	ELIL2	ELEMENT IDENTIFIER LEVEL 2 (DEVICE)
	X			5	036-040	CORY2	COORDINATE Y LEVEL 2
X				4	041-044	LOCL2	LOCATION CODE LEVEL 2
X				3	045-047	ELIL3	ELEMENT IDENTIFIER LEVEL 3 (CARD)
	X			5	048-052	CORY3	COORDINATE Y LEVEL 3
X				4	053-056	LOCL3	LOCATION CODE LEVEL 3
X				3	057-059	ELIL4	ELEMENT IDENTIFIER LEVEL 4 (CABLE)
	X			5	060-064	CORY4	COORDINATE Y LEVEL 4
X				4	065-068	LOCL4	LOCATION CODE LEVEL 4
X				6	069-074	CPFC4	CABLE'S PARENT FEATURE CODE NUMBER
X				1	075-075	NCBLE	NUMBER OF CABLE ENDS
X				3	076-078	GRAPHID	GRAPHICS MODULE ID NUMBER FOR PABS
X				1	079-079	GROUP	TASK GROUP FLAG (GROUPED IF "G")
X				1	080-080	CLASS	CLASS OF VALUES TO BE SET FOR TASK
X				1	081-081	SPCLS	SPECIAL CLASS OF VALUES TO BE SET
X				19	082-100	FILLR	RESERVED -- EXPANSION AREA

THE REMAINDER OF THIS RECORD FORMAT CONSISTS OF THE STDELEMT RECORD FROM THE SYSTOPOL FILE.

FIG. 8

R0987-022

## LOGIC FLOW OF HIRSU00




FIG. 9A

R0987-022

## LOGIC FLOW OF HIRSU00




FIG. 9B

R0987-022

## LOGIC FLOW OF HIRSU00




FIG. 9C

R0987-022

## LOGIC FLOW OF HIRSU00




FIG. 9D

R0987-022

## HIRS LAYER 3 PROGRAM FLOW DIAGRAM




FIG. 10A



RU987-022

## HIRS LAYER 3 PROGRAM FLOW DIAGRAM




FIG. 10B

R0987-022

## RCVRQST - RECEIVE THE NEXT FILE REQUEST

RCVRQST		
SET UP CONTROL, REXPLI, AND CMSCMD DECLARES. DECLARE VARIABLES AND BUFFERS.		
READ THE FIRST/NEXT RECORD IN THE CONTROL FILE.		
YES \ IF END-OF-FILE WAS NOT REACHED,		/NO
CALL CMSCMD TO PERFORM A FILEDEF COMMAND FOR THE NEW INTERMEDIATE DELTA FILE.		CLOSE THE CONTROL FILE.
\ IF THE RETURN CODE FROM THE YES \ FILEDEF COMMAND IS ZERO (0) / NO		SET RETURN CODE TO 1, EOF.
SET RETURN CODE TO 0, OKAY.	SET RETURN CODE TO 1, ERROR. DISPLAY ERROR MESSAGE.	
RETURN TO THE REQUEST RULE.		

218

FIG. 10C

R0987-022


FORMATTER 56 11/14 -  
TRANSLATOR PROGRAM

FIG. 11

R0987-022

## LOGIC FLOW OF TGIMU00




FIG. 12A

R0987-022

## LOGIC FLOW OF TGIMU00




FIG. 12B



(19)



Europäisches Patentamt  
European Patent Office  
Office européen des brevets



(11) Publication number:

**0 317 465 A3**

(12)

**EUROPEAN PATENT APPLICATION**(21) Application number: **88480030.1**(51) Int. Cl.<sup>5</sup>: **G06F 3/023, G06F 1/00**(22) Date of filing: **13.09.88**(30) Priority: **18.11.87 US 122295**(43) Date of publication of application:  
**24.05.89 Bulletin 89/21**(84) Designated Contracting States:  
**DE FR GB**(88) Date of deferred publication of the search report:  
**05.08.92 Bulletin 92/32**(71) Applicant: **International Business Machines Corporation**  
**Old Orchard Road**  
**Armonk, N.Y. 10504(US)**(72) Inventor: **Allen, LindaMay Patterson**  
**705 14th St. N.E.**  
**Rochester MN 55904(US)**  
Inventor: **Elshaug, Ronald George**  
**5601 North Highway 63 Lot No.65**  
**Rochester MN 55904(US)**  
Inventor: **Hamey, Carrie Lynn**  
**1856 Terracewood Drive N.W.**  
**Rochester MN 55901(US)**  
Inventor: **Rollings, Glen Everett**  
**1537 Kings Court, S.E.**  
**Rochester MN 55904(US)**  
Inventor: **Lemmon, Wayne Lawrence**  
**2227 14th Avenue N.W.**  
**Rochester MN 55901(US)**  
Inventor: **Nordstrom, Michael Lawrence**  
**715 6th Street S.W.**  
**Oronoco, MN 55960(US)**  
Inventor: **Miller, Irwin**  
**1440 Willow Lane S.W.**

**Rochester MN 55902(US)**  
Inventor: **Schablitsky, James Allen**  
**Rte 1, Box 102**  
**Kasson MN 55944(US)**  
Inventor: **Steinman, Anthony Victor**  
**1412 Windsor Chase Drive S.W.**  
**Rochester MN 55902(US)**  
Inventor: **Shanklin, Johnnie Dean**  
**2115 8th Avenue N.E.**  
**Rochester MN 55904(US)**  
Inventor: **Taylor, Deanna Christine**  
**2630 11th Avenue N.W.**  
**Rochester MN 55901(US)**  
Inventor: **Walberg, Darrel Clifford**  
**404 24th Street S.W.**  
**Rochester MN 55902(US)**  
Inventor: **Miller, Irwin Lionel**  
**RR 1, Box 639**  
**Pine Island MN 55963(US)**  
Inventor: **Suther III, Thomas Wilson**  
**Box 299**  
**Oronoco Minnesota 55960(US)**  
Inventor: **Wojtczak, Eugene Paul**  
**510 26th Street**  
**N.W.Rochester Minnesota 55901(US)**  
Inventor: **Murray, Gerald David**  
**1817 16th Street**  
**N.W.Rochester Minnesota 55901(US)**  
Inventor: **Peterson, LaVern Fred**  
**2108 9th Street**  
**N.E.Rochester Minnesota 55904(US)**

(74) Representative: **Vekemans, André**  
**Compagnie IBM France Département de**  
**Propriété Intellectuelle**  
**F-06610 La Gaude(FR)**

(54) Customized instruction generator.

(57) Customized instructions for installation of a device having multiple variable components is described, and are generated by an instruction generator program. A device description file lists a desired set of components for the device. Each of the com-

ponents is broken down into one or more installation tasks, and the tasks are sequenced in a desired order for installation of the device. Text and graphic modules for inclusion in the instructions are varied based on the physical characteristics of the compo-

nents, and their interconnection. Scaled line drawings are also generated based on information about each component and its placement in the device.




FIG. 2





European Patent  
Office

## EUROPEAN SEARCH REPORT

Application Number

EP 88 48 0030

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int. Cl.4)
X	J. MC DERMOTT 'R1: A rule-based configurer of computer systems.' Apr 11 1980, CARNEGIE-MELLON UNIVERSITY, US * abstract * * page 7, line 19 - page 7, line 30 * * figure 2-1 * * page 11, line 1 - page 11, line 9 * * page 9, line 23 - page 10, line 9 * * page 2, line 13 - page 2, line 21 * * page 12, line 21 - page 12, line 26 * * page 19, line 1 - page 19, line 9 * * page 1, line 1 - page 1, line 9 * ----	1-4, 8, 10	G06F3/023 G06F1/00
A	US-A-4 591 983 (J.S. BENNETT EL AL.) * column 3, line 27 - column 4, line 60; figure 1 * ----	1, 4, 10	
A	A. KRAFT 'XCON, An expert configuration system at DEC. Pages 41-49.' 1984, THE AI BUSINESS, THE MIT PRESS, CAMBRIDGE US * page 42, line 6 - line 16 * * page 44, line 29 - line 34 * -----	1, 10, 8	
			TECHNICAL FIELDS SEARCHED (Int. Cl.4)
			G06F
The present search report has been drawn up for all claims			
Place of search THE HAGUE		Date of completion of the search 25 MAY 1992	Examiner SCHARFENBERGER B.
CATEGORY OF CITED DOCUMENTS		I : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons ----- A : member of the same patent family, corresponding document	
X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document			

EPO FORM 1503 (11.81) (P.0001)

**THIS PAGE BLANK (USPTO)**

**This Page is Inserted by IFW Indexing and Scanning  
Operations and is not part of the Official Record**

## **BEST AVAILABLE IMAGES**

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ **BLACK BORDERS**
- ☐ **IMAGE CUT OFF AT TOP, BOTTOM OR SIDES**
- ☐ **FADED TEXT OR DRAWING**
- ☐ **BLURRED OR ILLEGIBLE TEXT OR DRAWING**
- ☐ **SKEWED/SLANTED IMAGES**
- ☐ **COLOR OR BLACK AND WHITE PHOTOGRAPHS**
- ☐ **GRAY SCALE DOCUMENTS**
- ☐ **LINES OR MARKS ON ORIGINAL DOCUMENT**
- ☐ **REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY**
- ☐ **OTHER:** \_\_\_\_\_

**IMAGES ARE BEST AVAILABLE COPY.**

**As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.**

**This Page Blank (uspto)**